



Hitachi CB 500 Blade Servers Support Matrix

Note: Configurations added since the last matrix will be shown in **red** text.

Introduction

Use this interoperability matrix to check whether a proposed customer configuration is supported. Each tab contains a set of components that together comprise an HDS-supported solution. This includes server model, operating system (OS) and maintenance release, host bus adapter (HBA), HBA driver, storage area network (SAN) switches, both Fibre channel (FC) and Fibre channel over Ethernet (FCoE).

In the sample datapath below, a customer configuration is supported if that particular server, HBA and driver, switch and switch firmware combinations all appear on the CB 540A A1 support matrix.

Note: The arrays supported now include the **VSP E990**.

These HV storage arrays are always supported:

HUS 100, HUS VM, VSP, VSP G1x00, F1500, **VSP E990**, Gxx0, Fxx0, VSP F700, F900, G700, G900, F350, F370, G350, G370, VSP 5100, 5100H, 5500, 5500H.

3rd party array support is determined by the vendor of those arrays.

For example: A Hitachi CB 540A A1 server running RedHat Enterprise Linux (RHEL) 6.5 that has an Emulex LPe1205A-HI HBA using driver v8.3.7.21.4p connected to a Hitachi Blade Server Switch - 5460 with FOS v7.2.1 installed.

If a combination does not appear on the support matrix, the customer's Hitachi Vantara Sales Engineer (SE) or other HV field service employee must submit an Interoperability Support Request in order to gain support for the new configuration.

Legal Disclaimer

This information is subject to change without notice. The information contained in this document is provided by HV for general information purposes only and is based on information as of the date of distribution (indicated by the date above). HV makes no express or implied warranties of any kind whatsoever regarding the contents of this Document or the performance of the products referred to in these documents and HV expressly disclaims all warranties including, without limitation, the implied warranties of satisfactory quality, merchantability or fitness for a particular purpose, the statutory warranty against infringement, and any warranty of title. HV will have no liability whatsoever for any direct loss or damage (but excluding any liability for death, personal injury or fraudulent misrepresentation) or for any indirect, special, incidental or consequential damages, including but not limited to loss of data or records, lost profits or other economic loss, arising out of or in connection with the use of this information even if such loss was foreseeable or HV had been advised of the possibility of such loss.

HDS support for Hitachi CB 520H A1|B1 (GGAGC0A1) | (GGAGC0B1) Server Blades

OS	Version	HVM/LPAR support	HVM/LPAR Manager version	SVP, Integrated firmware, EFI, BMC versions	HBA/CNA model	HBA/CNA driver
RedHat Enterprise Linux (RHEL)	RHEL 6.10 (X64)	Yes	02-66 or higher	A0107 or higher 01-39 or higher 01-39 or higher 02-12 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.6.19.2920
	RHEL 7.0 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v8.3.7.34.3p
	RHEL 7.1 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v10.2.8021.1
		Yes	02-40 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3116
	RHEL 7.2 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v10.7.0.1
		Yes	02-45 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3160
VMWare	VMWare 6.0 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2428
	VMWare 6.0 U1 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2446
	VMWare 6.0 U2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.19.96
	VMWare 6.0 U3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.140
	VMWare 6.5 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.112
	VMWare 6.5 U1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled (v11.1.196.3)
		No	N/A	N/A	Hitachi HFCE0802	v10.42.20.140
Windows	Windows Server 2012	No	N/A	N/A	Emulex LPe1205A-HI	v2.72.012.001
		No	N/A	N/A	Emulex OCm11104-F2	v2.72.012.001
		Yes	01-30 or higher	A0107 or higher 01-39 or higher 01-39 or higher 02-12 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.3.8.1970
	Windows Server 2012 R2	No	N/A	N/A	Emulex LPe1205A-HI	v2.74.214.004
		Yes	01-90 or higher	A0107 or higher 01-39 or higher 01-39 or higher 02-12 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.4.8.1690
	Citrix XENServer	XENServer 6.0 (X64)	No	N/A	N/A	Emulex LPe1205A-HI
XENServer 6.0.2 (X64)		No	N/A	N/A	Emulex LPe1205A-HI	Bundled
XENServer 6.1 (X64)		No	N/A	N/A	Emulex LPe1205A-HI	v8.3.5.77.1p
XENServer 6.2 (X64)		No	N/A	N/A	Emulex LPe1205A-HI	v8.3.7.14

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2f	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2f, v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148, 9222i, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1)	
	9148S, 9706	v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9250i	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9396S	v6.2(13), v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9710	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9396T (32Gb)	v8.3(1) - v8.3(2)	
	9706 (32Gb), 9710 (32Gb)	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
Hitachi	Blade Server Switch - 5460	v7.4.2c	
	Blade Server Switch - 6546	v8.1.2b	

3rd Party PCIe card support	
Blade Model	PCIe card
CB 500 Expansion Blade (GG-ES3PCB1X1-Y.P)	Brocade 1020
	Emulex LPe12002
	Emulex LPe16002B
	Fusion-io ioDrive2
	HGST Ultrastar SN150 (1.6TB/3.2TB)
	Mellanox MHQH29-XTC
	NVIDIA Grid K2
	QLogic QLE2562
	QLogic QLE2564

OS Server Certification	Link to the vendor HCL
OS	
RedHat Enterprise Linux (RHEL)	RedHat Customer Portal
SuSE Linux Enterprise Server (SLES)	SUSE YES Certification
Vmware	VMWare Compatibility Guide
Windows	Windows Server Catalog
Citrix XenServer	Citrix HCL

HDS support for Hitachi CB 520H A2|B2 (GG-RV3XGC0A2X1-Y) | (GG-RV3XGC0B2X1-Y) Server Blades

OS	Version	HVM/LPAR support	HVM/LPAR Manager version	SVP, Integrated firmware, EFI, BMC versions	HBA/CNA model	HBA/CNA driver	
RedHat Enterprise Linux (RHEL)	RHEL 6.10 (X64)	Yes	02-66 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE0802-M, HFCE0804-M (CB 520H B2 only)	v4.6.19.2920	
		Yes	02-66 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE1602-M (CB 520H B2 only)	v4.6.19.2920	
	RHEL 7.1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v10.2.8021.1	
		No	N/A	N/A	Emulex LPm16002B-HI	v10.2.8021.1	
		Yes	02-40 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3116	
		Yes	02-40 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE1602-M (CB 520H B2 only)	v4.7.18.3116	
	RHEL 7.2 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v10.7.0.1	
		Yes	02-45 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3160	
		Yes	02-45 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE1602-M (CB 520H B2 only)	v4.7.18.3160	
	RHEL 7.3 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v11.1.0.2	
		No	N/A	N/A	Emulex LPm16002B-HI	v11.1.0.2	
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.7.21.4252	
		No	N/A	N/A	Hitachi HFCE1602-M (CB 520H B2 only)	v4.7.21.4252	
	SuSE Linux Enterprise Server (SLES)	SLES 12 (X64)	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.12.18.3146
	VMWare	VMWare 6.0 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled
No			N/A	N/A	Emulex LPm16002B-HI (CB 520H B2 only)	Bundled	
No			N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2428	
No			N/A	N/A	Hitachi HFCE1602-M (CB 520H B2 only)	v10.42.19.96	
VMWare 6.0 U1 (X64)		No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled	
		No	N/A	N/A	Emulex LPm16002B-HI (CB 520H B2 only)	Bundled	
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2446	
		No	N/A	N/A	Hitachi HFCE1602-M (CB 520H B2 only)	v10.42.19.96	
VMWare 6.0 U2 (X64)		No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled	
		No	N/A	N/A	Emulex LPm16002B-HI (CB 520H B2 only)	Bundled	
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.19.96	
		No	N/A	N/A	Hitachi HFCE1602-M (CB 520H B2 only)	v10.42.19.96	

	VMWare 6.0 U3 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled	
		No	N/A	N/A	Emulex LPm16002B-HI (CB 520H B2 only)	Bundled	
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.140	
		No	N/A	N/A	Hitachi HFCE1602-M (CB 520H B2 only)	v10.42.20.140	
	VMWare 6.5 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled	
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.112	
	VMWare 6.5 U1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled (v11.1.196.3)	
		No	N/A	N/A	Hitachi HFCE0802	v10.42.20.140	
	Windows	Windows Server 2012	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v2.76.002.001
			Yes	01-60 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.3.8.1970
Yes			02-10 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE1602-M (CB 520H B2 only)	v4.3.8.1970	
Windows Server 2012 R2		No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v2.74.214.004	
		No	N/A	N/A	Emulex LPm16002B-HI (CB 520H B2 only)	v2.76.002.001	
		Yes	01-70 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.4.8.1690	
		Yes	02-10 or higher	A0160 or higher 04-15 or higher 04-11 or higher 10-23 or higher	Hitachi HFCE1602-M (CB 520H B2 only)	v4.4.8.1970	
Citrix XENServer		XENServer 6.1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v8.3.5.77.1p
	XENServer 6.2 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v8.3.7.14	
	XENServer 6.5 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v10.2.340.0	
	XENServer 7.0 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v11.0.0.12	
	XENServer 7.1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled	

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2f	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2f, v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.2.0, and v8.2.1 are not supported.

Cisco	9148, 9222i, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1)	
	9148S, 9706	v6.2(17) - v6.2(29) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9250i	v6.2(17) - v6.2(29) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9396S	v6.2(13), v6.2(17) - v6.2(29) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9710	v6.2(17) - v6.2(29) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9396T (32Gb)	v8.3(1) - v8.3(2)	
	9706 (32Gb), 9710 (32Gb)	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
Hitachi	Blade Server Switch - 5460	v7.4.2c	
	Blade Server Switch - 6546	v8.1.2b	

3rd Party PCIe card support	
Blade Model	PCIe card
CB 500 Expansion Blade (GG-RV3XGC0B2X1-Y)	Brocade 1020
	Emulex LPe12002
	Emulex LPe16002B
	Fusion-io ioDrive2
	HGST Ultrastar SN150 (1.6TB/3.2TB)
	Mellanox MHQH29-XTC
	NVIDIA Grid K2
	QLogic QLE2562
	QLogic QLE2564

OS Server Certification	Link to the vendor HCL
OS	
RedHat Enterprise Linux (RHEL)	RedHat Customer Portal
SuSE Linux Enterprise Server (SLES)	SUSE YES Certification
Vmware	VMWare Compatibility Guide
Windows	Windows Server Catalog
Citrix XenServer	Citrix HCL

HDS support for Hitachi CB 520H B4 (GG-RV3XGC0B4X1-Y) Server Blades

OS	Version	HVM/LPAR support	HVM/LPAR Manager version	SVP, Integrated firmware, BMC, EFI versions	HBA/CNA model	HBA/CNA driver
RedHat Enterprise Linux (RHEL)	RHEL 6.9 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.2.156.38
		No	N/A	N/A	Emulex LPm16002B-HI	v11.2.156.38
		Yes	02-59 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.6.18.2904
		Yes	02-59 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.6.18.2904
	RHEL 6.10 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.12
		No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.12
		Yes	02-66 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.6.19.2920
		Yes	02-66 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.6.19.2920
	RHEL 7.2 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v10.7.0.1
		No	N/A	N/A	Emulex LPm16002B-HI	v10.7.0.1
		Yes	02-50 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3160
		Yes	02-50 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.7.18.3160
	RHEL 7.3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.1.0.2
		No	N/A	N/A	Emulex LPm16002B-HI	v11.1.0.2
		Yes	02-58 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.21.4252
		Yes	02-58 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.7.21.4252
RHEL 7.4 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.2.156.38	
	No	N/A	N/A	Emulex LPm16002B-HI	v11.2.156.38	
	Yes	02-62 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.21.4294	
	Yes	02-62 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.7.21.4294	
RHEL 7.5 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.12	
	No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.12	
	Yes	02-64 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4328	
	Yes	02-64 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.7.22.4328	

RHEL 7.6 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.15	
	No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.15	
	Yes	02-64 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4328	
	Yes	02-64 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.7.22.4328	
RHEL 7.7 (X64)	Yes	02-69 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4346	
	Yes	02-69 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.7.22.4346	
RHEL 8.1 (X64)	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.8.22.4354	
	No	N/A	N/A	Hitachi HFCE1602-M	v4.8.22.4354	
SuSE Linux Enterprise Server (SLES)	SLES 12 (X64)	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.12.18.3146
		No	N/A	N/A	Hitachi HFCE1602-M	v4.12.18.3146
	SLES 12 SP1 (X64)	No	N/A	N/A	Emulex LPm16002B-HI	v10.5.0.2
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.12.20.4110
	Yes	02-58 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.12.20.4110	
	SLES 12 SP2 (X64)	Yes	02-58 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.12.21.4284
	SLES 12 SP4 (X64)	Yes	02-69 or higher	A0305 or higher 10-03 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.12.22.4340
	SLES 12 SP5 (X64)	No	N/A	N/A	Hitachi HFCE1602-M	v4.12.22.4346
SLES 15 SP1 (X64)	No	N/A	N/A	Hitachi HFCE1602-M	v4.15.22.4342	
VMWare	VMWare 6.0 U1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2446
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.19.96
	VMWare 6.0 U2 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.19.96
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.19.96
	VMWare 6.0 U3 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.140
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.140
	VMWare 6.5 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.112
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.112
VMWare 6.5 U1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled (v11.1.196.3)	
	No	N/A	N/A	Emulex LPm16002B-HI	Bundled (v11.1.196.3)	
	No	N/A	N/A	Hitachi HFCE0802	v10.42.20.140	
	No	N/A	N/A	Hitachi HFCE1602	v10.42.20.140	

	VMWare 6.5 U2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802	v10.42.20.162
		No	N/A	N/A	Hitachi HFCE1602	v10.42.20.162
	VMWare 6.5 U3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.1.196.3
		No	N/A	N/A	Emulex LPm16002B-HI	v11.1.196.3
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172
	VMWare 6.7 U1 (X64)	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
		No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0
		No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172
	VMWare 6.7 U2 (X64)	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
		No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0
		No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172
	VMWare 6.7 U3 (X64)	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
No		N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0	
No		N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0	
No		N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172	
Windows	Windows Server 2012	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v2.76.002.001
		No	N/A	N/A	Emulex LPm16002B-HI	v2.76.002.001
		Yes	02-50 or higher	A0305 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.3.8.1970
		Yes	02-50 or higher	A0305 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.3.8.1970
	Windows Server 2012 R2	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v2.76.002.001
		No	N/A	N/A	Emulex LPm16002B-HI	v2.76.002.001
		Yes	02-50 or higher	A0305 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.4.8.1690
		Yes	02-50 or higher	A0305 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.4.8.1970
	Windows Server 2016	No	N/A	N/A	Emulex LPe1205A-HI	v11.0.247.8000
		No	N/A	N/A	Emulex LPm16002B-HI	v11.0.247.8000
		Yes	02-56 or higher	A0305 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.5.8.2240
		Yes	02-56 or higher	A0305 or higher 10-03 or higher 10-03 or higher	Hitachi HFCE1602-M	v4.5.8.2240

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2f	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2f, v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148, 9222i, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1)	
	9148S, 9706	v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9250i	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9396S	v6.2(13), v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9710	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9396T (32Gb)	v8.3(1) - v8.3(2)	
	9706 (32Gb), 9710 (32Gb)	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.	
Hitachi	Blade Server Switch - 5460	v7.4.2c	
	Blade Server Switch - 6546	v8.1.2b	

3rd Party PCIe card support	
Blade Model	PCIe card
CB 500 Expansion Blade (GG-RV3XGC0B2X1-Y)	Brocade 1020
	Emulex LPe12002
	Emulex LPe16002B
	Fusion-io ioDrive2
	HGST Ultrastar SN150 (1.6TB/3.2TB)
	Mellanox MHQH29-XTC
	NVIDIA Grid K2
	QLogic QLE2562
	QLogic QLE2564

OS Server Certification	Link to the vendor HCL
OS	
RedHat Enterprise Linux (RHEL)	RedHat Customer Portal
Vmware	VMWare Compatibility Guide
Windows	Windows Server Catalog

HDS support for Hitachi CB 520H B3 (GG-RV3XGC0B3X1-Y) Server Blades

OS	Version	HVM/LPAR support	HVM/LPAR Manager version	SVP, Integrated firmware, BMC, EFI versions	HBA/CNA model	HBA/CNA driver
RedHat Enterprise Linux (RHEL)	RHEL 6.9 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.2.156.38
		No	N/A	N/A	Emulex LPm16002B-HI	v11.2.156.38
		Yes	02-59 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.6.18.2904
		Yes	02-59 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.6.18.2904
	RHEL 6.10 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.12
		No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.12
		Yes	02-66 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.6.19.2920
		Yes	02-66 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.6.19.2920
	RHEL 7.1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v10.2.8021.1
		No	N/A	N/A	Emulex LPm16002B-HI	v10.2.8021.1
		Yes	02-40 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3144 v4.7.18.3154
		Yes	02-40 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.7.18.3144 v4.7.18.3154
	RHEL 7.2 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v10.7.0.1
		No	N/A	N/A	Emulex LPm16002B-HI	v10.7.0.1
		Yes	02-45 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3160
		Yes	02-45 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.7.18.3160
	RHEL 7.3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.1.0.2
		No	N/A	N/A	Emulex LPm16002B-HI	v11.1.0.2
		Yes	02-58 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.21.4252
		Yes	02-58 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.7.21.4252
RHEL 7.4 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.2.156.38	
	No	N/A	N/A	Emulex LPm16002B-HI	v11.2.156.38	
	Yes	02-62 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.21.4294	
	Yes	02-62 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.7.21.4294	

RHEL 7.5 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.12	
	No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.12	
	Yes	02-67 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4328	
	Yes	02-67 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.7.22.4328	
RHEL 7.6 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.15	
	No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.15	
	Yes	02-64 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4328	
	Yes	02-64 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.7.22.4328	
RHEL 7.7 (X64)	Yes	02-69 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4346	
	Yes	02-69 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.7.22.4346	
RHEL 8.1 (X64)	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.8.22.4354	
	No	N/A	N/A	Hitachi HFCE1602-M	v4.8.22.4354	
SuSE Linux Enterprise Server (SLES)	SLES 11 SP4 (X64)	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.11.18.3154
		No	N/A	N/A	Hitachi HFCE1602-M	v4.11.18.3154
	SLES 12 (X64)	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.12.18.3146
		Yes	02-55 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.12.18.3146
	SLES 12 SP1 (X64)	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.12.20.4110
	SLES 12 SP2 (X64)	Yes	02-55 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.12.21.4284
	SLES 12 SP4 (X64)	Yes	02-69 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.12.22.4340
	SLES 12 SP5 (X64)	No	N/A	N/A	Hitachi HFCE1602-M	v4.12.22.4346
SLES 15 SP1 (X64)	No	N/A	N/A	Hitachi HFCE1602-M	v4.15.22.4342	
Oracle Linux	Oracle Linux 7.0 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v8.3.7.34.4p
	Oracle Linux 7.1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v10.2.8061.0
	Oracle Linux 7.2 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v10.6.61.1
VMWare	VMWare 6.0 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2428
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2428
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.19.96

VMWare 6.0 U1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled
	No	N/A	N/A	Emulex LPm16002B-HI	Bundled
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2446
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.19.96
VMWare 6.0 U2 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled
	No	N/A	N/A	Emulex LPm16002B-HI	Bundled
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.19.96
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.19.96
VMWare 6.0 U3 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled
	No	N/A	N/A	Emulex LPm16002B-HI	Bundled
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.140
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.140
VMWare 6.5 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled
	No	N/A	N/A	Emulex LPm16002B-HI	Bundled
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.112
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.112
VMWare 6.5 U1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	Bundled (v11.1.196.3)
	No	N/A	N/A	Emulex LPm16002B-HI	Bundled (v11.1.196.3)
	No	N/A	N/A	Hitachi HFCE0802	v10.42.20.140
	No	N/A	N/A	Hitachi HFCE1602	v10.42.20.140
VMWare 6.5 U2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
	No	N/A	N/A	Emulex LPm16002B-HI	Bundled
	No	N/A	N/A	Hitachi HFCE0802	v10.42.20.162
	No	N/A	N/A	Hitachi HFCE1602	v10.42.20.162
VMWare 6.5 U3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.1.196.3
	No	N/A	N/A	Emulex LPm16002B-HI	v11.1.196.3
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
VMWare 6.7 U1 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0
	No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
VMWare 6.7 U2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0
	No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
VMWare 6.7 U3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0
	No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172

Windows	Windows Server 2012	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v2.76.002.001	
		No	N/A	N/A	Emulex LPm16002B-HI	v2.76.002.001	
		Yes	02-05 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.3.8.1970	
		Yes	02-10 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.3.8.1970	
	Windows Server 2012 R2	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v2.76.002.001	
		No	N/A	N/A	Emulex LPm16002B-HI	v2.76.002.001	
		Yes	02-05 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.4.8.1690	
		Yes	02-10 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.4.8.1970	
	Windows Server 2016	No	N/A	N/A	Emulex LPe1205A-HI	v11.0.247.8000	
		No	N/A	N/A	Emulex LPm16002B-HI	v11.0.247.8000	
		Yes	02-56 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.5.8.2240	
		Yes	02-56 or higher	A0240 or higher 08-19 or higher 08-19 or higher 08-18 or higher	Hitachi HFCE1602-M	v4.5.8.2240	
	Cirix XENServer	XENServer 6.5 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v10.2.340.0
		XENServer 7.0 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v11.0.0.12
		XENServer 7.1 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v11.1.210.1
		XENServer 7.2 (X64)	No	N/A	N/A	Emulex LPe12002, LPe1205A-HI	v11.1.210.1

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2f	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2f, v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.2.0, and v8.2.1 are not supported.

Cisco	9148, 9222i, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1)	
	9148S, 9706	v6.2(17) - v6.2(29) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9250i	v6.2(17) - v6.2(29) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9396S	v6.2(13), v6.2(17) - v6.2(29) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9710	v6.2(17) - v6.2(29) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9396T (32Gb)	v8.3(1) - v8.3(2)	
	9706 (32Gb), 9710 (32Gb)	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
Hitachi	Blade Server Switch - 5460	v7.4.2c	
	Blade Server Switch - 6546	v8.1.2b	

3rd Party PCIe card support	
Blade Model	PCIe card
CB 500 Expansion Blade (GG-RV3XGC0B2X1-Y)	Brocade 1020
	Emulex LPe12002
	Emulex LPe16002B
	Fusion-io ioDrive2
	HGST Ultrastar SN150 (1.6TB/3.2TB)
	Mellanox MHQH29-XTC
	NVIDIA Grid K2
	QLogic QLE2562 QLogic QLE2564

OS Server Certification	Link to the vendor HCL
OS	
RedHat Enterprise Linux (RHEL)	RedHat Customer Portal
SuSE Linux Enterprise Server (SLES)	SUSE YES Certification
Oracle Linux	Oracle Linux HCL
Vmware	VMWare Compatibility Guide
Windows	Windows Server Catalog
Citrix XenServer	Citrix HCL

HDS support for Hitachi CB 520X B1 (GG-RV3XGE0B1X1-Y) Server Blade

OS	Version	HVM/LPAR support	HVM/LPAR Manager version	SVP, Integrated firmware, BMC, EFI versions	HBA/CNA model	HBA/CNA driver
RedHat Enterprise Linux (RHEL)	RHEL 6.9 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.2.156.38
		No	N/A	N/A	Emulex LPm16002B-HI	v11.2.156.38
		Yes	02-59 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE0802	v4.6.18.2904
		Yes	02-59 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE1602	v4.6.18.2904
	RHEL 6.10 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.12
		No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.12
		Yes	02-66 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.6.19.2920
		Yes	02-66 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE1602-M	v4.6.19.2920
	RHEL 7.1 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v10.2.8021.1
		No	N/A	N/A	Emulex LPm16002B-HI	v10.2.8021.1
		Yes	02-40 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3144 v4.7.18.3154
		Yes	02-40 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE1602-M	v4.7.18.3144 v4.7.18.3154
	RHEL 7.2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v10.7.0.1
		No	N/A	N/A	Emulex LPm16002B-HI	v10.7.0.1
		Yes	02-45 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3160
		Yes	02-45 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE1602-M	v4.7.18.3160
RHEL 7.3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.1.215.9	
	No	N/A	N/A	Emulex LPm16002B-HI	v11.1.215.9	
	Yes	02-59 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE0802	v4.7.21.4252	
	Yes	02-59 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE1602	v4.7.21.4252	
RHEL 7.4 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.2.156.38	
	No	N/A	N/A	Emulex LPm16002B-HI	v11.2.156.38	
	Yes	02-62 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.21.4294	
	Yes	02-62 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE1602-M	v4.7.21.4294	

	RHEL 7.6 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.15
		No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.15
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4328
		No	N/A	N/A	Hitachi HFCE1602-M	v4.7.22.4328
	RHEL 7.7 (X64)	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4346
		No	N/A	N/A	Hitachi HFCE1602-M	v4.7.22.4346
SuSE Linux Enterprise Server (SLES)	SLES 11 SP4 (X64)	No	N/A	N/A	Hitachi HFCE0802-M	v4.11.18.3154
		No	N/A	N/A	Hitachi HFCE1602-M	v4.11.18.3154
	SLES 12 (X64)	No	N/A	N/A	Hitachi HFCE0802-M	v4.12.18.3146
		No	N/A	N/A	Hitachi HFCE1602-M	v4.12.18.3146
	SLES 12 SP1 (X64)	No	N/A	N/A	Hitachi HFCE0802-M	v4.12.20.4110
	SLES 12 SP2 (X64)	No	N/A	N/A	Hitachi HFCE0802-M	v4.12.21.4284
SLES 15 SP1 (X64)	No	N/A	N/A	Hitachi HFCE0802-M	v4.15.22.4342	
Oracle Linux	Oracle Linux 7.0 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v8.3.7.34.4p
VMWare	VMWare 6.0 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2848
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.19.96
	VMWare 6.0 U1 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2446
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.19.96
	VMWare 6.0 U2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.19.96
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.19.96
	VMWare 6.0 U3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled (v11.1.196.3)
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled (v11.1.196.3)
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.140
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.140
	VMWare 6.5 U3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.1.196.3
		No	N/A	N/A	Emulex LPm16002B-HI	v11.1.196.3
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
	VMWare 6.7 U1 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0
		No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
	VMWare 6.7 U2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0
		No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
VMWare 6.7 U3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0	
	No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0	
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172	
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172	

Windows	Windows Server 2012	No	N/A	N/A	Emulex LPe1205A-HI	v2.76.002.001
		No	N/A	N/A	Emulex LPm16002B-HI	v2.76.002.001
		Yes	01-81 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.3.8.1970
		Yes	02-10 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE1602-M	v4.3.8.1970
	Windows Server 2012 R2	No	N/A	N/A	Emulex LPe1205A-HI	v2.76.002.001
		No	N/A	N/A	Emulex LPm16002B-HI	v2.76.002.001
		Yes	01-81 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.4.8.1690
		Yes	02-10 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE1602-M	v4.4.8.1970
Cirix XENServer	XENServer 6.5 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v10.2.340.0

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2f	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2f, v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148, 9222i, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1)	
	9148S, 9706	v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9250i	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9396S	v6.2(13), v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9710	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	

	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9396T (32Gb)	v8.3(1) - v8.3(2)	
	9706 (32Gb), 9710 (32Gb)	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
Hitachi	Blade Server Switch - 5460	v7.4.2c	
	Blade Server Switch - 6546	v8.1.2b	

OS Server Certification OS	Link to the vendor HCL
RedHat Enterprise Linux (RHEL)	RedHat Customer Portal
SuSE Linux Enterprise Server (SLES)	SUSE YES Certification
Oracle Linux	Oracle Linux HCL
Vmware	VMWare Compatibility Guide
Windows	Windows Server Catalog
Citrix Xenserver	Citrix HCL

HDS support for Hitachi CB 520X B2 (GG-RV3XGE0B2X1-Y) Server Blade

OS	Version	HVM/LPAR support	HVM/LPAR Manager version	SVP, Integrated firmware, BMC, EFI versions	HBA/CNA model	HBA/CNA driver
RedHat Enterprise Linux (RHEL)	RHEL 6.9 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.2.156.38
		No	N/A	N/A	Emulex LPm16002B-HI	v11.2.156.38
		Yes	02-59 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.6.18.2904
		Yes	02-59 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.6.18.2904
	RHEL 6.10 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.12
		No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.12
		Yes	02-66 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.6.19.2920
		Yes	02-66 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.6.19.2920
	RHEL 7.1 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v10.2.8021.1
		No	N/A	N/A	Emulex LPm16002B-HI	v10.2.8021.1
		Yes	02-40 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3144 v4.7.18.3154
		Yes	02-40 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.7.18.3144 v4.7.18.3154
	RHEL 7.2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v10.7.0.1
		No	N/A	N/A	Emulex LPm16002B-HI	v10.7.0.1
		Yes	02-45 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3160
		Yes	02-45 or higher	A0206 or higher 06-04 or higher 06-04 or higher 06-04 or higher	Hitachi HFCE1602-M	v4.7.18.3160
	RHEL 7.3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.1.0.2
		No	N/A	N/A	Emulex LPm16002B-HI	v11.1.0.2
		Yes	02-58 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.21.4252
		Yes	02-58 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.7.21.4252
RHEL 7.4 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.2.156.38	
	No	N/A	N/A	Emulex LPm16002B-HI	v11.2.156.38	
	Yes	02-62 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.21.4294	
	Yes	02-62 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.7.21.4294	

RHEL 7.5 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.12	
	No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.12	
	Yes	02-64 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4328	
	Yes	02-64 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.7.22.4328	
RHEL 7.6 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.15	
	No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.15	
	Yes	02-67 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4328	
	Yes	02-67 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.7.22.4328	
RHEL 7.7 (X64)	Yes	02-69 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4346	
	Yes	02-69 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.7.22.4346	
RHEL 8.1 (X64)	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.8.22.4354	
	No	N/A	N/A	Hitachi HFCE1602-M	v4.8.22.4354	
SuSE Linux Enterprise Server (SLES)	SLES 11 SP4 (X64)	Yes	02-62 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.7.21.4294
		No	N/A	N/A	Hitachi HFCE1602-M	v4.11.18.3154
	SLES 12 (X64)	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.12.18.3146
		No	N/A	N/A	Hitachi HFCE1602-M	v4.12.18.3146
	SLES 12 SP5 (X64) SLES 15 SP1 (X64)	No	N/A	N/A	Hitachi HFCE1602-M	v4.12.22.4346 v4.15.22.4342
Oracle Linux	Oracle Linux 7.0 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v8.3.7.34.4p
	Oracle Linux 7.1 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v10.2.8061.0
	Oracle Linux 7.2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v10.6.61.1
VMWare	VMWare 6.0 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2446
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.19.96
	VMWare 6.0 U1 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.40.18.2848
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.19.96
	VMWare 6.0 U2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.19.96
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.19.96
	VMWare 6.0 U3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.140
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.140
VMWare 6.5 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled	
	No	N/A	N/A	Emulex LPm16002B-HI	Bundled	
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.112	
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.112	

	VMWare 6.5 U1 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled (v11.1.196.3)	
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled (v11.1.196.3)	
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.140	
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.140	
	VMWare 6.5 U2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	Bundled	
		No	N/A	N/A	Emulex LPm16002B-HI	Bundled	
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.162	
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.162	
	VMWare 6.5 U3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.1.196.3	
		No	N/A	N/A	Emulex LPm16002B-HI	v11.1.196.3	
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172	
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172	
	VMWare 6.7 U1 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0	
		No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0	
		No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172	
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172	
VMWare 6.7 U2 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0		
	No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0		
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172		
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172		
VMWare 6.7 U3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0		
	No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0		
	No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172		
	No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172		
Windows	Windows Server 2012	No	N/A	N/A	Emulex LPe1205A-HI	v2.76.002.001	
		No	N/A	N/A	Emulex LPm16002B-HI	v2.76.002.001	
		Yes	02-10 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.3.8.1970	
		Yes	02-10 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.3.8.1970	
		Windows Server 2012 R2	No	N/A	N/A	Emulex LPe1205A-HI	v2.76.002.001
			No	N/A	N/A	Emulex LPm16002B-HI	v2.76.002.001
	Yes		02-10 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.4.8.1690	
	Yes		02-10 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.4.8.1970	
	Windows Server 2016		No	N/A	N/A	Emulex LPe1205A-HI	v11.0.247.8000
			No	N/A	N/A	Emulex LPm16002B-HI	v11.0.247.8000
		Yes	02-56 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.5.8.2240	
		Yes	02-56 or higher	A0250 or higher 09-02 or higher 09-01 or higher 09-02 or higher	Hitachi HFCE1602-M	v4.5.8.2240	
Cirix XENServer	XENServer 6.5 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v10.2.340.0	

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2f	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2f, v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f, v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148, 9222i, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1)	
	9148S, 9706	v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9250i	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9396S	v6.2(13), v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9710	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9396T (32Gb)	v8.3(1) - v8.3(2)	
	9706 (32Gb), 9710 (32Gb)	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
Hitachi	Blade Server Switch - 5460	v7.4.2c	
	Blade Server Switch - 6546	v8.1.2b	

OS Server Certification	Link to the vendor HCL
OS	
RedHat Enterprise Linux (RHEL)	RedHat Customer Portal
Oracle Linux	Oracle Linux HCL
Vmware	VMWare Compatibility Guide
Windows	Windows Server Catalog
Citrix Xenserver	Citrix HCL

HDS support for Hitachi CB 520X B3 (GG-RV3XGE0B3X1-Y) Server Blade

OS	Version	HVM/LPAR support	HVM/LPAR Manager version	SVP, Integrated firmware, BMC, EFI versions	HBA/CNA model	HBA/CNA driver
RedHat Enterprise Linux (RHEL)	RHEL 6.9 (X64)	Yes	02-59 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.6.18.2904
		Yes	02-59 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE1602-M	v4.6.18.2904
	RHEL 6.10 (X64)	Yes	02-66 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.6.19.2920
		Yes	02-66 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE1602-M	v4.6.19.2920
RHEL 7.2 (X64)		No	N/A	N/A	Emulex LPe1205A-HI	v10.7.0.1
		No	N/A	N/A	Emulex LPm16002B-HI	v10.7.0.1
		Yes	02-56 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.18.3160
		Yes	02-56 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE1602-M	v4.7.18.3160
RHEL 7.3 (X64)		No	N/A	N/A	Emulex LPe1205A-HI	v11.1.0.2
		No	N/A	N/A	Emulex LPm16002B-HI	v11.1.0.2
		Yes	02-58 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.21.4252
		Yes	02-58 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE1602-M	v4.7.21.4252
RHEL 7.4 (X64)		No	N/A	N/A	Emulex LPe1205A-HI	v11.2.156.38
		No	N/A	N/A	Emulex LPm16002B-HI	v11.2.156.38
		Yes	02-62 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.21.4294
		Yes	02-62 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE1602-M	v4.7.21.4294
RHEL 7.5 (X64)		Yes	02-64 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4328
		Yes	02-64 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE1602-M	v4.7.22.4328
RHEL 7.6 (X64)		No	N/A	N/A	Emulex LPe1205A-HI	v12.0.261.15
		No	N/A	N/A	Emulex LPm16002B-HI	v12.0.261.15
		Yes	02-67 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4328
		Yes	02-67 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE1602-M	v4.7.22.4328

	RHEL 7.7 (X64)	Yes	02-69 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.7.22.4346
		Yes	02-69 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE1602-M	v4.7.22.4346
Oracle Virtual Machine (OVM)	OVM 3.4.1 (X64)	No	N/A	N/A	Emulex LPm16002B-HI	Bundled
	OVM 3.4.2 (X64)	No	N/A	N/A	Emulex LPm16002B-HI	Bundled
VMWare	VMWare 6.5 U3 (X64)	No	N/A	N/A	Emulex LPm16002B-HI	v11.1.196.3
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
	VMWare 6.7 U1 (X64)	No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
	VMWare 6.7 U2 (X64)	No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0
		No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172
	VMWare 6.7 U3 (X64)	No	N/A	N/A	Emulex LPe1205A-HI	v11.4.341.0
		No	N/A	N/A	Emulex LPm16002B-HI	v11.4.341.0
No	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v10.42.20.172		
No	N/A	N/A	Hitachi HFCE1602-M	v10.42.20.172		
Windows	Windows Server 2012	Yes	02-56 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.3.8.1970
		Yes	02-56 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE1602-M	v4.3.8.1970
	Windows Server 2012 R2	Yes	02-56 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.3.8.1970
		Yes	02-56 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE1602-M	v4.3.8.1970
	Windows Server 2016	Yes	02-56 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.5.8.2240
		Yes	02-56 or higher	A0320 or higher 11-07 or higher 11-07 or higher 11-07 or higher	Hitachi HFCE1602-M	v4.5.8.2240

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2f	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2f, v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148, 9222i, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1)	

9148S, 9706	v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
9250i	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1)), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
9396S	v6.2(13), v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
9710	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
9396T (32Gb)	v8.3(1) - v8.3(2)	
9706 (32Gb), 9710 (32Gb)	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
Hitachi	Blade Server Switch - 5460	v7.4.2c
	Blade Server Switch - 6546	v8.1.2b

OS Server Certification OS	Link to the vendor HCL
RedHat Enterprise Linux (RHEL)	RedHat Customer Portal
Oracle VM	Oracle VM HCL
Windows	Windows Server Catalog

HDS support for Hitachi CB 540A A1/B1 (GGAGD0A1) / (GGAGD0B1) Server Blades

OS	OS version	HVM/LPAR support	HVM/LPAR Manager version	SVP and Integrated F/W version	HBA/CNA model	HBA/CNA driver
RedHat Enterprise Linux (RHEL)	RHEL 6.10 (X64)	RedHat Enterprise Linux (RHEL)	RedHat Enterprise Linux (RHEL)	RedHat Enterprise Linux (RHEL)	RedHat Enterprise Linux (RHEL)	RedHat Enterprise Linux (RHEL)
		Yes	02-66 or higher	A0125 or higher 03-04 or higher 03-02 or higher 01-08 or higher	Hitachi HFCE1602-M	v4.6.19.2920
Windows	Windows Server 2012	No	N/A	N/A	Emulex LPe1205A-HI	v2.76.002.001
		Yes	01-30 or higher	A0125 or higher 03-04 or higher 03-02 or higher 01-08 or higher	Hitachi HFCE0802-M, HFCE0804-M	v4.3.8.1970
	Windows Server 2012 R2	No	N/A	N/A	Emulex LPe1205A-HI	v2.74.214.004
	No	N/A	N/A	N/A	Emulex LPe1205A-HI	v2.74.214.004
	No	N/A	N/A	N/A	Hitachi HFCE0802-M, HFCE0804-M	v4.4.8.1690

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2f	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2f, v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.0.2b - v8.0.2f, v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2h, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1d, v8.2.2 - v8.2.2b	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148, 9222i, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1)	
	9148S, 9706	v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9250i	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9396S	v6.2(13), v6.2(17) - v6.2(29) - v6.2(31) , v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9710	v6.2(17) - v6.2(29) - v6.2(31) , v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	

	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9396T (32Gb)	v8.3(1) - v8.3(2)	
	9706 (32Gb), 9710 (32Gb)	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(1a)	
	9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(1a)	Cisco OS v8.3(1) is no longer supported on the 9718.
Hitachi	Blade Server Switch - 5460	v7.4.2c	
	Blade Server Switch - 6546	v8.1.2b	

OS Server	Link to the vendor HCL
OS	
RedHat Enterprise Linux (RHEL)	RedHat Customer Portal