



VMWare Support Matrix

Hitachi Unified Storage 100 Family

Note: Configurations added since the last matrix will be shown in red text.

Introduction

Use this interoperability matrix to check whether a proposed customer configuration is supported. Each tab contains a set of components that together comprise a Hitachi Vantara supported solution. This includes operating system (OS) and maintenance release, host bus adapter (HBA), HBA driver, and storage area network (SAN) switches, both Fibre channel (FC) and Fibre channel over Ethernet (FCoE).

In the sample datapath below, a customer configuration is supported if that particular HBA and driver, switch and switch firmware combinations both appear on the Windows Server 2012 R2 support matrix.

For example: Windows Server 2012 R2 host that has an Emulex LPe12000/12002 HBA using driver v2.76.002.001 connected to a Brocade DCX SAN switch with FOS v7.2.1 installed.

If a combination does not appear on the OS support matrix, the customer's Hitachi Vantara Sales Engineer (SE) or other Hitachi field service employee must submit an Interoperability Support Request in order to gain support for the new configuration.

Note that in some cases a component (HBA, driver, switch, switch firmware version) may no longer be supported (end of service life, EOSL) in which case the customer should choose components that are already supported from the matrix. Click on a tab to view associated components.

Legal Disclaimer

This information is subject to change without notice. The information contained in this document is provided by Hitachi Vantara for general information purposes only and is based on information as of the date of distribution (indicated by the date above). Hitachi Vantara makes no express or implied warranties of any kind whatsoever regarding the contents of this Document or the performance of the products referred to in these documents and Hitachi Vantara expressly disclaims all warranties including, without limitation, the implied warranties of satisfactory quality, merchantability or fitness for a particular purpose, the statutory warranty against infringement, and any warranty of title. Hitachi Vantara will have no liability whatsoever for any direct loss or damage (but excluding any liability for death, personal injury or fraudulent misrepresentation) or for any indirect, special, incidental or consequential damages, including but not limited to loss of data or records, lost profits or other economic loss, arising out of or in connection with the use of this information even if such loss was foreseeable or Hitachi Vantara had been advised of the possibility of such loss.

HUS 110 130 150 support for VMWare ESXi 6.5 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe12000, LPe12002, LPe1205	Bundled	
	LPe35000, LPe35002	v12.0.257.5	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2f	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2f, v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k	
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(31)	
	9250i	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)	
	9396S	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)	
	9710	v6.2(17) - v6.2(31)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1)	
ISCSI Storage Interface			
ISCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	
QLogic	QLE8360, QLE8362	v644.6.06.0	
ISCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	

HUS 110 130 150 support for VMWare ESXi 6.0, UP1, UP2, UP3 (X64)

NOTE: VMware 6.0 General support ended 3/12/2020. Extended support ends 2/12/2022.

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.12b v1.6.0.17a v1.6.0.25 v1.6.0.28 v2.4.0.13	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.17a v1.6.0.25 v1.6.0.34 v1.6.0.36 v2.4.0.13	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.6.0.17a v1.6.0.28	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe12000, LPe12002, LPe1205	Bundled	
	LPe16000, LPe16002, LPe16002B	Bundled v10.2.455.0	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.0.237.0	
	OCe10102	Bundled	
	OCe11102	Bundled v11.0.237.0	
QLogic	QLE2560, QLE2562	Bundled	
	QLE2660, QLE2662, QLE2670, QLE2672	Bundled	
	QLE2690, QLE2692	Bundled	
	QLE2740, QLE2742, QLE2764	v2.1.41.0	
	QLE8260, QLE8262	Bundled	
	QLE8360, QLE8362	Bundled	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2f	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2f	
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(31)	
	9250i	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)	
	9396S	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)	
	9710	v6.2(17) - v6.2(31)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1)	
FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	Nexus 5672up, 5672up-16G, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(3a) - v2.2(4c), v2.2(6c) - v2.2(8g), v3.1(1e) - v3.1(1l)	
	UCS 6324	v3.0(2c) - v3.0(2d), v3.1(1e) - v3.1(1l)	Cisco UCS Mini only

ISCSI Storage Interface			
ISCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	
ISCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	

HUS 110 130 150 support for VMWare ESXi 5.5, UP1, UP2, UP3 (X64)
NOTE: VMware 5.5 support ended 9/19/2018. Extended support ends 9/19/2020.

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.45 v1.5.0.49 v1.6.0.5 v1.6.0.10 v1.6.0.12 v1.6.0.12b v1.6.0.17a v1.6.0.25 v1.6.0.28 v2.4.0.13	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.12 v1.6.0.12b v1.6.0.16 v1.6.0.25 v2.4.0.13	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.5.0.45 v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe12000, LPe12002, LPe1205, LPe1205-HI	Bundled v10.0.720.0 v10.2.261.7 v10.2.340.18	
	LPe16000, LPe16002, LPe16002B	Bundled v10.0.725.203 v11.1.145.18	
	OCe10102	v8.2.3.1-129vmw v8.2.4.151.65	
	OCe11102	v8.2.3.1-129vmw v8.2.4.151.65 v10.2.455.0	
HP	A8003A, A8003B, FC2242SR, A8002A, A8002B, FC2142SR	Bundled	
	AJ763A, AJ763B, 82E, AJ762A, AJ762B, 81E	Bundled	
	AE311A, AE312A, FC1142SR	Bundled	
	AK344A, AJ764A, 81Q, 82Q	Bundled	
	403619-B21 QMH2462	Bundled	
	451871-B21 QMH2562	Bundled	
	534M	v1.78.28.v55.2 v1.78.80.v55.3	
	554FLB, 554M	v10.2.298.12 v10.2.340.18 v10.5.39.0	
	650FLB, 650M	v10.2.340.18 v10.2.292.0 v10.5.39.0	
	651281-B21 QMH2572	Bundled	
	718203-B21	v10.0.725.203	
	NC553i	v10.2.298.12 v10.5.39.0	
IBM	88Y5920	v1.78.76.v55.1	
	90Y3554	Bundled	

Qlogic	QLE2560, QLE2562	Bundled	
	QLE2660, QLE2662, QLE2670, QLE2672	Bundled	
	QLE2690, QLE2692	Bundled	
	QLE8240, QLE8242	Bundled	
	QLE8360, QLE8362	Bundled v1.1.39.0	
	QME2572	Bundled	
	QME2662	Bundled	

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2f	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2f	
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(31)	
	9148S, 9706	v7.3(0)D1(1) - v7.3(1)D1(1)	
	9250i	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)	
	9396S	v6.2(17) - v6.2(31)	
	9710	v6.2(17) - v6.2(31)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1)	

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	9250i (FCoE), 9513 (FCoE), 9706 (FCoE), 9710 (FCoE), 9718 (FCoE)	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(3a) - v2.2(4c), v2.2(5b) - v2.2(5d), v2.2(6c) - v2.2(8f), v3.1(1e)	
	Nexus 5596UP, 5548up-2232pp, Nexus 5596T-2232TM-E	v7.1(0)N1(1a) - v7.1(4)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.1(0)N1(1a) - v7.1(4)N1(1), v7.3(0)N1(1) - v7.3(1)N1(1)	
	Nexus 6001T, 6004, 6001p-2248pq	v6.0(2)N1(1), v6.0(2)N1(2), v6.0(2)N1(2a), v7.1(0)N1(1a) - v7.1(4)N1(1)	
	Nexus 7710 (FCoE)	v7.3(0)D1(1) - v7.3(1)D1(1)	
	UCS 6324	v3.0(2c) - v3.0(2d), v3.1(1e) - v3.1(1l)	Cisco UCS Mini only

ISCSI Storage Interface			
ISCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	
HP	554FLB	v4.9.303	
	554FLR-SFP	v4.9.303.0	
	556FLR-SFP+	v10.2.250.0	
ISCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	