



## **RHEL Support Matrix**

### **Hitachi VSP 5x00, G1x00, F1500, E990, Gxx0, Fxx0, HUS VM**

**Note:** Configurations added since the last matrix will be shown in red text.

#### **Introduction**

Use this interoperability matrix to check whether a proposed customer configuration is supported. Each tab contains a set of components that together comprise an Hitachi Vantara-supported solution. This includes operating system (OS) and maintenance release, host bus adapter (HBA), HBA driver, and storage area network (SAN) switches, for Fibre channel (FC), Fibre channel over Ethernet (FCoE), and 10 Gbps iSCSI.

**Note:** The arrays supported now include the VSP E990.

#### **Note on the 16 & 32 Gb Interfaces:**

- The 32Gb interface is only available on the VSP 5x00, E990, GX00 and FX00 arrays. It is supported with both 16 & 32Gb SFPs and operates at a maximum of 32Gbps.
- The HUS VM does not have a 16Gb FC interface.
- With SVOS 7, for Direct connection to 16Gb or 32Gb FC you must set the storage port to Fabric = OFF and Connection Type P-to-P (Point to Point)

If a combination does not appear on the OS support matrix, the customer's Hitachi Vantara Sales Engineer (SE) or other Hitachi field service employee must submit an Interoperability Support Request in order to gain support for the new configuration.

#### **Legal Disclaimer**

*This information is subject to change without notice. The information contained in this document is provided by Hitachi Vantara for general information purposes only and is based on information as of the date of distribution (indicated by the date above). Hitachi Vantara makes no express or implied warranties of any kind whatsoever regarding the contents of this Document or the performance of the products referred to in these documents and Hitachi Vantara expressly disclaims all warranties including, without limitation, the implied warranties of satisfactory quality, merchantability or fitness for a particular purpose, the statutory warranty against infringement, and any warranty of title. Hitachi Vantara will have no liability whatsoever for any direct loss or damage (but excluding any liability for death, personal injury or fraudulent misrepresentation) or for any indirect, special, incidental or consequential damages, including but not limited to loss of data or records, lost profits or other economic loss, arising out of or in connection with the use of this information even if such loss was foreseeable or Hitachi Vantara had been advised of the possibility of such loss.*

## VSP 5x00, G1x00, F1500, E990, Gxx0, Fxx0 support for RHEL 8.2 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v12.6.0.2	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v12.6.0.2	
	LPe35000, LPe35002, LPe35004	v12.6.0.2	
QLogic	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v10.01.00.21.08.2-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v10.01.00.21.08.2-k	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	
	G610	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c, v9.0.0a	
	G620, X6	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c, v9.0.0a	
	G630	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c, v9.0.0a	
	G620v2, G630v2, G720, X6 Plus, X7	v9.0.0a - v9.0.0b	
Cisco	9132T	v8.4(1) - v8.4(2a)	
	9148S, 9706	v8.4(1) - v8.4(2a)	
	9148T, 9396T	v8.4(1) - v8.4(2a)	
	9250i	v8.4(1) - v8.4(2a)	
	9396S	v8.4(1) - v8.4(2a)	
	9710	v8.4(1) - v8.4(2a)	
	9718	v8.4(1) - v8.4(2a)	
	9706 (32Gb), 9710 (32Gb)	v8.4(1) - v8.4(2a)	
	9718 (32Gb)	v8.4(1) - v8.4(2a)	

10 Gbps iSCSI Storage Interface			
iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe14102	v11.4.0.1	
QLogic	QLE8442	v2.7.10.1	
iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	

## VSP 5x00, G1x00, F1500, E990, Gxx0, Fxx0 support for RHEL 8.1 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1340, 1380	v2.0.0.60-141.0	
	UCS 1440, 1455, 1457, 1480	v2.0.0.60-141.0	
Emulex	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v12.2.0.3 v12.4.243.20	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v12.2.0.3 v12.4.243.20	
HPE	SN1100E	v12.2.0.3 v12.4.243.20	
	SN1200E	v12.2.0.3 v12.4.243.20	
	SN1600E	v12.2.0.3 v12.4.243.20	
QLogic	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v10.01.00.15.08.1-k1	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v10.01.00.15.08.1-k1	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
	G610	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
	G620, X6	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
	G630	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
Cisco	9132T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9148S, 9706	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9250i	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9396S	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9710	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9718	v8.3(2), v8.4(1) - v8.4(2a)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb) 9718 (32Gb)	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a) v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	UCS 6454	v4.1(1b)	
10 Gbps iSCSI Storage Interface			
iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe14102	v11.4.0.1	
QLogic	QLE8442	v2.7.10.1	
iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	

## VSP 5x00, G1x00, F1500, E990,Gxx0, Fxx0 support for RHEL 8.0 (X64)

<b>FC Storage Interface</b>			
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v12.2.383.0 v12.6.182.4	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v12.2.383.0 v12.6.182.4	
HPE	3530C	v12.2.383.0	
	718203-B21	v12.2.383.0	
	LPe1605		
	SN1100E	v12.2.383.0	
	SN1200E	v12.2.383.0	
	SN1600E	v12.2.383.0	
	SN1100Q	v10.00.00.07.08.0-k1	
Qlogic	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v10.01.00.55.08.0-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v10.00.00.07.08.0-k1 v10.01.00.55.08.0-k	
<b>FC Switches</b>			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
	G610	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
	G620, X6	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
	G630	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(29) - v6.2(31)	
	9132T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9148S, 9706	v6.2(29) - v6.2(31), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9250i	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9396S	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9710	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9718	v8.3(2), v8.4(1) - v8.4(2a)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.3(1) - v8.3(2)	
	9718 (32Gb)	v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.

<b>10 Gbps iSCSI Storage Interface</b>			
<b>iSCSI Adapters</b>			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe14102	v11.4.0.1	
<b>iSCSI Switches</b>			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	

## VSP 5x00, G1x00, F1500, E990, Gxx0, Fxx0 support for RHEL 7.8 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe12000, LPe12002, LPe1205	v12.0.0.13	
	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v12.0.0.13	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v12.0.0.13	
	LPe35000, LPe35002, LPe35004	v12.0.0.13	
HPE	3530C	v12.0.0.13	
	650FLB, 650M	v12.0.0.13	
	710608-B21 QMH2672	v10.01.00.20.07.8-k	
	718203-B21 LPe1605	v12.0.0.13	
	SN1100E	v12.0.0.13	
	SN1200E	v12.0.0.13	
	SN1600E	v12.0.0.13	
	SN1000Q	v10.01.00.20.07.8-k	
	SN1100Q	v10.01.00.20.07.8-k	
	SN1600Q, SN1610Q	v10.01.00.20.07.8-k	
QLogic	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v10.00.00.12.07.7-k v10.01.00.20.07.8-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v10.00.00.12.07.7-k v10.01.00.20.07.8-k	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	
	G610	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c, v9.0.0a	
	G620, X6	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c, v9.0.0a	
	G630	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c, v9.0.0a	
	G620v2, G630v2, G720, X6 Plus, X7	v9.0.0a - v9.0.0b	
Cisco	9132T	v8.4(1) - v8.4(2a)	
	9148S, 9706	v8.4(1) - v8.4(2a)	
	9148T, 9396T	v8.4(1) - v8.4(2a)	
	9250i	v8.4(1) - v8.4(2a)	
	9396S	v8.4(1) - v8.4(2a)	
	9710	v8.4(1) - v8.4(2a)	
	9718	v8.4(1) - v8.4(2a)	
	9706 (32Gb), 9710 (32Gb)	v8.4(1) - v8.4(2a)	
	9718 (32Gb)	v8.4(1) - v8.4(2a)	
10 Gbps iSCSI Storage Interface			
iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe14102	v11.4.0.1	
QLogic	QLogic QLE8442	v2.7.10.1	
iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	

## VSP 5x00, G1x00, F1500, E990, Gxx0, Fxx0 support for RHEL 7.7 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1340, 1380	v2.0.0.59-133.0	
	UCS 1440, 1455, 1457, 1480	v2.0.0.59-133.0	
Emulex	LPe12000, LPe12002, LPe1205	v12.0.0.10	
	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v12.0.0.10	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v12.0.0.10	
	OCe14102	v12.0.0.10	
HPE	3530C	v12.0.0.10	
	710608-B21	v10.00.00.12.07.7-k	
	QMH2672		
	718203-B21		
	LPe1605	v12.0.0.10	
	<b>AK344A, AJ764A, 81Q, 82Q</b>	<b>v10.00.00.12.07.7-k</b>	
	SN1100E	v12.0.0.10	
	SN1200E	v12.0.0.10	
	SN1600E	v12.0.0.10	
	SN1100Q	v10.00.00.12.07.7-k	
Qlogic	QLE2560, QLE2562, QLE2564, QME2572	v10.00.00.12.07.7-k	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v10.00.00.12.07.7-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v10.00.00.12.07.7-k	
	QLogic QLE8442	v2.11.8	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v8.1.2a -v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2e, v8.2.1 are not supported.
	G610	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
	G620, X6	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
	G630	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
Cisco	9132T	v8.3(1) - v8.3(2)	
	9148S, 9706	v8.3(1) - v8.3(2)	
	9148T, 9396T	v8.3(1) - v8.3(2)	
	9250i	v8.3(1) - v8.3(2)	
	9396S	v8.3(1) - v8.3(2)	
	9710	v8.3(1) - v8.3(2)	
	9718	v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.3(1) - v8.3(2)	
9718 (32Gb)	v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.	
FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(3)N1(1)	
	UCS 6332-16UP	v4.1(1b)	

### FCOE Storage Interface - VSP G1000 only

#### Converged Network Adapters (CNA)

Manufacturer	Models	Driver Versions	Notes
Emulex	OCe14102	v12.0.0.10	
QLogic	QLogic QLE8442	v2.11.8	

#### FCOE Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(3)N1(1)	

### 10 Gbps iSCSI Storage Interface

#### iSCSI Adapters

Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe14102	v11.4.0.1	
QLogic	QLogic QLE8442	v2.7.10.1	

#### iSCSI Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	

## VSP 5x00, G1x00, F1500, E990, Gxx0, Fxx0 support for RHEL 7.6 (X64)

<b>FC Storage Interface</b>			
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.47	
	UCS 1340, 1380	v2.0.0.42-77.0	
	UCS 1440, 1455, 1457, 1480	v2.0.0.42-77.0 v2.0.0.60-141.0	
Emulex	LPe12000, LPe12002, LPe1205	v12.0.0.5	
	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v12.0.0.5 v12.6.182.4	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v12.0.0.5 v12.0.0.10 v12.6.182.4	
	LPe35000, LPe35002, LPe35004	v12.2.383.0 v12.2.299.13 v12.4.243.20	
	Oce14102	v12.0.0.5	
HPE	3530C	v12.0.0.5	
	3830C	v10.00.00.06.07.6-k	
	451871-B21	v10.00.00.06.07.6-k	
	QMH2562		
	650FLB, 650M	v12.0.0.5	
	710608-B21	v10.00.00.06.07.6-k	
	QMH2672		
	718203-B21	v12.0.0.5	
	LPe1605		
	AJ763A, AJ763B, AH403A, 82E AJ762A, AJ762B, AH402A, 81E	v12.0.0.5	
	CN1200E	v12.0.0.5	
	SN1100E	v12.0.0.5	
	SN1200E	v12.0.0.5	
	SN1600E	v12.0.0.5	
	SN1000Q	v10.00.00.06.07.6-k	
SN1100Q	v10.00.00.06.07.6-k		
SN1600Q	v10.00.00.06.07.6-k		
IBM	00Y3337, 00Y3341	v10.00.00.06.07.6-k	
	42D0485, 42D0494	v12.0.0.5	
QLogic	QLE2560, QLE2562, QLE2564, QME2572	v10.00.00.06.07.6-k	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v10.00.00.06.07.6-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v10.00.00.06.07.6-k	
	QLE8360, QLE8362	v10.00.00.06.07.6-k	



FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2g, v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(29) - v6.2(31)	
	9132T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9148S, 9706	v6.2(29) - v6.2(31), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9250i	v6.2(29) - v6.2(31), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9396S	v6.2(29) - v6.2(31), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9710	v6.2(29) - v6.2(31), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9718	v8.3(2), v8.4(1) - v8.4(2a)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9718 (32Gb)	v8.3(2), v8.4(1) - v8.4(2a)	Cisco OS v8.3(1) is no longer supported on the 9718.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v4.0(2b)	
	UCS 6332-16UP	v4.0(2b), v4.0(4b)	
	UCS 6454	v4.1(1b)	

### FCOE Storage Interface - VSP G1000 only

Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
HPE	CN1200E	v12.0.0.5	
Emulex	OCe14102	v12.0.0.5	
QLogic	QLE8360, QLE8362	v10.00.00.06.07.6-k	
		v10.00.00.07.08.0-k1	

FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	9148S, 9706 (FCoE)	v6.2(29) - v6.2(31), v8.4(1) - v8.4(2a)	
	9710, 9718 (FCoE)	v6.2(29) - v6.2(31), v8.4(1) - v8.4(2a)	
	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	

### 10 Gbps iSCSI Storage Interface

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe14102	v11.4.0.1	
QLogic	QLE8360, QLE8362	v5.04.00.00.07.02-k0	

  

iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	

## VSP 5x00, G1x00, F1500, Gxx0, Fxx0 support for RHEL 7.5 (X64)

<b>FC Storage Interface</b>			
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.34	
	UCS 1340, 1380	v1.6.0.44	
	UCS 1440 ,1480	v1.6.0.34	
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI	v11.4.0.4	
	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v11.4.0.4 v12.0.193.22	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v11.4.0.4 v12.0.193.22	
	OCe14102	v11.4.0.4	
HPE	3530C	v11.4.0.4	
	3830C	v9.00.00.00.07.5-k1	
	651281-B21	v9.00.00.00.07.5-k1	
	QMH2572		
	710608-B21	v9.00.00.00.07.5-k1	
	QMH2672		
	AK344A, AJ764A, 81Q, 82Q	v9.00.00.00.07.5-k1	
	CN1200E	v11.4.0.4	
	NCS53i, NCS53m, CN1100E	v11.4.0.4	
	SN1100E	v11.4.0.4	
	SN1200E	v11.4.0.4	
	SN1600E	v11.4.0.4	
	SN1000Q	v9.00.00.00.07.5-k1	
	SN1100Q	v9.00.00.00.07.5-k1	
SN1600Q	v9.00.00.00.07.5-k1		
IBM	00Y3337, 00Y3341	v9.00.00.00.07.5-k1	
	42D0485, 42D0494	v11.4.0.4	
Qlogic	QLE2560, QLE2562, QLE2564	v9.00.00.00.07.5-k1	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v9.00.00.00.07.5-k1 v9.00.00.00.40.0-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v9.00.00.00.07.5-k1 v9.00.00.00.40.0-k1	
	QLE8360, QLE8362	v9.00.00.00.07.5-k1	

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2g, v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31)	
	9148S, 9706	v6.2(29) - v6.2(31), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9148T, 9396T	v8.3(1) - v8.3(2)	
	9250i	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9396S	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9710	v6.2(29) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9718	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(2a)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v3.2(3h)	
	UCS 6332-16UP	v4.0(1c)	

### FCOE Storage Interface - VSP G1000 only

Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
HPE	CN1200E	v11.4.0.4	
Emulex	OCe14102	v11.4.0.4	
QLogic	QLE8360, QLE8362	v9.00.00.00.07.5-k1	

FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	7706 (FCoE), 7710(FCoE), 7718(FCoE)	v8.3(1) - v8.3(2)	
	9706 (FCoE), 9710 (FCoE), 9718 (FCoE)	v6.2(29) - v6.2(31), v8.1(1) - v8.1(1b), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	

### 10 Gbps iSCSI Storage Interface - VSP G1x00, F1500, Gxx0, Fxx0 only

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe14102	v11.4.0.1	
QLogic	QLE8360, QLE8362	v5.04.00.00.07.02-k0	

iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	

## VSP 5x00, G1x00, F1500, Gxx0, Fxx0 support for RHEL 7.4 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.36	
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI	v11.2.0.6	
	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v11.2.0.6	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v11.2.0.6	
	OCe11102	v11.2.0.6	
	OCe14102	v11.2.0.6	
HPE	3820c	v2.11.11	
	650FLB, 650M	v11.2.0.6	
	651281-B21	v8.07.00.38.07.4-k1	
	QMH2572		
	710608-B21	v8.07.00.38.07.4-k1	
	QMH2672		
	AJ763A, AJ763B, AH403A, 82E	v11.2.0.6	
	AJ762A, AJ762B, AH402A, 81E		
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.38.07.4-k1	
	SN1000Q	v8.07.00.38.07.4-k1	
IBM	42D0485, 42D0494	v11.2.0.6	
	42D0501, 42D0510	v8.07.00.38.07.4-k1	
Qlogic	QLE2560, QLE2562, QLE2564	v8.07.00.38.07.4-k1	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.38.07.4-k1	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v8.07.00.38.07.4-k1	
	QLE8360, QLE8362	v8.07.00.38.07.4-k1	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2g	
	6505, 6510, 6520, 7840, DCX 8510	v8.1.2a -v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2a -v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
	G620, X6	v8.1.2a -v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.

Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9148S, 9706	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9148T, 9396T	v8.3(1) - v8.3(2)	
	9250i	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9396S	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9710	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9718	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.

### FCOE Switches (FCF mode)

Manufacturer	Models	Firmware Versions	Notes
Cisco	Nexus 5596UP, 5548up-2232pp, Nexus 5596T-2232TM-E	v7.0(0)N1(1) - v7.0(8)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v3.2(1) - v3.2(2d)	

### FCOE Storage Interface - VSP G1000 only

#### Converged Network Adapters (CNA)

Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	v11.2.0.6	
	OCe14102	v11.2.0.6	
Intel	X520	4.4.0-k-rh7.3	
QLogic	QLE8360, QLE8362	v8.07.00.38.07.4-k1	

#### FCOE Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Brocade	G620, X6	v8.2.0a	
Cisco	Nexus 5596UP, 5548up-2232pp, Nexus 5596T-2232TM-E	v7.0(0)N1(1) - v7.0(8)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(8)N1(1)	

### 10 Gbps iSCSI Storage Interface - VSP 5x00, G1x00, F1500, Gxx0, Fxx0 only

#### iSCSI Adapters

Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe11102	v11.2.1.0	
QLogic	QLE8360, QLE8362	v5.04.00.00.07.02-k0	

#### iSCSI Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	

## VSP 5x00, G1x00, F1500, Gxx0, Fxx0 support for RHEL 7.3 (X64)

<b>FC Storage Interface</b>			
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.34	
	UCS 1340, 1380	v1.6.0.34 v1.6.0.37	
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI	v11.1.0.2	
	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v11.1.0.2	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v11.1.0.2	
	OCe11102	v11.0.0.2	
HPE	451871-B21	v8.07.00.33.07.3-k1	
	QMH2562	v8.07.00.34.07.3-k1	
	650FLB, 650M	v11.1.183.21	
	651281-B21	v8.07.00.33.07.3-k1	
	QMH2572	v8.07.00.34.07.3-k1	
	659818-B21	v11.1.183.21	
	LPe1205A		
	710608-B21	v8.07.00.33.07.3-k1	
	QMH2672	v8.07.00.34.07.3-k1	
	AJ763A, AJ763B, AH403A, 82E AJ762A, AJ762B, AH402A, 81E	v11.1.0.2	
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1	
	NC553i, NC553m, CN1100E	v11.1.183.21	
	SN1000Q	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1	
	SN1100Q	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1	
	SN1100E	v11.1.0.2	
	SN1600Q	v8.07.00.42.07.0-k1	
IBM	42D0485, 42D0494	v11.1.0.2	
	42D0501, 42D0510	v8.07.00.33.07.3-k1	
Qlogic	QLE2560, QLE2562, QLE2564	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1 v8.07.00.42.07.0-k1	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1 v8.07.00.42.07.0-k1	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1	
		v8.07.00.42.07.0-k1	

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2g	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2g, v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
	G620, X6	v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9148S, 9706	v6.2(17) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9250i	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9396S	v6.2(17) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9710	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v3.1.2(b) - v3.1.2(e), v3.1.3(a) - v3.1(3d)	
	UCS 6324	v3.1.2(b) - v3.1.2(e), v3.1.3(a) - v3.1(3d)	Cisco UCS Mini only
	UCS 6332-16UP	v3.1(3e), v3.2(2b) - v3.2(2d), v3.2(3d)	

### FCOE Storage Interface - VSP G1000 only

Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	v11.1.0.2	
Intel	X520	4.4.0-k-rh7.3	
QLogic	QLE8360, QLE8362	v8.07.00.33.07.3-k1	

FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(8)N1(1)	

### 10 Gbps iSCSI Storage Interface - VSP 5x00, G1x00, F1500, Gxx0, Fxx0 only

ISCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe11102	v11.0.0.0	
QLogic	QLE8360, QLE8362	v5.04.00.00.07.02-k0	
ISCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	
Cisco	Nexus 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v7.3(0)N1(1) - v7.3(1)N1(1)	



## VSP G1x00, F1500, Gxx0, Fxx0 support for RHEL 7.2 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.17 v1.6.0.25	
	UCS 1340, 1380	v1.6.0.25 v1.6.0.34	
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI	v10.7.0.1 v11.1.0.2 v11.1.183.21 v11.1.218.0	
	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v10.7.0.1 v11.0.240.0 v11.1.183.21 v11.1.218.0 v11.2.156.18	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v11.0.240.0 v11.1.183.21 v11.2.156.18	
	Oce14102	v10.7.0.1	
HPE	3530c	v11.1.183.21	
	3830C	v8.07.00.34.07.0-k1	
	QMH2682		
	456972-B21	v11.1.183.21	
	LPe1205-HP		
	554M, 554FLB	v11.1.183.21	
	650FLB, 650M	v10.7.0.1 v11.1.183.21	
	651281-B21	v8.07.00.18.07.2-k	
	QMH2572		
	659818-B21	v10.7.0.1	
	LPe1205A	v11.1.183.21	
	710608-B21	v8.07.00.18.07.2-k	
	QMH2672		
	AJ763A, AJ763B, AH403A, 82E	v10.7.0.1	
AJ762A, AJ762B, AH402A, 81E			
AK344A, AJ764A, 81Q, 82Q	v8.07.00.18.07.2-k		
NC551i, NC551m	v10.7.0.1		
NC553i, NC553m, CN1100E	v11.1.183.21		
SN1000Q	v8.07.00.18.07.2-k		
IBM	42D0485, 42D0494	v10.7.0.1	
	42D0501, 42D0510	v8.07.00.18.07.2-k	
Qlogic	QLE2560, QLE2562, QLE2564	v8.07.00.18.07.2-k v8.07.00.42.07.0-k1	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.18.07.2-k v8.07.00.34.07.0-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v8.07.00.18.07.2-k v8.07.00.34.07.0-k	
		v8.07.00.42.07.0-k1	

<b>FC Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Brocade	300, 7800	v7.4.2d - v7.4.2g	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2g, v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
	G620, X6	v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
Cisco	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9148S, 9706	v6.2(17) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9250i	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9396S	v6.2(17) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9710	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.	
<b>FCOE Switches (FCF mode)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Cisco	9250i (FCoE), 9513 (FCoE), 9710 (FCoE), 9718 (FCoE)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	Nexus 5672up, 5672up-2248pq	v7.1(0)N1(1a) - v7.2(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v3.1(1e) - v3.1(1f)	
	UCS 6324	v3.1(1e) - v3.1(1f), v3.1.2(b) - v3.1.2(e)	Cisco UCS Mini only
	UCS 6332-16UP	v3.1(2e)	
<b>FCOE Storage Interface - VSP G1000 only</b>			
<b>Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Emulex	OCe11102	v10.7.0.1	
	Oce14102	v10.7.0.1	
QLogic	QLE8360, QLE8362	v8.07.00.18.07.2-k	
<b>FCOE Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	Nexus 5672up, 5672up-2248pq	v7.1(0)N1(1a) - v7.2(1)N1(1), v7.3(0)N1(1) - v7.3(1)N1(1)	
	UCS 6324	v3.1(1e)	Cisco UCS Mini only

### 10 Gbps iSCSI Storage Interface - VSP G1x00, F1500, Gxx0, Fxx0 only

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe11102	v10.6.0.0r	
Intel	82599ES	v4.0.1-k v4.3.13	
	X520	Bundled	
QLogic	QLE8360, QLE8362	v5.04.00.00.07.02-k0	
iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only

## VSP G1x00, F1500, Gxx0, Fxx0 support for RHEL 7.1 (X64)

<b>FC Storage Interface</b>			
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.18 v1.6.0.25	
	UCS 1340, 1380	v1.6.0.18 v1.6.0.25	
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI	v10.2.8021.1	
	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v10.2.8021.1 v10.6.144.21	
HPE	651281-B21 QMH2572	v8.07.00.08.07.1-k2	
	710608-B21 QMH2672	v8.07.00.08.07.1-k2	
	AJ763A, AJ763B, AH403A, 82E AJ762A, AJ762B, AH402A, 81E	v10.2.8021.1	
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.08.07.1-k2	
	SN1100E	v10.2.8021.1	
	SN1000Q	v8.07.00.08.07.1-k2	
IBM	42D0485, 42D0494	v10.2.8021.1	
	42D0501, 42D0510	v8.07.00.08.07.1-k2	
Qlogic	QLE2560, QLE2562, QLE2564	v8.07.00.08.07.1-k2 v8.07.00.16.39.0-k	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.08.07.1-k2	
<b>FC Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Brocade	300, 7800	v7.4.2d - v7.4.2g	
	6505, 6510, 6520, 7840, DCX 8510	v8.1.2a -v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2a -v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
	G620, X6	v8.1.2a -v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.	
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9148S, 9706	v6.2(17) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9250i	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9396S	v6.2(17) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9710	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.	

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(5b) - v2.2(5d), v2.2(6c) - v2.2(8f)	
	UCS 6324	v3.0(2c) - v3.0(2d)	Cisco UCS Mini only

### FCOE Storage Interface - VSP G1000 only

Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.18	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.18	
Emulex	OCe10102	v10.4r v10.4.74.0r	
	OCe11102	v10.2.8021.1	
QLogic	QLe8362	v8.07.00.08.07.1-k2	

FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	Nexus 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v7.0(1)N1(1) - v7.0(6)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(5b) - v2.2(5d), v2.2(6c) - v2.2(8f)	
	UCS 6324	v3.0(2c) - v3.0(2d)	Cisco UCS Mini only

### 10 Gbps iSCSI Storage Interface - VSP G1x00, F1500, Gxx0, Fxx0 only

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCE10102	v10.4r	
	OCe11102	v10.4.74.0r	
HP	530SFP+	v1.710.51-0	
	534FLB	v7.14.07-1	
	534FLR-SFP+	v7.14.07-1	
	CN1100R	v7.14.07-1	
	CN1200E	v11.1.145.27-1	
Intel	X520	v4.0.1-k	
QLogic	QLE8360, QLE8362	v5.04.00.04.07.01-k0	
	QLE8440, QLE8442	v5.04.00.04.070-ko	

iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	
Cisco	Nexus 5672up, 5672up-2248pq, 5672up-2348UPQ	v7.0(5)N1(1) - v7.0(7)N1(1), v7.1(0)N1(1a) - v7.2(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(6)N1(1)	

## VSP G1x00, F1500, Gxx0, Fxx0 support for RHEL 7.0 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.12b v1.6.0.16	
	UCS 1340, 1380	v1.6.0.12b v1.6.0.16	
Emulex	LPe12000, LPe12002, LPe1205, LPe1205-HI, LPe1205A-HI	v8.3.7.34.3p	
	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v8.3.7.34.3p v10.2.340.16	
	LPm16002B-HI	v8.3.7.34.3p	
	OCe10102	v8.3.7.34.3p	
	OCe11102	v8.3.7.34.3p	
HPE	710608-B21	v8.06.00.08.07.0-k2	
	QMH2672	v8.07.00.16.07.0-k	
	AJ763A, AJ763B, AH403A, 82E AJ762A, AJ762B, AH402A, 81E	v8.3.7.34.3p	
	AK344A, AJ764A, 81Q, 82Q	v8.06.00.08.07.0-k2	
	SN1100E	v8.3.7.34.3p	
	SN1000Q	v8.06.00.08.07.0-k2	
IBM	42D0485, 42D0494	v8.3.7.34.3p	
	42D0501, 42D0510	v8.06.00.08.07.0-k2	
Qlogic	QLE2560, QLE2562, QLE2564	v8.06.00.08.07.0-k2 v8.07.00.16.07.0-k	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.06.00.08.07.0-k2	
	QLE8240, QLE8242	v8.06.00.08.07.0-k2	
	QLE8360, QLE8362	v8.06.00.08.07.0-k2	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 7800	v7.4.2d - v7.4.2g	
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)	
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9148S, 9706	v6.2(17) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9250i	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1)), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9396S	v6.2(17) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9710	v6.2(17) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	

9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
9706 (32Gb), 9710 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	9250i (FCoE), 9513 (FCoE), 9710 (FCoE), 9718 (FCoE)	v7.3(0)D1(1) - v7.3(1)D1(1)	
	Nexus 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(3a) - v2.2(4c)	
	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v7.0(1)N1(1) - v7.0(6)N1(1)	
	UCS 6324	v3.0(2c) - v3.0(2d)	Cisco UCS Mini only

### FCOE Storage Interface - VSP G1000 only

Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	OCe10102	Bundled	
Qlogic	QLE8360, QLE8362	v8.06.00.08.07.0-k2	

FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	Nexus 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v6.0(2)N2(1), v6.0(2)N2(1b), v6.0(2)N2(2) - v6.0(2)N2(6)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(3a) - v2.2(4c)	

### 10 Gbps iSCSI Storage Interface - VSP G1x00, F1500, Gxx0, Fxx0 only

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	v10.4.74.0r	

iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	
Cisco	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(6)N1(1)	

## VSP 5x00, G1x00, F1500, Gxx0, Fxx0 support for RHEL 6.10 (X64)

FC Storage Interface				
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)				
Manufacturer	Models	Driver Versions	Notes	
Emulex	LPe12000, LPe12002, LPe1205	v11.0.1.6		
	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v11.0.1.6 v12.0.193.22		
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v11.0.1.6 v12.0.193.22 v12.2.299.13		
	LPe35000, LPe35002, LPe35004	v12.2.299.13		
	OCe14102	v11.0.1.6 v11.4.1186.5		
HPE	3530C	v11.0.1.6		
	3830C	v8.07.00.26.06.8-k		
	451871-B21 QMH2562	v8.07.00.26.06.8-k		
	651281-B21 QMH2572	v8.07.00.26.06.8-k		
	659818-B21 LPe1205A	v11.0.1.6		
	710608-B21 QMH2672	v8.07.00.26.06.8-k		
	SN1100E	v11.0.1.6		
	SN1200E	v11.0.1.6		
	SN1600E	v11.0.1.6		
	SN1000Q	v8.07.00.26.06.8-k		
	SN1100Q	v8.07.00.26.06.8-k		
	SN1600Q	v8.07.00.26.06.8-k		
	Qlogic	QLE2560, QLE2562, QLE2564, QME2572	v8.07.00.26.06.8-k	
		QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.26.06.8-k	
QLE2690, QLE2692, QLE2740, QLE2742, QLE2764		v8.07.00.26.06.8-k		
QLE8360, QLE8362		v8.07.00.26.06.8-k		
FC Switches				
Manufacturer	Models	Firmware Versions	Notes	
Brocade	6505, 6510, 6520, 7840, DCX 8510	v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.	
	G610	v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.	
	G620, X6	v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.	
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.	
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31)		
	9132T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)		
	9148S, 9706	v6.2(29) - v6.2(31), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)		
	9148T, 9396T	v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)		
	9250i	v6.2(17) - v6.2(31), v8.4(1) - v8.4(2a)		
	9396S	v8.4(1) - v8.4(2a)		
	9710	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)		
	9718	v8.2(1) - v8.2(2), v8.3(2), v8.4(1) - v8.4(2a)	Cisco OS v8.3(1) is no longer supported on the 9718.	
	9706 (32Gb), 9710 (32Gb) 9718 (32Gb)	v8.2(1) - v8.2(2) v8.2(1) - v8.2(2)		
FCOE Switches (FCF mode)				
Manufacturer	Models	Firmware Versions	Notes	



Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
-------	-----------------------------	-----------------------------	--

### FCOE Storage Interface - VSP G1000 only

Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe14102	v11.0.1.6 v11.4.1186.5	
QLogic	QLE8360, QLE8362	v8.07.00.26.06.8-k	
FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	9148S, 9706 (FCoE)	v6.2(29) - v6.2(31), v8.4(1) - v8.4(2a)	
	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	

### 10 Gbps iSCSI Storage Interface - VSP 5x00, G1x00, F1500, Gxx0, Fxx0 only

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe14102	v11.1.0.0	VSP G1x00, F1500, Gxx0, Fxx0 only
QLogic	QLE8360, QLE8362	v5.03.00.00.06.07-k0	
iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only

## VSP G1x00, F1500, Gxx0, Fxx0, HUS VM support for RHEL 6.9 (X64)

<b>FC Storage Interface</b>			
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.34	
	UCS 1340, 1380	v1.6.0.34	
Emulex	LPe12000, LPe12002, LPe1205	v11.0.0.5 v11.0.1.6	
	LPe16000, LPe16002, LPe16004, LPe16000B, Pe16002B	v11.0.0.5 v11.0.1.6 v12.0.193.22	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002, LPe32004	v12.0.193.22 v12.2.299.13	
	OCe11102	v11.0.0.5	
HPE	3820c	v2.11.11	
	650FLB, 650M	v8.07.00.26.06.8-k	
	651281-B21 QMH2572	v8.07.00.26.06.8-k	
	710608-B21 QMH2672	v8.07.00.26.06.8-k	
	AJ763A, AJ763B, AH403A, 82E AJ762A, AJ762B, AH402A, 81E	v11.0.0.5	
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.26.06.8-k	
	SN1000Q	v8.07.00.26.06.8-k	
	SN1100Q	v8.07.00.26.06.8-k	
	SN1100E	v11.0.0.5 v11.0.1.6	
	IBM	42D0485, 42D0494	v11.0.0.5
42D0501, 42D0510		v8.07.00.26.06.8-k	
Qlogic	QLE2560, QLE2562, QLE2564	v8.07.00.26.06.8-k	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.26.06.8-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v8.07.00.26.06.8-k	
	QLE8360, QLE8362	v8.07.00.26.06.8-k	

<b>FC Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Brocade	300, 7800	v7.4.2d - v7.4.2g	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2g, v8.1.2a -v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.2a -v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
	G620, X6	v8.1.2a -v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(31), v7.3(0)DY(1) - v7.3(1)DY(1)	
	9148S, 9706	v6.2(17) - v6.2(31), v8.4(1) - v8.4(2a)	
	9148T, 9396T	v8.3(1) - v8.3(2)	
	9250i	v6.2(25) - v6.2(31), v8.1(1) - v8.1(1b), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	9710	v6.2(23) - v6.2(31), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9718	v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9718 (32Gb)	v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
<b>FCOE Switches (FCF mode)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Brocade	X6 (FCoE)	v8.2.0a - v8.2.0b	
Cisco	9706 (FCoE), 9710 (FCoE), 9718 (FCoE)	v6.2(25) - v6.2(29) - v6.2(31), v8.1(1) - v8.1(1b), v8.3(1) - v8.3(2), v8.4(1) - v8.4(2a)	
	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v3.1.3(a) - v3.1(3d)	

### FCOE Storage Interface - VSP G1000 only

#### Converged Network Adapters (CNA)

Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	v11.0.0.5	
	Emulex Oce14102	v11.0.0.5 v11.4.1186.5	
QLogic	QLE8360, QLE8362	v8.07.00.26.06.8-k v8.07.00.56.06.0-k1	

#### FCOE Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(8)N1(1)	

### 10 Gbps iSCSI Storage Interface - VSP G1x00, F1500, Gxx0, Fxx0 only

#### iSCSI Adapters

Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe11102	v11.1.0.0	
Intel	X520	Bundled	
QLogic	QLE8360, QLE8362	v5.03.00.00.06.07-k0	

#### iSCSI Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	