



## HP-UX Support Matrix

### Hitachi VSP 5x00, G1x00, F1500, Gxx0, Fxx0, HUS VM

**Note:** Configurations added since the last matrix will be shown in red text.

#### Introduction

Use this interoperability matrix to check whether a proposed customer configuration is supported. Each tab contains a set of components that together comprise an Hitachi Vantara-supported solution. This includes operating system (OS) and maintenance release, host bus adapter (HBA), HBA driver, and storage area network (SAN) switches, both Fibre channel (FC), Fibre channel over Ethernet (FCoE).

**Note:** The arrays supported now include the VSP 5100, 5100H, 5500, 5500H.

#### Note on the 16 & 32 Gb Interfaces:

- The 32Gb interface is only available on the VSP 5x00, GX00 and FX00 arrays. It is supported with both 16 & 32Gb SFPs and operates at a maximum of 32Gbps.
- The HUS VM does not have a 16Gb FC interface.
- With SVOS 7, for Direct connection to 16Gb or 32Gb FC you must set the storage port to Fabric = OFF and Connection Type P-to-P (Point to Point)

If a combination does not appear on the OS support matrix, the customer's Hitachi Vantara Sales Engineer (SE) or other Hitachi field service employee must submit an Interoperability Support Request in order to gain support for the new configuration.

#### Legal Disclaimer

*This information is subject to change without notice. The information contained in this document is provided by Hitachi Vantara for general information purposes only and is based on information as of the date of distribution (indicated by the date above). Hitachi Vantara makes no express or implied warranties of any kind whatsoever regarding the contents of this Document or the performance of the products referred to in these documents and Hitachi Vantara expressly disclaims all warranties including, without limitation, the implied warranties of satisfactory quality, merchantability or fitness for a particular purpose, the statutory warranty against infringement, and any warranty of title. Hitachi Vantara will have no liability whatsoever for any direct loss or damage (but excluding any liability for death, personal injury or fraudulent misrepresentation) or for any indirect, special, incidental or consequential damages, including but not limited to loss of data or records, lost profits or other economic loss, arising out of or in connection with the use of this information even if such loss was foreseeable or Hitachi Vantara had been advised of the possibility of such loss.*

**VSP 5x00, G1x00, F1500, Gxx0, Fxx0, HUS VM support for HP-UX 11.31 (IA64)**

<b>FC Storage Interface</b>			
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
HPE	451871-B21, QMH2562	Bundled	
	456972-B21, LPe1205	Bundled	
	81E, 82E, AH402A, AH403A, AJ762A, AJ763A	Bundled	
	81Q, 82Q, AH400A, AH401A, AK344A, AJ764A	Bundled	
	AT094A	Bundled	
	SN1000Q	Bundled	
<b>FC Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Brocade	300, 7800	v7.4.2d - v7.4.2g	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d - v7.4.2g, v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k	Brocade FOS v8.1.2c, and v8.1.2e are not supported.
	G610	v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, and v8.1.2e are not supported.
	G620, X6	v8.1.2a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2k, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.1.2c, v8.1.2e, and v8.2.1 are not supported.
	G630	v8.2.1a - v8.2.1e, v8.2.2 - v8.2.2c	Brocade FOS v8.2.1 is not supported.
Cisco	9148, 9506 (8Gb), 9513 (8Gb)	v6.2(17) - v6.2(29) - v6.2(31)	
	9132T, 9148T, 9396T	v8.2(1) - v8.2(2)	
	9148S, 9706	v6.2(17) - v6.2(29) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2)	
	9250i	v6.2(17) - v6.2(29) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2)	
	9396S	v6.2(17) - v6.2(29) - v6.2(31), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2)	
	9710	v6.2(17) - v6.2(29) - v6.2(31), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2)	
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2)	