



## **RHEL Support Matrix**

### **Hitachi VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM**

**Note:** Configurations added since the last matrix will be shown in red text.

#### **Introduction**

Use this interoperability matrix to check whether a proposed customer configuration is supported. Each tab contains a set of components that together comprise an Hitachi Vantara-supported solution. This includes operating system (OS) and maintenance release, host bus adapter (HBA), HBA driver, and storage area network (SAN) switches, both Fibre channel (FC) and Fibre channel over Ethernet (FCoE).

**Note:** The arrays supported now include the VSP F700, F900, G700, G900, F350, F370, G350, & G370.

#### **Note on the 16 & 32 Gb Interfaces:**

- The 32Gb interface is only available on the GX00 and FX00 arrays. It is supported with both 16 & 32Gb SFPs and operates at a maximum of 32Gbps.
- The VSP and HUS VM do not have 16Gb FC interfaces.
- With SVOS 7, for Direct connection to 16Gb or 32Gb FC you must set the storage port to Fabric = OFF and Connection Type P-to-P (Point to Point)

Note: The Hitachi FIVE FC HBA also has an alternate option of Fabric Emulation. When it is configured in this mode it should be treated as switch attached and the storage port should be set to Fabric = On and Connection Type = P-to-P

If a combination does not appear on the OS support matrix, the customer's Hitachi Vantara Sales Engineer (SE) or other Hitachi field service employee must submit an Interoperability Support Request in order to gain support for the new configuration.

#### **Legal Disclaimer**

*This information is subject to change without notice. The information contained in this document is provided by Hitachi Vantara for general information purposes only and is based on information as of the date of distribution (indicated by the date above). Hitachi Vantara makes no express or implied warranties of any kind whatsoever regarding the contents of this Document or the performance of the products referred to in these documents and Hitachi Vantara expressly disclaims all warranties including, without limitation, the implied warranties of satisfactory quality, merchantability or fitness for a particular purpose, the statutory warranty against infringement, and any warranty of title. Hitachi Vantara will have no liability whatsoever for any direct loss or damage (but excluding any liability for death, personal injury or fraudulent misrepresentation) or for any indirect, special, incidental or consequential damages, including but not limited to loss of data or records, lost profits or other economic loss, arising out of or in connection with the use of this information even if such loss was foreseeable or Hitachi Vantara had been advised of the possibility of such loss.*

## VSP G1x00, F1500, Gxx0, Fxx0 support for RHEL 7.5 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe16000, LPe16002, LPe16002B	v11.4.0.4 v12.0.193.22	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.4.0.4 v12.0.193.22	
	OCe14102	v11.4.0.4	
HPE	3530C	v11.4.0.4	
	3830C	v9.00.00.00.07.5-k1	
	403619-B21	v9.00.00.00.07.5-k1	
	QMH2462		
	710608-B21	v9.00.00.00.07.5-k1	
	QMH2672		
	CN1200E	v11.4.0.4	
	SN1100E	v11.4.0.4	
	SN1200E	v11.4.0.4	
	SN1600E	v11.4.0.4	
	SN1000Q	v9.00.00.00.07.5-k1	
	SN1100Q	v9.00.00.00.07.5-k1	
SN1600Q	v9.00.00.00.07.5-k1		
IBM	00Y3337, 00Y3341	v9.00.00.00.07.5-k1	
Qlogic	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v9.00.00.00.07.5-k1	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v9.00.00.00.07.5-k1	
	QLE8360, QLE8362	v9.00.00.00.07.5-k1	
<b>FC Switches</b>			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G610	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9124, 9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(17) - v6.2(23)	
	9148S, 9706	v8.2(1) - v8.2(2), v8.3(1)	
	9710	v8.2(1) - v8.2(2), v8.3(1)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.2(1) - v8.2(2), v8.3(1)	
<b>FCOE Switches (FCF mode)</b>			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6740	v6.0.1a	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	Nexus 7710 (FCoE)	v8.3(1)	

<b>FCOE Storage Interface</b>			
<b>Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
HP	CN1200E	v11.4.0.4	
Emulex	OCe14102	v11.4.0.4	
QLogic	QLE8360, QLE8362	v9.00.00.00.07.5-k1	
<b>FCOE Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Brocade	VDX 6740	v6.0.1a	VSP G1x00, & VSP only
Cisco	Nexus 5672up, 5672up-2248pq 7706 (FCoE), 7710(FCoE), 7718(FCoE)	v7.3(0)N1(1) - v7.3(1)N1(1) v8.3(1)	
<b>10 Gbps iSCSI Storage Interface</b>			
<b>iSCSI Adapters</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Any	10 GbE NIC	Bundled	
Emulex	OCe14102	v11.4.0.1	VSP G1x00, F1500, Gxx0, Fxx0 only
QLogic	QLE8360, QLE8362	v5.04.00.00.07.02-k0	
<b>iSCSI Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only

## VSP G1x00, F1500, Gxx0, Fxx0, VSP support for RHEL 7.4 (X64)

FC Storage Interface				
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)				
Manufacturer	Models	Driver Versions	Notes	
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.36	Must connect to a Cisco UCS top of rack interconnect switch.	
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI	v11.2.0.6		
	LPe16000, LPe16002, LPe16002B	v11.2.0.6		
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.2.0.6		
	OCe11102	v11.2.0.6		
	OCe14102	v11.2.0.6		
HPE	3820c	v2.11.11		
	403619-B21 QMH2462	v8.07.00.38.07.4-k1		
	650FLB, 650M	v11.2.0.6		
	651281-B21 QMH2572	v8.07.00.38.07.4-k1		
	710608-B21 QMH2672	v8.07.00.38.07.4-k1		
	AJ763A, AJ763B, 82E AJ762A, AJ762B, 81E	v11.2.0.6		
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.38.07.4-k1		
	SN1000Q	v8.07.00.38.07.4-k1		
	SN1100E	v11.2.0.6		
	IBM	42D0485, 42D0494	v11.2.0.6	
		42D0501, 42D0510	v8.07.00.38.07.4-k1	
Qlogic	QLE2560, QLE2562, QLE2564	v8.07.00.38.07.4-k1		
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.38.07.4-k1		
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v8.07.00.38.07.4-k1		
	QLE8360, QLE8362	v8.07.00.38.07.4-k1		
FC Switches				
Manufacturer	Models	Firmware Versions	Notes	
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b>	Brocade FOS v7.4.2b is not supported.	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2c - <b>v7.4.2d</b> , v8.0.1 - <b>v8.0.2f</b> , v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.1.2c, <b>v8.1.2e</b> , v8.2.0, and <b>v8.2.1</b> are not supported.	
	G610	v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.1.0, v8.1.2c, <b>v8.1.2e</b> , and v8.2.0 are not supported.	
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, <b>v8.1.2e</b> , v8.2.0, and <b>v8.2.1</b> are not supported.	
	G630	v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.2.0, and <b>v8.2.1</b> are not supported.	
Cisco	9124, 9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.	
	9132T	v8.2(1) - v8.2(2), v8.3(1)		
	9148S, 9706	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)		
	9710	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)		
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)		
FCOE Switches (FCF mode)				
Manufacturer	Models	Firmware Versions	Notes	
Brocade	VDX 6740	v6.0.1a		
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)		
	UCS 6120XP, 6140XP, 6248up, 6296up	v3.2(1) - v3.2(2d)		
FCOE Storage Interface				
Converged Network Adapters (CNA)				
Manufacturer	Models	Driver Versions	Notes	
Emulex	OCe11102	v11.2.0.6		

	OCe14102	v11.2.0.6	
Intel	X520	4.4.0-k-rh7.3	
QLogic	QLE8360, QLE8362	v8.07.00.38.07.4-k1	

### FCOE Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	VSP G1000 & VSP only
Brocade	VDX 6740	v6.0.1a	
	G620, X6	v8.2.0a	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(8)N1(1)	

### 10 Gbps iSCSI Storage Interface

#### iSCSI Adapters

Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
Emulex	OCe11102	v11.2.1.0	
QLogic	QLE8360, QLE8362	v5.04.00.00.07.02-k0	

#### iSCSI Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only

## VSP G1x00, F1500, Gxx0, Fxx0, VSP support for RHEL 7.3 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.34	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.34 v1.6.0.37	
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI	v11.1.0.2	
	LPe16000, LPe16002, LPe16002B	v11.1.0.2	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.1.0.2	
	OCe11102	v11.0.0.2	
HPE	451871-B21	v8.07.00.33.07.3-k1	
	QMH2562	v8.07.00.34.07.3-k1	
	650FLB, 650M	v11.1.183.21	
	651281-B21	v8.07.00.33.07.3-k1	
	QMH2572	v8.07.00.34.07.3-k1	
	659818-B21	v11.1.183.21	
	LPe1205A		
	710608-B21	v8.07.00.33.07.3-k1	
	QMH2672	v8.07.00.34.07.3-k1	
	AJ763A, AJ763B, 82E	v11.1.0.2	
	AJ762A, AJ762B, 81E		
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1	
	NC553i, NC553m, CN1100E	v11.1.183.21	
	SN1000Q	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1	
	SN1100Q	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1	
SN1100E	v11.1.0.2		
SN1600Q	v8.07.00.42.07.0-k1		
IBM	42D0485, 42D0494	v11.1.0.2	
	42D0501, 42D0510	v8.07.00.33.07.3-k1	
Qlogic	QLE2560, QLE2562, QLE2564	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1 v8.07.00.42.07.0-k1	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1 v8.07.00.42.07.0-k1	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v8.07.00.33.07.3-k1 v8.07.00.34.07.3-k1	
		v8.07.00.42.07.0-k1	

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d	Brocade FOS v7.4.2b is not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2c - v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9124, 9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9132T	v8.2(1) - v8.2(2), v8.3(1)	
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	

### FCOE Switches (FCF mode)

Manufacturer	Models	Firmware Versions	Notes
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v3.1.2(b) - v3.1.2(e), v3.1.3(a) - v3.1(3d)	
	UCS 6324	v3.1.2(b) - v3.1.2(e), v3.1.3(a) - v3.1(3d)	Cisco UCS Mini only
	UCS 6332-16UP	v3.1(3e), v3.2(2b) - v3.2(2d), v3.2(3d)	

### FCOE Storage Interface

#### Converged Network Adapters (CNA)

Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	v11.1.0.2	
Intel	X520	4.4.0-k-rh7.3	
QLogic	QLE8360, QLE8362	v8.07.00.33.07.3-k1	

#### FCOE Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Brocade	VDX 6740	v6.0.1a	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	VSP G1000 & VSP only
	Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(8)N1(1)	

### 10 Gbps iSCSI Storage Interface

#### iSCSI Adapters

Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	
Emulex	OCe11102	v11.0.0.0	VSP G1x00, F1500, Gxx0, Fxx0 only
QLogic	QLE8360, QLE8362	v5.04.00.00.07.02-k0	

#### iSCSI Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	

## VSP G1x00, F1500, Gxx0, Fxx0, VSP support for RHEL 7.2 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.17 v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LP11000, LP11002	v10.7.0.1	
	LPe11000, LPe11002	v10.7.0.1	
	LPe12000, LPe12002, LPe1205, LPe1205A-HI	v10.7.0.1 v11.1.0.2 v11.1.183.21 v11.1.218.0	
	LPe16000, LPe16002, LPe16002B	v10.7.0.1 v11.0.240.0 v11.1.183.21 v11.1.218.0 v11.2.156.18	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.0.240.0 <b>v11.1.183.21</b> v11.2.156.18	
	Oce14102	v10.7.0.1	
HPE	3530c	v11.1.183.21	
	3830C	v8.07.00.34.07.0-k1	
	QMH2682		
	403619-B21	v8.07.00.18.07.2-k	
	QMH2462		
	456972-B21	v11.1.183.21	
	LPe1205-HP		
	554M, 554FLB	v11.1.183.21	
	650FLB, 650M	v10.7.0.1 v11.1.183.21	
	651281-B21	v8.07.00.18.07.2-k	
	QMH2572		
	659818-B21	v10.7.0.1	
	LPe1205A	v11.1.183.21	
	710608-B21	v8.07.00.18.07.2-k	
	QMH2672		
	A8003A, A8003B, FC2242SR	v10.7.0.1	
	A8002A, A8002B, FC2142SR		
	AJ763A, AJ763B, 82E	v10.7.0.1	
	AJ762A, AJ762B, 81E		
AK344A, AJ764A, 81Q, 82Q	v8.07.00.18.07.2-k		
NC551i, NC551m	v10.7.0.1		
NC553i, NC553m, CN1100E	v11.1.183.21		
SN1000Q	v8.07.00.18.07.2-k		
IBM	42C2069, 42C2071	v10.7.0.1	
	42D0485, 42D0494	v10.7.0.1	
	42D0501, 42D0510	v8.07.00.18.07.2-k	
QLogic	QLE2560, QLE2562, QLE2564	v8.07.00.18.07.2-k v8.07.00.42.07.0-k1	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.18.07.2-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v8.07.00.18.07.2-k	
		v8.07.00.42.07.0-k1	



FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b>	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b> , v8.0.1 - <b>v8.0.2f</b> , v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , <b>v8.2.1a</b>	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.1.0, v8.1.2c, <b>v8.1.2e</b> , and v8.2.0 are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, <b>v8.1.2e</b> , v8.2.0, and <b>v8.2.1</b> are not supported.
	G630	v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.2.0, and <b>v8.2.1</b> are not supported.
Cisco	9124, 9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9132T	v8.2(1) - v8.2(2), v8.3(1)	
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	
9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)		
FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	9250i (FCoE), 9513 (FCoE), 9710 (FCoE), 9718 (FCoE)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	Nexus 5672up, 5672up-2248pq	v7.1(0)N1(1a) - v7.2(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v3.1(1e) - v3.1(1l)	
	UCS 6324	v3.1(1e) - v3.1(1l), v3.1.2(b) - v3.1.2(e)	Cisco UCS Mini only
FCOE Storage Interface			
Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	v10.7.0.1	
	OCe14102	v10.7.0.1	
Qlogic	QLE8360, QLE8362	v8.07.00.18.07.2-k	
FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Brocade	VDX 6740	v6.0.1a	VSP G1000 & VSP only
Cisco	Nexus 5672up, 5672up-2248pq	v7.1(0)N1(1a) - v7.2(1)N1(1), v7.3(0)N1(1) - v7.3(1)N1(1)	
	UCS 6324	v3.1(1e)	Cisco UCS Mini only

## 10 Gbps iSCSI Storage Interface

ISCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
Emulex	OCe11102	v10.6.0.0r	
Intel	82599ES	v4.0.1-k v4.3.13	
	X520	Bundled	
QLogic	QLE8360, QLE8362	v5.04.00.00.07.02-k0	
ISCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only
Brocade	VDX 6740	v5.0.1b	

## VSP G1x00, F1500, Gxx0, Fxx0, VSP support for RHEL 7.1 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.18 v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.18 v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI	v10.2.8021.1	
	LPe16000, LPe16002, LPe16002B	v10.2.8021.1 v10.6.144.21	
HPE	651281-B21 QMH2572	v8.07.00.08.07.1-k2	
	710608-B21 QMH2672	v8.07.00.08.07.1-k2	
	AJ763A, AJ763B, 82E AJ762A, AJ762B, 81E	v10.2.8021.1	
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.08.07.1-k2	
	SN1100E	v10.2.8021.1	
	SN1000Q	v8.07.00.08.07.1-k2	
IBM	42D0485, 42D0494	v10.2.8021.1	
	42D0501, 42D0510	v8.07.00.08.07.1-k2	
Qlogic	QLE2560, QLE2562, QLE2564	v8.07.00.08.07.1-k2 v8.07.00.16.39.0-k	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.08.07.1-k2	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b>	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b> , v8.0.1 - <b>v8.0.2f</b> , v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , <b>v8.2.1a</b>	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.1.0, v8.1.2c, <b>v8.1.2e</b> , and v8.2.0 are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, <b>v8.1.2e</b> , v8.2.0, and <b>v8.2.1</b> are not supported.
	G630	v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.2.0, and <b>v8.2.1</b> are not supported.
Cisco	9124, 9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9132T	v8.2(1) - v8.2(2), v8.3(1)	
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	
FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(5b) - v2.2(5d), v2.2(6c) - v2.2(8f)	
	UCS 6324	v3.0(2c) - v3.0(2d)	Cisco UCS Mini only

## FCOE Storage Interface

### Converged Network Adapters (CNA)

Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.18	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.18	
Emulex	OCe10102	v10.4r v10.4.74.0r	
	OCe11102	v10.2.8021.1	
QLogic	QLe8362	v8.07.00.08.07.1-k2	

### FCOE Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	VSP G1000 & VSP only
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v7.0(1)N1(1) - v7.0(6)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(5b) - v2.2(5d), v2.2(6c) - v2.2(8f)	
	UCS 6324	v3.0(2c) - v3.0(2d)	

## 10 Gbps iSCSI Storage Interface

### iSCSI Adapters

Manufacturer	Models	Driver Versions	Notes
Emulex	OCE10102	v10.4r	VSP G1x00, F1500, Gxx0, Fxx0 only
	OCe11102	v10.4.74.0r	
HP	530SFP+	v1.710.51-0	
	534FLB	v7.14.07-1	
	534FLR-SFP+	v7.14.07-1	
	CN1100R	v7.14.07-1	
	CN1200E	v11.1.145.27-1	
Intel	X520	v4.0.1-k	
QLogic	QLE8360, QLE8362	v5.04.00.04.07.01-ko	
	QLE8440, QLE8442	v5.04.00.04.070-ko	

### iSCSI Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only
Brocade	VDX 6730	v4.1.2	
		v4.1.3a	
Cisco	Nexus 5672up, 5672up-2248pq, 5672up-2348UPQ	v7.0(5)N1(1) - v7.0(7)N1(1), v7.1(0)N1(1a) - v7.2(1)N1(1)	
		Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(6)N1(1)

## VSP G1x00, F1500, Gxx0, Fxx0, VSP support for RHEL 7.0 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.12b v1.6.0.16	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.12b v1.6.0.16	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe12000, LPe12002, LPe1205, LPe1205-HI, LPe1205A-HI	v8.3.7.34.3p	
	LPe16000, LPe16002, LPe16002B	v8.3.7.34.3p v10.2.340.16	
	LPm16002B-HI	v8.3.7.34.3p	
	OCe10102	v8.3.7.34.3p	
	OCe11102	v8.3.7.34.3p	
HPE	710608-B21	v8.06.00.08.07.0-k2	
	QMH2672	v8.07.00.16.07.0-k	
	AJ763A, AJ763B, 82E AJ762A, AJ762B, 81E	v8.3.7.34.3p	
	AK344A, AJ764A, 81Q, 82Q	v8.06.00.08.07.0-k2	
	SN1100E	v8.3.7.34.3p	
	SN1000Q	v8.06.00.08.07.0-k2	
IBM	42D0485, 42D0494	v8.3.7.34.3p	
	42D0501, 42D0510	v8.06.00.08.07.0-k2	
QLogic	QLE2560, QLE2562, QLE2564	v8.06.00.08.07.0-k2 v8.07.00.16.07.0-k	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.06.00.08.07.0-k2	
	QLE8240, QLE8242	v8.06.00.08.07.0-k2	
	QLE8360, QLE8362	v8.06.00.08.07.0-k2	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b>	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b> , v8.0.1 - <b>v8.0.2f</b> , v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , <b>v8.2.1a</b>	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.1.0, v8.1.2c, <b>v8.1.2e</b> , and v8.2.0 are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, <b>v8.1.2e</b> , v8.2.0, and <b>v8.2.1</b> are not supported.
	G630	v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.2.0, and <b>v8.2.1</b> are not supported.
Cisco	9124, 9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9132T	v8.2(1) - v8.2(2), v8.3(1)	
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.

	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	
<b>FCOE Switches (FCF mode)</b>			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Brocade	8000	v7.1.0a - v7.1.2b	
Cisco	9250i (FCoE), 9513 (FCoE), 9710 (FCoE), 9718 (FCoE)	v7.3(0)D1(1) - v7.3(1)D1(1)	
	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	
	7706 (FCoE), 7710(FCoE), 7718(FCoE)	v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(3a) - v2.2(4c)	
	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v7.0(1)N1(1) - v7.0(6)N1(1)	
UCS 6324	v3.0(2c) - v3.0(2d)	Cisco UCS Mini only	

<b>FCOE Storage Interface</b>			
<b>Converged Network Adapters (CNA)</b>			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	OCe10102	Bundled	
Qlogic	QLE8360, QLE8362	v8.06.00.08.07.0-k2	
<b>FCOE Switches</b>			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	VSP G1000 & VSP only
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v6.0(2)N2(1), v6.0(2)N2(1b), v6.0(2)N2(2) - v6.0(2)N2(6)	VSP G1000 & VSP only
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(3a) - v2.2(4c)	

<b>10 Gbps iSCSI Storage Interface</b>			
<b>iSCSI Adapters</b>			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	v10.4.74.0r	VSP G1x00, F1500, Gxx0, Fxx0 only
<b>iSCSI Switches</b>			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	
Cisco	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(6)N1(1)	VSP G1x00, F1500, Gxx0, Fxx0 only

## VSP G1x00, F1500, Gxx0, Fxx0 support for RHEL 6.10 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe16000, LPe16002, LPe16002B	v11.0.1.6	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.0.1.6	
	OCe14102	v11.0.1.6	
HPE	3530C	v11.0.1.6	
	3830C	v8.07.00.26.06.8-k	
	SN1100E	v11.0.1.6	
	SN1200E	v11.0.1.6	
	SN1600E	v11.0.1.6	
	SN1000Q	v8.07.00.26.06.8-k	
	SN1100Q	v8.07.00.26.06.8-k	
Qlogic	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.26.06.8-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v8.07.00.26.06.8-k	
	QLE8360, QLE8362	v8.07.00.26.06.8-k	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G610	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148S, 9706	v8.2(1) - v8.2(2), v8.3(1)	
	9710	v8.2(1) - v8.2(2), v8.3(1)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.2(1) - v8.2(2), v8.3(1)	
FCOE Storage Interface			
Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe14102	v11.0.1.6	
Qlogic	QLE8360, QLE8362	v8.07.00.26.06.8-k	
FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	VSP G1x00, & VSP only
Brocade	VDX 6740	v6.0.1a	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	

## 10 Gbps iSCSI Storage Interface

### ISCSI Adapters

Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
Emulex	OCe14102	v11.1.0.0	
QLogic	QLE8360, QLE8362	v5.03.00.00.06.07-k0	

### ISCSI Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only



## VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for RHEL 6.9 (X64)

<b>FC Storage Interface</b>			
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.34	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.34	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe11000, LPe11002, LPe1105	v11.0.0.5 v11.0.1.6	
	LPe12000, LPe12002, LPe1205	v11.0.0.5	
	LPe16000, LPe16002, LPe16002B	v11.0.0.5 v11.0.1.6 v12.0.193.22	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v12.0.193.22	
	OCe11102	v11.0.0.5	
HPE	3820c	v2.11.11	
	403619-B21 QMH2462	v8.07.00.26.06.8-k	
	650FLB, 650M	v8.07.00.26.06.8-k	
	651281-B21 QMH2572	v8.07.00.26.06.8-k	
	710608-B21 QMH2672	v8.07.00.26.06.8-k	
	AJ763A, AJ763B, 82E AJ762A, AJ762B, 81E	v11.0.0.5	
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.26.06.8-k	
	SN1000Q	v8.07.00.26.06.8-k	
	SN1100Q	v8.07.00.26.06.8-k	
	SN1100E	v11.0.0.5 v11.0.1.6	
IBM	42C069, 42C071	v11.0.0.5 v11.0.1.6	
	42D0485, 42D0494	v11.0.0.5	
	42D0501, 42D0510	v8.07.00.26.06.8-k	
Qlogic	QLE2560, QLE2562, QLE2564	v8.07.00.26.06.8-k	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.26.06.8-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v8.07.00.26.06.8-k	
	QLE8360, QLE8362	v8.07.00.26.06.8-k	

<b>FC Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b>	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b> , v8.0.1 - <b>v8.0.2f</b> , v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , <b>v8.2.1a</b>	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.1.0, v8.1.2c, <b>v8.1.2e</b> , and v8.2.0 are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, <b>v8.1.2e</b> , v8.2.0, and <b>v8.2.1</b> are not supported.
	G630	v8.2.0a - v8.2.0b, <b>v8.2.1a</b>	Brocade FOS v8.2.0, and <b>v8.2.1</b> are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9132T	v8.2(1) - v8.2(2), v8.3(1)	
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2), v8.3(1)	
<b>FCOE Switches (FCF mode)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Brocade	VDX 6740	v6.0.1a	VSP G1000 & VSP only
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v3.1.3(a) - v3.1(3d)	

<b>FCOE Storage Interface</b>			
<b>Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Emulex	OCe11102	v11.0.0.5	
	Emulex OCm11104-F2-HI	v11.0.0.5	
QLogic	QLE8360, QLE8362	v8.07.00.26.06.8-k	VSP G1000, G800, G600, G400, G200 only
<b>FCOE Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Brocade	VDX 6740	v6.0.1a	VSP G1000 & VSP only
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(8)N1(1)	
<b>10 Gbps iSCSI Storage Interface</b>			
<b>iSCSI Adapters</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Any	10 GbE NIC	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
Emulex	OCe11102	v11.1.0.0	
Intel	X520	Bundled	
QLogic	QLE8360, QLE8362	v5.03.00.00.06.07-k0	
<b>iSCSI Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only

**VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for RHEL 6.8 (X64)**

<b>FC Storage Interface</b>			
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.27 v1.6.0.34	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.27	
Emulex	LPe12000, LPe12002, LPe1205	v11.0.0.4 v11.1.183.21 v11.1.218.0 v11.2.156.18	
	LPe16000, LPe16002, LPe16002B	v11.0.0.4 v11.1.183.21 v11.1.218.0 v11.1.38.64 v11.2.156.18	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.0.0.4 v11.1.38.64 v11.2.156.18	
	OCe11102	v10.7.0.1 v11.0.0.4	
HPE	3530c	v11.1.183.21	
	3830C	v8.07.00.34.06.0-k1	
	QMH2682		
	451871-B21	v8.07.00.26.06.8-k	
	QMH2562		
	554M, 554FLB	v11.1.183.21	
	650FLB, 650M	v11.1.183.21	
	651281-B21	v8.07.00.26.06.8-k	
	QMH2572		
	710608-B21	v8.07.00.26.06.8-k	
	QMH2672		
	AE311A, AE312A, FC1142SR, FC1242SR	v8.07.00.26.06.8-k	
	AJ763A, AJ763B, 82E	v11.0.0.4	
	AJ762A, AJ762B, 81E		
AK344A, AJ764A, 81Q, 82Q	v8.07.00.26.06.8-k		
NC553i, NC553m, CN1100E	v11.1.183.21		
SN1000Q	v8.07.00.26.06.8-k		
SN1100E	v11.0.0.4		
IBM	39R6525, 39R6527	v8.07.00.26.06.8-k	
	42D0485, 42D0494	v11.0.0.4	
	42D0501, 42D0510	v8.07.00.26.06.8-k	
Qlogic	QLE2460, QLE2462	v8.07.00.26.06.8-k	
	QLE2560, QLE2562, QLE2564	v8.07.00.26.06.8-k	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.26.06.8-k	
	QLE2740, QLE2742, QLE2764	v8.07.00.26.06.8-k	
	QLE8360, QLE8362	v8.07.00.26.06.8-k	

<b>FC Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b>	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b> , v8.0.1 - <b>v8.0.2f</b> , v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b>	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b	Brocade FOS v8.1.0, v8.1.2c, <b>v8.1.2e</b> , and v8.2.0 are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, <b>v8.1.2e</b> , and v8.2.0 are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9132T	v8.2(1) - v8.2(2)	
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
<b>FCOE Switches (FCF mode)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Cisco	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(8)N1(1)	
	Nexus 7706 (FCoE), 7710 (FCoE)	v8.1(1) - v8.1(1a)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(6c) - v2.2(8f), v3.1.2(b) - v3.1.2(e), v3.1.3(a) - v3.1(3d)	
	UCS 6324	v3.1.2(b) - v3.1.2(e), v3.1.3(a) - v3.1(3d)	Cisco UCS Mini only

### FCOE Storage Interface

<b>Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Emulex	OCE11102	v11.0.0.4	
QLogic	QLE8360, QLE8362	v8.07.00.26.06.8-k	VSP G1000, G800, G600, G400, G200 only
	QLE8440, QLE8442	Bundled	VSP G1000, G800, G600, G400, G200 only
<b>FCOE Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Brocade	VDX 6730	v4.1.3	VSP G1000 & VSP only
Cisco	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(8)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(8)N1(1)	

## 10 Gbps iSCSI Storage Interface

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
Intel	82598EB	v4.2.1-k	
Emulex	OCe11102	v10.4.272.1r v10.6.03r	
	OCe14102	v10.6.03r	
QLogic	QLE8360, QLE8362	v5.03.00.00.06.07-k0	
	QLE8442	v1.712.30-0 v2.7.10.1	
iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only
Brocade	VDX 6730	v4.1.3a	
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v5.2(1)N1(1) - v5.2(1)N1(9), v7.0(0)N1(1) - v7.0(6)N1(1)	

## VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for RHEL 6.7 (X64)

<b>FC Storage Interface</b>				
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>				
Manufacturer	Models	Driver Versions	Notes	
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.	
	UCS 1340, 1380	v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.	
Emulex	LPe11000, LPe11002, LPe1105	v10.6.0.20		
	LPe12000, LPe12002, LPe1205	v10.6.0.20		
	LPe16000, LPe16002, LPe16002B	v10.6.0.20 v11.1.183.21		
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.0.240.0		
	OCe11102	v10.6.0.20		
HPE	403619-B21 QMH2462	v8.07.00.16.06.7-k		
	403621-B21 LPe1105	v10.6.0.20		
	456972-B21 LPe1205-HP	v10.6.0.20		
	650FLB, 650M	v10.6.0.20 v11.1.183.21		
	651281-B21 QMH2572	v8.07.00.16.06.7-k		
	659818-B21 LPe1205A	v10.6.0.20 v11.1.183.21		
	710608-B21 QMH2672	v8.07.00.16.06.7-k		
	AJ763A, AJ763B, 82E AJ762A, AJ762B, 81E	v10.6.0.20		
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.16.06.7-k		
	NC553i, NC553m, CN1100E	v11.1.183.21		
	SN1100E	v10.6.0.20		
	SN1000Q	v8.07.00.16.06.7-k		
	IBM	42D0485, 42D0494	v10.6.0.20	
		42D0501, 42D0510	v8.07.00.16.06.7-k	
44X1940, 44X1942, 44X1945, 44X1947		v8.07.00.16.06.7-k		
46M6065, 46M6068 QMI2572		v8.07.00.16.06.7-k		
Qlogic		QLE2460, QLE2462	v8.07.00.16.06.7-k	
	QLE2560, QLE2562, QLE2564	v8.07.00.16.06.7-k		
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.16.06.7-k		

<b>FC Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b>	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b> , v8.0.1 - <b>v8.0.2f</b> , v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b>	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b	Brocade FOS v8.1.0, v8.1.2c, <b>v8.1.2e</b> , and v8.2.0 are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.0a - v8.2.0b	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, <b>v8.1.2e</b> , and v8.2.0 are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
<b>FCOE Switches (FCF mode)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Cisco	UCS 6120XP, 6140XP, 6248up, 6296up	v3.1(1e)	
	UCS 6324	v3.1(1e)	Cisco UCS Mini only

### FCOE Storage Interface

<b>Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Qlogic	QLE8360, QLE8362	v8.07.00.16.06.7-k	
<b>FCOE Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Any	Generic DCB IP Switch	Any DCB 10GigE FW	VSP G1000 & VSP only
Brocade	VDX 6740	v5.0.1d	VSP G1000 & VSP only
Cisco	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(8)N1(1)	VSP G1000 & VSP only
	UCS 6324	v3.1(1e)	Cisco UCS Mini only



## VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for RHEL 6.6 (X64)

<b>FC Storage Interface</b>				
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>				
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>	
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.12b v1.6.0.18 v1.6.0.23 v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.	
	UCS M81KR	v1.6.0.18 v1.6.0.23 v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.	
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI	v10.2.8020.1		
	LPe16000, LPe16002, LPe16002B	v10.2.8020.1		
	LPm16002B-HI	v10.2.8020.1		
	OCe10102	v10.2.8020.1		
	OCe11102	v10.2.8020.1		
HPE	403619-B21 QMH2462	v8.07.00.08.06.6-k1		
	451871-B21 QMH2562	v8.07.00.08.06.6-k1		
	554M, 554FLB	v10.2.8020.1		
	650FLB, 650M	v10.2.8020.1		
	651281-B21 QMH2572	v8.07.00.08.06.6-k1		
	710608-B21 QMH2672	v8.07.00.16.06.0-k		
	AJ763A, AJ763B, 82E AJ762A, AJ762B, 81E	v10.2.8020.1		
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.08.06.6-k1		
	NC551i, NC551m	v10.2.8020.1		
	SN1100E	v10.2.8020.1		
	SN1000Q	v8.07.00.08.06.6-k1		
	IBM	42D0485, 42D0494	v10.2.8020.1	
		42D0501, 42D0510	v8.07.00.08.06.6-k1	
46M6065, 46M6068		v8.07.00.08.06.6-k1		
QMI2572				
Qlogic	QLE2460, QLE2462	v8.07.00.08.06.6-k1		
	QLE2560, QLE2562, QLE2564	v8.07.00.08.06.6-k1		
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.07.00.08.06.6-k1		
	QLE8360, QLE8362	v8.07.00.08.06.6-k1		

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	

### FCOE Switches (FCF mode)

Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	9250i (FCoE), 9513 (FCoE), 9710 (FCoE), 9718 (FCoE)	v7.3(0)D1(1) - v7.3(1)D1(1)	
	Nexus 5020, 5596UP, 5548up-2232pp, Nexus 5596T-2232TM-E	v7.0(0)N1(1) - v7.0(8)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1)	
	7706 (FCoE), 7710(FCoE), 7718(FCoE)	v7.3(0)D1(1) - v7.3(1)D1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(3a) - v2.2(4c), v2.2(5b) - v2.2(5d), v2.2(6c) - v2.2(8f), v3.1(1e)	
	UCS 6324	v3.0(2c) - v3.0(2d)	Cisco UCS Mini only

### FCOE Storage Interface

Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS M81KR	v1.6.0.18	Must connect to a Cisco UCS top of rack interconnect switch.
FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Cisco	9250i (FCoE), 9513 (FCoE), 9718 (FCoE)	v7.3(0)D1(1) - v7.3(1)D1(1)	
	7710 (FCoE)	v7.3(0)D1(1) - v7.3(1)D1(1)	
	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(3a) - v2.2(4c), v2.2(5b) - v2.2(5d), v2.2(6c) - v2.2(8f), v3.1(1e)	
	UCS 6324	v3.0(2c) - v3.0(2d)	Cisco UCS Mini only

## 10 Gbps iSCSI Storage Interface

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCE10102	v10.2r	VSP G1x00, F1500, Gxx0, Fxx0 only
HP	530SFP+	v1.78.19-0	
	554FLR-SFP	v10.2.477.6-1	
QLogic	QLE8362	v5.04.01.09.00.00-k0	
	QLE8440, QLE8442	v1.78.19-0	
iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only
Brocade	VDX 6730	v4.1.2	
		v4.1.3a	
Cisco	Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(8)N1(1)	
	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v7.0(0)N1(1) - v7.0(8)N1(1)	

## VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for RHEL 6.5 (X64)

<b>FC Storage Interface</b>				
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>				
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>	
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.45 v1.5.0.49 v1.6.0.6 v1.6.0.10 v1.6.0.12 v1.6.0.12b v1.6.0.16 v1.6.0.23	Must connect to a Cisco UCS top of rack interconnect switch.	
	UCS 1340, 1380	v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.	
	UCS M81KR	v1.5.0.45 v1.5.0.49 v1.6.0.6 v1.6.0.10 v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.	
Emulex	LPe11000, LPe11002	v8.3.7.21.4p		
	LPe12000, LPe12002, LPe1205, LPe1205-HI	v8.3.7.21.4p v10.0.803.24 v11.0.240.0		
	LPe16000, LPe16002, LPe16002B	v8.3.5.86.1p v8.3.7.21.4p v8.3.7.33 v10.2.340.16		
	LPe16202	v8.3.7.21.4p		
	LPm16002B-HI	v8.3.7.21.4p		
	OCe10102	v10.0.803.24		
	OCe11102	v10.2.469.0		
HPE	403619-B21 QMH2462	v8.05.00.03.06.5-k2		
	403621-B21 LPe1105	v8.3.7.21.4p v8.3.7.39		
	451871-B21 QMH2562	v8.05.00.03.06.5-k2		
	651281-B21 QMH2572	v8.05.00.03.06.5-k2		
	554M, 554FLB	v8.3.7.39 v10.2.477.17		
	650M, 650FLB	v10.2.477.17		
	AJ763A, AJ763B, 82E AJ762A, AJ762B, 81E	v8.3.7.21.4p v10.0.803.24		
	AK344A, AJ764A, 81Q, 82Q	v8.05.00.03.06.5-k2		
	NC551i, NC551m	v10.2.477.17		
	NC553i, NC553m, CN1100E	v8.3.7.39		
	IBM	46M6065, 46M6068 QMI2572	v8.05.00.03.06.5-k2	
		42D0494	v10.0.803.24	
Qlogic	QLE2460, QLE2462	v8.05.00.03.06.5-k2		
	QLE2560, QLE2562, QLE2564	v8.05.00.03.06.5-k2		
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	v8.05.00.03.06.5-k2 v8.06.00.10.06.0-k v8.07.00.16.06.0-k		
	QME2572	v8.05.00.03.06.5-k2		
	QLE8142	v8.05.00.03.06.0-k v8.06.00.10.06.0-k		
	QLE8152	v8.06.00.10.06.0-k		
	QLE8240, QLE8242	v8.05.00.03.06.5-k2		
	QLE8360, QLE8362	v8.05.00.03.06.5-k2		

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b>	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b> , v8.0.1 - <b>v8.0.2f</b> , v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b>	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b>	Brocade FOS v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b>	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1), v7.2(0)N1(1) - v7.2(1)N1(1), v7.3(0)N1(1) - v7.3(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(8)N1(1)	Cisco Nexus 6001/6004 series requires v6.0(2)N1(2) and above. Nexus 6001T requires v6.0(2)N2(1) and above.
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(2c), v2.2(3a) - v2.2(4c)	
	UCS 6324	v3.0(2c) - v3.0(2d)	Cisco UCS Mini only

<b>FCOE Storage Interface</b>			
<b>Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Brocade	1860	v3.2.4.0	
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.49 v1.6.0.6 v1.6.0.10 v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.5.0.49 v1.6.0.6 v1.6.0.10 v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	OCe10102	v10.0.803.24	
	OCe11102	v8.3.7.21.4p v10.2.469.0	
Qlogic	QLE8152	v8.06.00.10.06.0-k	
<b>FCOE Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Any	Generic DCB IP Switch	Any DCB 10GigE FW	VSP G1000 & VSP only
Brocade	DCX (FCoE)	v7.3.1 - v7.3.1b	VSP G1000 & VSP only
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v7.0(1)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1)	VSP G1000 & VSP only
	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1), v7.2(0)N1(1) - v7.2(1)N1(1), v7.3(0)N1(1) - v7.3(1)N1(1)	VSP G1000 & VSP only
	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v7.0(1)N1(1) - v7.0(8)N1(1)	VSP G1000 & VSP only
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(2c), v2.2(3a) - v2.2(4c)	VSP G1000 & VSP only

## VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for RHEL 6.4 (X64)

<b>FC Storage Interface</b>			
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.45 v1.6.0.12 v1.6.0.12b v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.5.0.45	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe11000, LPe11002	v8.3.5.86.1p	
	LPe12000, LPe12002, LPe1205, LPe1205-HI	v8.3.5.86.1p	
	LPe16000, LPe16002, LPe16002B	v8.3.5.68 v8.3.5.82 v8.3.5.86.1p	
	OCe10102	v8.3.7.18-1	
	OCe11102	v8.3.5.86.1p	
HPE	451871-B21 QMH2562	v8.04.00.08.06.4-k	
	456972-B21 LPe1205	v8.3.5.86.1p	
	590647-B21	v3.0.23.0	
	651281-B21 QMH2572	v8.04.00.08.06.4-k	
	AJ763A, AJ763B, 82E AJ762A, AJ762B, 81E	v8.3.5.86.1p	
	AK344A, AJ764A, 81Q, 82Q	v8.04.00.08.06.4-k v8.04.00.12.06.0-k2-1	
	554M, 554FLB	v10.2.477.17	
IBM	44X1940, 44X1942, 44X1945, 44X1947	v8.04.00.08.06.4-k	
	90Y3554	v8.3.7.29	
Intel	X520	v3.9.15-k	
Qlogic	QLE2460, QLE2462	v8.04.00.08.06.4-k	
	QLE2560, QLE2562, QLE2564	v8.04.00.08.06.4-k v8.04.00.12.06.0-k2-1	
	QLE2660, QLE2662, QLE2670, QLE2672	v8.04.00.06.06.0-k v8.04.00.08.06.4-k v8.05.00.06.06.0-k	
	QLE8300	v8.04.00.08.06.4-k	
	QLE8142	v8.05.00.03.06.0-k	
	QME2572	v8.04.00.08.06.4-k	

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v5.1(3)N1(1), v5.1(3)N1(1a), v5.1(3)N2(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(1b), v5.2(1)N1(2), v5.2(1)N1(2a), v5.2(1)N1(3) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a),	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.1(1a) - v2.1(1f), v2.2(3a) - v2.2(4c), v3.1(1e) - v3.1(1l)	
	Nexus 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a)	
IBM	EN4093R	v7.7.5.0	



<b>FCOE Storage Interface</b>			
<b>Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.45	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.5.0.45	
Emulex	OCe10102	v8.3.7.18-1	
	OCe11102	v8.3.5.86.1p v10.0.803.24	
<b>FCOE Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Any	Generic DCB IP Switch	Any DCB 10GigE FW	VSP G1000 & VSP only
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T-2232TM-E	v5.1(3)N1(1), v5.1(3)N1(1a), v5.1(3)N2(1), v5.1(3)N2(1a), v5.1(3)N2(1b), v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(7), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	VSP G1000 & VSP only
	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2),v6.0(2)N1(2a)	VSP G1000 & VSP only
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.1(1a) - v2.1(1f), v2.2(3a) - v2.2(4c)	VSP G1000 & VSP only

<b>10 Gbps iSCSI Storage Interface</b>			
<b>iSCSI Adapters</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Any	10 GbE NIC	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
<b>iSCSI Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only

## VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for RHEL 6.3 (X64)

<b>FC Storage Interface</b>			
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.1 v1.5.0.20	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.5.0.1 v1.5.0.20 v1.5.0.45	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe11000, LPe11002	v8.3.5.68.5p	
	LPe12000, LPe12002, LPe1205, LPe1205-HI	v8.3.5.68 v8.3.5.68.5p	
	LPe16000, LPe16002, LPe16002B	Bundled v8.3.5.68.5p	
HPE	403619-B21 QMH2462	v8.03.07.03-k v8.04.00.04.06.3-k v8.04.00.09.06.0	
	403621-B21 LPe1105	v8.3.5.68.5p	
	451871-B21 QMH2562	v8.03.07.03-k v8.04.00.04.06.3-k	
	456972-B21 LPe1205	v8.3.5.68.5p	
	554M, 554FLB	v8.3.23 v8.3.5.86 v8.3.5.86.4p	
	651281-B21 QMH2572	v8.03.07.03-k v8.04.00.04.06.3-k	
	AJ763A, AJ763B, 82E AJ762A, AJ762B, 81E	v8.3.5.68 v8.3.5.68.5p	
	AK344A, AJ764A, 81Q, 82Q	v8.03.7.13.06.0-k v8.04.00.04.06.3-k	
	NC553i, NC553m, CN1100E	v8.3.23	
	IBM	41Y8527	v8.04.00.04.06.3-k
44X1940, 44X1942, 44X1945, 44X1947		v8.04.00.04.06.3-k	
46M6140		v8.3.5.68.5p	
69Y1938		v8.04.00.04.06.3-k	
88Y6370		v3.1.0.1	
90Y3554		v8.3.5.68.5p	
95Y2375		v8.3.5.68.5p	
95Y2379		v3.2.3.0	
Qlogic	QLE2460, QLE2462	v8.04.00.04.06.3-k	
	QLE2560, QLE2562, QLE2564	v8.03.7.13.06.0-k v8.04.00.04.06.3-k	
	QLE2660, QLE2662, QLE2670, QLE2672	v8.04.00.04.06.3-k	
	QLE8142	v8.03.7.13.11.1-k	
	QLE8360, QLE8362	v8.05.00.03.06.0-k	
	QME2572	v8.04.00.04.06.3-k	

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b>	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b> , v8.0.1 - <b>v8.0.2f</b> , v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.1	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b>	Brocade FOS v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b>	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
IBM	69Y1930	v9.1.0.18.0	
	88Y6381	v7.0.0_pha	
	88Y6374	v7.0.0_pha4	

FCOE Storage Interface			
Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.20	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.5.0.20	Must connect to a Cisco UCS top of rack interconnect switch.
Qlogic	QLE8360, QLE8362	v8.05.00.03.06.0-k	
FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic DCB IP Switch	Any DCB 10GigE FW	VSP G1000 & VSP only
Cisco	9250i (FCoE)	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1)	Cisco OS v6.2(15) is no longer supported.
	9513 (FCoE)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1)	Cisco OS v6.2(15) is no longer supported.
	9706 (FCoE)	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(21),	Cisco OS v6.2(15) is no longer supported.
	9710 (FCoE)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1)	Cisco OS v6.2(15) is no longer supported.
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.0(5a) - v2.0(5f), v2.1(1a) - v2.1(1f)	VSP G1000 & VSP only

## VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for RHEL 6.2 (X64)

<b>FC Storage Interface</b>				
<b>Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)</b>				
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>	
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.20 v1.5.0.45	Must connect to a Cisco UCS top of rack interconnect switch.	
	UCS M81KR	v1.5.0.1		
	UCS P81E	v1.5.0.20		
Emulex	LPe11000, LPe11002	v8.3.5.45.4p		
	LPe12000, LPe12002, LPe1205, LPe1205-HI	v8.3.5.65 v8.3.5.45.4p		
	LPe16000, LPe16002, LPe16002B	v8.3.5.45.4p		
	OCe10102	v8.3.5.45.4p v8.3.5.68		
	OCe11102	v8.3.5.45.4p		
HPE	403619-B21 QMH2462	v8.03.07.13.06.0		
	403621-B21 LPe1105	v8.3.5.45.4p		
	451871-B21 QMH2562	v8.04.00.06.06.0-k		
	456972-B21 LPe1205	v8.3.5.45.4p		
	554M, 554FLB	v8.3.5.77.1p		
	590647-B21	v3.0.3.0		
	AJ763A, AJ763B, 82E AJ762A, AJ762B, 81E	v8.3.5.65 v8.3.5.45.4p		
	AK344A, AJ764A, 81Q, 82Q	v8.03.07.05.06.2-k		
	NC553i, NC553m, CN1100E	v8.3.5.45-4p v8.3.5.77.1p		
	Qlogic	QLE2460, QLE2462	v8.03.07.05.06.2-k	
		QLE2560, QLE2562, QLE2564	v8.03.07.05.06.2-k	
QLE2660, QLE2662, QLE2670, QLE2672		v8.04.00.06.06.0-k		
QLE8152		v8.03.01.06 v8.03.07.13.06.0-k		
QLE8240, QLE8242		v8.03.07.05.06.2-k		

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b>	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - <b>v7.4.2d</b> , v8.0.1 - <b>v8.0.2f</b> , v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b> , v8.2.1	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b>	Brocade FOS v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, <b>v8.1.2f</b>	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and <b>v8.1.2e</b> are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
IBM	69Y1930	v9.1.0.18.0	
	88Y6381	v7.0.0_pha	
	88Y6374	v7.0.0_pha4	
FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TME, 5596up	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.0(4a), v2.0(5a), v2.1(1a) - v2.1(1f)	
	Nexus 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(5), v7.0(0)N1(1) - v7.0(8)N1(1)	Cisco Nexus 6001/6004 series requires v6.0(2)N1(2) and above. Nexus 6001T requires v6.0(2)N2(1) and above.

<b>FCOE Storage Interface</b>			
<b>Converged Network Adapters (CNA)</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Driver Versions</b>	<b>Notes</b>
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.20 v1.5.0.45	Must connect to a Cisco UCS top of rack interconnect switch.
	P81E	v1.5.0.20	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	OCe10102	v8.2.0.106.1p v8.3.5.68 v8.3.5.45.4p	
	OCe11102	v8.3.5.45.4p	
Qlogic	QLE8240, QLE8242	v8.03.07.05.06.2-k	
	QLE8152	v8.03.01.06 v8.03.07.13.06.0-k	
<b>FCOE Switches</b>			
<b>Manufacturer</b>	<b>Models</b>	<b>Firmware Versions</b>	<b>Notes</b>
Any	Generic DCB IP Switch	Any DCB 10GigE FW	VSP G1000 & VSP only
Cisco	9250i (FCoE)	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1)	Cisco OS v6.2(15) is no longer supported.
	9513 (FCoE)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1)	Cisco OS v6.2(15) is no longer supported.
	9706 (FCoE)	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(21),	Cisco OS v6.2(15) is no longer supported.
	9710 (FCoE)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1)	Cisco OS v6.2(15) is no longer supported.
	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM- E, 5596up	v5.1(3)N1(1), v5.1(3)N1(1a), v5.1(3)N2(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(1b), v5.2(1)N1(2), v5.2(1)N1(2a), v5.2(1)N1(3) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1), v6.0(2)N2(1b), v6.0(2)N2(2) - v6.0(2)N2(5), v7.0(0)N1(1), v7.0(1)N1(1) - 7.0(8)N1(1)	VSP G1000 & VSP only
	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1), v6.0(2)N2(1b), v6.0(2)N2(2), v6.0(2)N2(3) - v6.0(2)N2(5), v7.0(0)N1(1), v7.0(1)N1(1) - v7.0(8)N1(1)	