



SuSE Linux Enterprise Server (SLES) Support Matrix Hitachi VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM

Note: Configurations added since the last matrix will be shown in red text.

Introduction

Use this interoperability matrix to check whether a proposed customer configuration is supported. Each tab contains a set of components that together comprise an Hitachi Vantara-supported solution. This includes operating system (OS) and maintenance release, host bus adapter (HBA), HBA driver, and storage area network (SAN) switches, both Fibre channel (FC) and Fibre channel over Ethernet (FCoE).

Note: The arrays supported now include the VSP F700, F900, G700, G900, F350, F370, G350, and G370.

Note on the 16 & 32 Gb Interfaces:

- The 32Gb interface is only available on the GX00 and FX00 arrays. It is supported with both 16 & 32Gb SFPs and operates at a maximum of 32Gbps.
- The VSP and HUS VM do not have 16Gb FC interfaces.
- With SVOS 7, for Direct connection to 16Gb or 32Gb FC you must set the storage port to Fabric = OFF and Connection Type P-to-P (Point to Point)

Note: The Hitachi FIVE FC HBA also has an alternate option of Fabric Emulation. When it is configured in this mode it should be treated as switch attached and the storage port should be set to Fabric = On and Connection Type = P-to-P

If a combination does not appear on the OS support matrix, the customer's Hitachi Vantara Sales Engineer (SE) or other Hitachi field service employee must submit an Interoperability Support Request in order to gain support for the new configuration.

Legal Disclaimer

This information is subject to change without notice. The information contained in this document is provided by Hitachi Vantara for general information purposes only and is based on information as of the date of distribution (indicated by the date above). Hitachi Vantara makes no express or implied warranties of any kind whatsoever regarding the contents of this Document or the performance of the products referred to in these documents and Hitachi Vantara expressly disclaims all warranties including, without limitation, the implied warranties of satisfactory quality, merchantability or fitness for a particular purpose, the statutory warranty against infringement, and any warranty of title. Hitachi Vantara will have no liability whatsoever for any direct loss or damage (but excluding any liability for death, personal injury or fraudulent misrepresentation) or for any indirect, special, incidental or consequential damages, including but not limited to loss of data or records, lost profits or other economic loss, arising out of or in connection with the use of this information even if such loss was foreseeable or Hitachi Vantara had been advised of the possibility of such loss.

VSP G1x00, F1500, Gxx0, Fxx0 support for SLES 15 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe16000, LPe16002, LPe16002B	v12.0.0.1	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v12.0.0.1	
	OCe14102	v12.0.0.1	
HPE	3530C	v12.0.0.1	
	3830C	v10.00.00.06-k	
	SN1000Q	v10.00.00.06-k	
	SN1100Q	v10.00.00.06-k	
	SN1600Q	v10.00.00.06-k	
	SN1100E	v12.0.0.1	
	SN1200E	v12.0.0.1	
	SN1600E	v12.0.0.1	
IBM	00Y3337, 00Y3341	v10.00.00.06-k	
	95Y2386, 95Y2391	v12.0.0.1	
QLogic	QLE2660, QLE2662, QLE2670, QLE2672	v10.00.00.06-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v10.00.00.06-k	
	QLE8360, QLE8362	v10.00.00.06-k	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G610	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G620, X6	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148S, 9706	v8.2(1) - v8.2(2)	
	9250i	v8.2(1) - v8.2(2)	
	9396S	v8.2(1) - v8.2(2)	
	9710	v8.2(1) - v8.2(2)	
	9718	v8.2(1) - v8.2(2)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.2(1) - v8.2(2)	
FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6740	v6.0.1a	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(1)N1(1)	
FCOE Storage Interface			
Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe14102	v12.0.0.1	
QLogic	QLe8362	v10.00.00.06-k	
FCOE Switches			
Manufacturer	Models	Driver Versions	Notes
Brocade	VDX 6740	v6.0.1a	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(1)N1(1)	

10 Gbps iSCSI Storage Interface

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
Emulex	OCe14102	v11.4.0.1	
QLogic	QLe8362	v5.04.00-k6	
iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only

VSP G1x00, F1500, Gxx0, Fxx0 support for SLES 12 SP3 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe12000, LPe12002, LPe1205	v11.4.0.5	
	LPe16000, LPe16002, LPe16002B	v11.4.0.5	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.4.0.5	
	OCe11102	v11.4.0.5	
HPE	AJ763A, AJ763B, 82E		
	AJ762A, AJ762B, 81E	v11.4.0.5	
	AK344A, AJ764A, 81Q, 82Q	v9.00.00.00-k	
	SN1000Q	v9.00.00.00-k	
	SN1100Q	v9.00.00.00-k	
	SN1600Q	v9.00.00.00-k	
	SN1100E	v11.4.0.5	
	SN1200E	v11.4.0.5	
IBM	42D0485, 42D0494	v11.4.0.5	
	42D0501, 42D0510	v9.00.00.00-k	
QLogic	QLE2560, QLE2562, QLE2564	v9.00.00.00-k	
	QLE2660, QLE2662, QLE2670, QLE2672	v9.00.00.00-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v9.00.00.00-k	
	QLE8360, QLE8362	v9.00.00.00-k	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v7.4.2c - v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b	Brocade FOS v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported.
	G630	v8.2.0a - v8.2.0b, v8.2.1a	Brocade FOS v8.2.0, and v8.2.1 are not supported.
Cisco	9148S, 9706	v8.1(1) - v8.1(1a), v8.3(1)	
	9250i	v8.1(1) - v8.1(1a), v8.3(1)	
	9396S	v8.1(1) - v8.1(1a), v8.3(1)	
	9710	v8.1(1) - v8.1(1a), v8.3(1)	
	9718	v8.1(1) - v8.1(1a), v8.3(1)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.3(1)	
FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6740	v6.0.1a	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(1)N1(1)	
FCOE Storage Interface			
Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	v11.4.0.5	
QLogic	QLe8362	v9.00.00.00-k	
FCOE Switches			
Manufacturer	Models	Driver Versions	Notes
Brocade	VDX 6740	v6.0.1a	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(1)N1(1)	

10 Gbps iSCSI Storage Interface

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
Emulex	OCe11102	v11.2.1.0	
QLogic	QLe8362	v5.04.00-k6	
iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for SLES 12 SP2 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.34	Must connect to a Cisco UCS or UCS Mini top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.34	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe12000, LPe12002, LPe1205	v11.1.0.1	
	LPe16000, LPe16002, LPe16002B	v11.1.0.1	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.1.0.1	
HPE	3820C	v2.11.9	
	403619-B21, QMH2462	v8.07.00.33-k	
	451871-B21	v8.07.00.33-k	
	QMH2562	v8.07.00.34.12.0-k1	
	651281-B21	v8.07.00.33-k	
	QMH2572	v8.07.00.34.12.0-k1	
	659818-B21, LPe1205A	v11.1.0.1	
	710608-B21	v8.07.00.33-k	
	QMH2672	v8.07.00.34.12.0-k1	
	AJ763A, AJ763B, 82E		
	AJ762A, AJ762B, 81E	v11.1.0.1	
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.33-k v8.07.00.34.12.0-k1	
	SN1000Q	v8.07.00.33-k v8.07.00.34.12.0-k1	
	SN1100Q	v8.07.00.33-k v8.07.00.34.12.0-k1	
SN1100E	v11.1.0.1		
SN1600Q	v8.07.00.42.12.0-k4		
IBM	42D0485, 42D0494	v11.1.0.1	
	42D0501, 42D0510	v8.07.00.33-k	
Qlogic	QLE2560, QLE2562, QLE2564	v8.07.00.33-k v8.07.00.34.12.0-k1	
	QLE2660, QLE2662, QLE2670, QLE2672	v8.07.00.33-k v8.07.00.34.12.0-k1 v8.07.00.39.12.0-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v8.07.00.33-k v8.07.00.34.12.0-k1	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d	Brocade FOS v7.4.2b is not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d , v8.0.1 - v8.0.2f , v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G630	v8.2.0a - v8.2.0b	Brocade FOS v8.2.0 is not supported.

Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9132T	v8.2(1)	
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
9706 (32Gb), 9710 (32Gb), 9718 (32Gb)		v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	

FCOE Switches (FCF mode)

Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6730	v4.1.3a	
Cisco	UCS 6120XP, 6140XP, 6248up, 6296up	v3.1.2(b) - v3.1.2(e), v3.1.3(a)	
	Nexus 6001p-2248pq, 6001T, 6004	v7.3(0)N1(1) - v7.3(1)N1(1)	
	UCS 6324	v3.1.2(b) - v3.1.2(e), v3.1.3(a)	Cisco UCS Mini only

FCOE Storage Interface

Converged Network Adapters (CNA)

Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	v11.1.0.1	
QLogic	QLe8362	v8.07.00.33-k	

FCOE Switches

Manufacturer	Models	Driver Versions	Notes
Brocade	VDX 6740	v6.0.1a	
	G620, X6	v8.2.0a	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1)	

10 Gbps iSCSI Storage Interface

iSCSI Adapters

Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
Emulex	OCe11102	v11.0.0.0	
Intel	X520	v4.2.1-k	
QLogic	QLe8362	v5.04.00-k6	

iSCSI Switches

Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only
Brocade	Brocade VDX 6740	v6.0.1a	
Cisco	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v7.3(0)N1(1) - v7.3(1)N1(1)	

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for SLES 12 SP1 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe12000, LPe12002, LPe1205	v10.5.0.2 v11.1.218.0 v11.2.156.18	
	LPe16000, LPe16002, LPe16002B	v10.5.0.2 v10.6.144.21 v11.0.240.0 v11.1.218.0 v11.2.156.18	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.0.240.0 v11.1.0.1 v11.1.183.21 v11.2.156.18	
	Oce11102	v10.5.0.2	
	Oce14102	v10.7.0.1	
	HPE	3530c	v11.1.183.21
3830C		v8.07.00.34.12.0-k1	
QMH2682			
650FLB, 650M		v10.5.0.2	
659818-B21, LPe1205A		v10.5.0.2	
718203-B21			
LPe1605		v10.5.0.2	
AJ763A, AJ763B, 82E			
AJ762A, AJ762B, 81E		v10.5.0.2	
AK344A, AJ764A, 81Q, 82Q		v8.07.00.18-k	
SN1100E		v10.5.0.2	
SN1000Q	v8.07.00.18-k		
IBM	42D0485, 42D0494	v10.5.0.2	
	42D0501, 42D0510	v8.07.00.18-k	
Qlogic	QLE2460, QLE2462	v8.07.00.18-k	
	QLE2560, QLE2562, QLE2564	v8.07.00.18-k v8.07.00.34.12.0-k1	
	QLE2660, QLE2662, QLE2670, QLE2672	v8.07.00.18-k v8.07.00.34.12.0-k v8.07.00.39.12.0-k	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2764	v8.07.00.18-k v8.07.00.34.12.0-k v8.07.00.39.12.0-k	
	QLE8360, QLE8362	v8.07.00.18-k	

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9132T	v8.2(1)	
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	Nexus 7706 (FCoE), 7710 (FCoE)	v8.1(1)	

FCOE Storage Interface

Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	v10.5.0.2	
	OCe14102	v10.5.0.2	
QLogic	QLe8362	v8.07.00.18-k	

FCOE Switches			
Manufacturer	Models	Driver Versions	Notes
Brocade	VDX 6740	v6.0.1a	
Cisco	9132T, 9250i	v8.2(1)	
	Nexus 5672up, 5672up-2248pq	v7.1(0)N1(1a) - v7.2(1)N1(1), v7.3(0)N1(1)	
	Nexus 7706 (FCoE), 7710 (FCoE)	v8.2(1)	

10 Gbps iSCSI Storage Interface

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Any	10 GbE NIC	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only

iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for SLES 12 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.18 v1.6.0.25	Must connect to a Cisco UCS or UCS Mini top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.18 v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe12000, LPe12002, LPe1205, LPe1205-HI	v10.2.8040.1 v11.0.240.0	
	LPe16000, LPe16002, LPe16002B	v10.2.8040.1	
	LPm16002B-HI	v10.2.8040.1	
	OCe11102	v10.2.8040.1	
	Oce14102	v10.2.8040.1	
HPE	554M, 554FLB	v10.2.477.17	
	650FLB, 650M	v10.2.477.17	
	AJ763A, AJ763B, 82E		
	AJ762A, AJ762B, 81E	v10.2.8040.1	
	AK344A, AJ764A, 81Q, 82Q	v8.07.00.08.12.0-k	
	NC551i, NC551m	v10.2.477.17	
	SN1100E	v10.2.8040.1	
	SN1000Q	v8.07.00.08.12.0-k	
IBM	42D0485, 42D0494	v10.2.8040.1	
	42D0501, 42D0510	v8.07.00.08.12.0-k	
Qlogic	QLE2560, QLE2562, QLE2564	v8.07.00.08.12.0-k	
	QLE2660, QLE2662, QLE2670, QLE2672	v8.07.00.08.12.0-k	
	QLE8240, QLE8242	v8.07.00.08.12.0-k	
	QLE8360, QLE8362	v8.07.00.08.12.0-k	
	QME8242, QLE8262, QME8262, QMD8262-k	v8.07.00.08.12.0-k	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d , v8.0.1 - v8.0.2f , v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6730 (8G)	v4.1.2	
Cisco	Nexus 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(8)N1(1)	Cisco Nexus 6001/6004 series requires v6.0(2)N1(2) and above. Nexus 6001T requires v6.0(2)N2(1) and above.
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(5b) - v2.2(6f), v2.2(7b), v2.2(8a), v3.1(1e) - v3.1(1l)	
	UCS 6324	v3.1(1e) - v3.1(1l)	Cisco UCS Mini only
FCOE Storage Interface			
Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.18	Must connect to a Cisco UCS or UCS Mini top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.18	Must connect to a Cisco UCS top of rack interconnect switch.
FCOE Switches			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 6120XP, 6140XP, 6248up, 6296up	v2.2(5b) - v2.2(6f), v2.2(7b), v2.2(8a), v3.1(1e) - v3.1(1l)	
	UCS 6324	v3.1(1e) - v3.1(1l)	Cisco UCS Mini only
10 Gbps iSCSI Storage Interface			
iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Qlogic	QLE8360, QLE8362	v5.04.00.00.12.0-k3	
iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only
Cisco	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(8)N1(1)	

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for SLES 11 SP4 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.6.0.25 v1.6.0.34	Must connect to a Cisco UCS or UCS Mini top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.25 v1.6.0.34	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe12000, LPe12002, LPe1205	v10.4.8000.0	
	LPe16000, LPe16002, LPe16002B	v10.4.8000.0	
	LPe31000, LPe31002, LPe31004, LPe32000, LPe32002	v11.0.240.0	
HPE	3530c	v11.1.183.21	
	3820C	v2.11.9	
	3830C		
	QMH2682	v8.07.00.34.11.3-k1	
	554M, 554FLB	v10.4.8000.0	
	650FLB, 650M	v10.4.8000.0	
	659818-B21, LPe1205A	v10.4.8000.0	
	AJ763A, AJ763B, 82E AJ762A, AJ762B, 81E AK344A, AJ764A, 81Q, 82Q	v10.4.8000.0 v8.07.00.18-k	
IBM	42D0485, 42D0494	v10.4.8000.0	
	42D0501, 42D0510	v8.07.00.18-k	
Qlogic	QLE2460, QLE2462	v8.07.00.18-k	
	QLE2560, QLE2562, QLE2564	v8.07.00.18-k	
	QLE2660, QLE2662, QLE2670, QLE2672	v8.07.00.18-k	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and v8.1.2e are are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Cisco	UCS 6120XP, 6140XP, 6248up, 6296up	v3.1(1e) - v3.1(1l), v3.1.2(b) - v3.1.2(e), v3.1.3(a)	
	UCS 6324	v3.1(1e) - v3.1(1l), v3.1.2(b) - v3.1.2(e), v3.1.3(a)	Cisco UCS Mini only

10 Gbps iSCSI Storage Interface

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	v10.4.114.0	VSP G1x00, F1500, Gxx0, Fxx0 only

iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only
Brocade	Brocade VDX 6740	v6.0.1a	
Cisco	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v7.3(0)N1(1) - v7.3(1)N1(1)	

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for SLES 11 SP3 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.45 v1.5.0.49 v1.6.0.6 v1.6.0.10 v1.6.0.12 v1.6.0.12b v1.6.0.16	Must connect to a Cisco UCS or UCS Mini top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.5.0.45 v1.5.0.49 v1.6.0.6 v1.6.0.10 v1.6.0.12 v1.6.0.12b v1.6.0.18 v1.6.0.25	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe11000, LPe11002	v8.3.7.10.6p	
	LPe12000, LPe12002, LPe1205	v8.3.5.68.5p v8.3.7.10.6p	
	LPe1205A-HI	v8.3.7.10.6p	
	LPe1205-HI	v8.3.7.10.6p	
	LPe16000, LPe16002, LPe16002B	v8.3.7.10.6p v10.0.803.24	
	LPm16002B-HI	v8.3.7.10.6p	
	OCe10102	v8.3.7.10.6p v10.0.803.24	
	OCe11102	v8.3.7.10.6p v10.2.370.12	
HPE	403621-B21, LPe1105	v8.3.7.24.2p	
	456972-B21, LPe1205	v8.3.7.24.2p	
	659818-B21, LPe1205A	v8.3.7.24.2p	
	A8003A, A8003B, FC2242SR	v8.3.5.68.5p	
	A8002A, A8002B, FC2142SR	v8.3.7.10.6p	
	AE311A, AE312A, FC1142SR, FC1242SR	v8.04.00.13.11.3-k	
	AJ763A, AJ763B, 82E	v8.3.5.68.5p	
	AJ762A, AJ762B, 81E	v8.3.7.10.6p	
	AK344A, AJ764A, 81Q, 82Q	v8.04.00.13.11.3-k v8.06.00.10.11.1-k v8.07.00.08.11.3-k2	
	SN1100E	v8.3.7.10.6p	
SN1000Q	v8.04.00.13.11.3-k		
IBM	39R6525, 39R6527	v8.04.00.13.11.3-k	
	42C2069, 42C2071	v8.3.5.68.5p v8.3.7.10.6p	
	42D0485, 42D0494	v8.3.5.68.5p v8.3.7.10.6p	
	42D0501, 42D0510	v8.04.00.13.11.3-k v8.06.00.10.11.1-k v8.07.00.08.11.3-k2	

Qlogic	QLE2460, QLE2462	v8.04.00.13.11.3-k	
	QLE2560, QLE2562, QLE2564	v8.04.00.13.11.3-k v8.06.00.10.11.1-k v8.07.00.08.11.3-k2	
	QLE2660, QLE2662, QLE2670, QLE2672	v8.03.07.07-k v8.04.00.13.11.3-k	
	QLE8142	v8.06.00.10.11.1-k	
	QLE8152	v8.06.00.10.11.1-k	
	QLE8240, QLE8242	v8.04.00.13.11.3-k	
	QLE8360, QLE8362	v8.04.00.13.11.3-k v8.07.00.16.11.3-k	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d , v8.0.1 - v8.0.2f , v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6730 (8G)	v4.0.1, v4.1.2	
Cisco	9250i (FCoE)	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1)	Cisco OS v6.2(15) is no longer supported.
	9513 (FCoE)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1)	Cisco OS v6.2(15) is no longer supported.
	9706 (FCoE)	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(21)	Cisco OS v6.2(15) is no longer supported.
	9710 (FCoE), 9718 (FCoE)	v6.2(7) - v6.2(13b), v6.2(17) - v6.2(21)	
	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1), v7.3(0)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(5), v7.0(0)N1(1) - v7.0(8)N1(1)	Cisco Nexus 6001/6004 series requires v6.0(2)N1(2) and above. Nexus 6001T requires v6.0(2)N2(1) and above.
	Nexus 7710 (FCoE)	v7.3(0)D1(1)	
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(3a) - v2.2(3d), v2.2(5b) - v2.2(6f), v2.2(7b), v2.2(8a)	
UCS 6324	v3.0(2c)	Cisco UCS Mini only	

FCOE Storage Interface			
Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Brocade	1020	v3.1.2.1	
	1860	v3.2.3.0 v3.2.4.0	
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.45 v1.5.0.49 v1.6.0.6 v1.6.0.10 v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS 1340, 1380	v1.6.0.12 v1.6.0.12b	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.5.0.45 v1.5.0.49 v1.6.0.6 v1.6.0.10 v1.6.0.12 v1.6.0.12b v1.6.0.18	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	OCe10102	v8.3.7.10.6p v10.0.803.24	
	OCe11102	v8.3.7.10.6p v10.2.370.12 v10.6.144.21	
QLogic	QLE8142	v8.06.00.10.11.1-k	
	QLE8152	v8.06.00.10.11.1-k	
	QLE8360, QLE8362	v8.04.00.13.11.3-k v8.07.00.16.11.3-k	

FCOE Switches				
Manufacturer	Models	Driver Versions	Notes	
Any	Generic DCB IP Switch	Any DCB 10GigE FW		
Brocade	DCX (FCoE)	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.0c, v7.3.1 - v7.3.1d	VSP G1000 & VSP only	
Cisco	9250i (FCoE)	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1)	Cisco OS v6.2(15) is no longer supported.	
	9513 (FCoE)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1)	Cisco OS v6.2(15) is no longer supported.	
	9706 (FCoE)	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(21)	Cisco OS v6.2(15) is no longer supported.	
	9710 (FCoE), 9718 (FCoE)	v7.3(0)D1(1) - v7.3(1)D1(1)		
	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T- 2232TM-E	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1)		
	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1), v7.3(0)N1(1)	VSP G1000 & VSP only	
	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(5), v7.0(0)N1(1) - v7.0(8)N1(1)		
	Nexus 7710 (FCoE)	v7.3(0)D1(1) - v7.3(1)D1(1)		
UCS 6120XP, 6140XP, 6248up, 6296up	v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(3a) - v2.2(3d), v2.2(5b) - v2.2(6f), v2.2(7b), v2.2(8a)			

10 Gbps iSCSI Storage Interface

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCE11102	v10.2.365.0	VSP G1x00, F1500, Gxx0, Fxx0 only

iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	
Cisco	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(6)N1(1)	VSP G1x00, F1500, Gxx0, Fxx0 only

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for SLES 11 SP2 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.2 v1.5.0.45	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS M81KR	v1.5.0.2 v1.5.0.20 v1.5.0.45	Must connect to a Cisco UCS top of rack interconnect switch.
	UCS P81E	v1.5.0.1 v1.5.0.20	Must connect to a Cisco UCS top of rack interconnect switch.
Emulex	LPe11000, LPe11002	v8.3.5.48.2p v8.3.5.48.3p	
	LPe12000, LPe12002, LPe1205	v8.3.5.48.2p v8.3.5.48.3p v8.3.5.68	
	LPe1205A-HI, LPe1205-HI	v8.3.5.48.2p	
	LPe16000, LPe16002, LPe16002B	v8.3.5.48.2p v8.3.5.68	
	LPm16002B-HI	v8.3.7.10.6p	
	OCe10102	v8.3.5.48.2p v8.3.5.68	
	OCe11102	v8.3.5.48.2p	
HPE	403619-B21, QMH2462	v8.03.07.07-k	
	451871-B21, QMH2562	v8.03.07.07-k	
	554M, 554FLB	v8.3.5.86 v8.3.5.77.1p	
	A8003A, A8003B, FC2242SR, A8002A, A8002B, FC2142SR	v8.3.5.48.2p v8.3.5.48.3p	
	AE311A, AE312A, FC1142SR, FC1242SR	v8.03.07.07-k	
	AJ763A, AJ763B, 82E, AJ762A, AJ762B, 81E	v8.3.5.48.2p v8.3.5.48.3p v8.3.5.68	
	AK344A, AJ764A, 81Q, 82Q	v8.03.01.15.11.0.0-k4 v8.03.07.07-k v8.03.7.13.11.1-k v8.05.00.06.06.0-k	
IBM	39M5894, 39M5895	v8.03.01.15.11.0.0-k4 v8.03.07.07-k	
	39R6525, 39R6527	v8.03.07.07-k	
	42C2069, 42C2071	v8.3.5.48.2p v8.3.5.48.3p	
	42D0485, 42D0494	v8.3.5.48.2p v8.3.5.48.3p v8.3.5.68	
	42D0501, 42D0510	v8.03.01.15.11.0.0-k4 v8.03.07.07-k v8.03.7.13.11.1-k v8.05.00.06.06.0-k	

Qlogic	QLA2460, QLA2462	v8.03.01.15.11.0.0-k4 v8.03.07.07-k	
	QLE2460, QLE2462	v8.03.07.07-k	
	QLE2560, QLE2562, QLE2564	v8.03.01.15.11.0.0-k4 v8.03.07.07-k v8.03.7.13.11.1-k v8.05.00.06.06.0-k	
	QLE2660, QLE2662, QLE2670, QLE2672	v8.04.00.06.11.1-k v8.05.00.03.11.1-k	
	QLE8142	v8.05.00.03.06.0-k	
	QLE8152	v8.03.07.13.11.1-k	

FC Switches

Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5100, 5300, 7800, DCX, DCX-4s	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d	Brocade FOS v7.2.0, and v7.4.2b are not supported.
	6505, 6510, 6520, 7840, DCX 8510	v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v7.4.2c - v7.4.2d , v8.0.1 - v8.0.2f , v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v7.2.0, v7.4.2b, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
Cisco	9148, 9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	
	9706 (32Gb), 9710 (32Gb), 9718 (32Gb)	v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2)	

FCOE Switches (FCF mode)

Manufacturer	Models	Firmware Versions	Notes
Cisco	9250i (FCoE)	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1)	Cisco OS v6.2(15) is no longer supported.
	9513 (FCoE)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1)	Cisco OS v6.2(15) is no longer supported.
	9706 (FCoE)	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(21)	Cisco OS v6.2(15) is no longer supported.
	9710 (FCoE)	v6.2(7) - v6.2(13b), v6.2(17) - v6.2(21)	Cisco OS v6.2(15) is no longer supported.
	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(7)N1(1), v7.1(0)N1(1a) - v7.2(1)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(7)N1(1), v7.1(0)N1(1a) - v7.2(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(5), v7.0(0)N1(1) - v7.0(7)N1(1)	Cisco Nexus 6001/6004 series requires v6.0(2)N1(2) and above. Nexus 6001T requires v6.0(2)N2(1) and above.
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.0(2m), v2.0(2q), v2.0(3a), v2.0(4a), v2.0(5a), v2.1(1a), v2.1(3a) - v2.1(3g)	

FCOE Storage Interface				
Converged Network Adapters (CNA)				
Manufacturer	Models	Driver Versions	Notes	
Cisco	UCS 1225, 1225T, 1227, 1240, 1280, 1285	v1.5.0.2 v1.5.0.45	Must connect to a Cisco UCS top of rack interconnect switch.	
	UCS M81KR	v1.5.0.20 v1.5.0.45	Must connect to a Cisco UCS top of rack interconnect switch.	
	UCS P81E	v1.5.0.20	Must connect to a Cisco UCS top of rack interconnect switch.	
Emulex	OCe10102	v8.3.5.48.2p v8.3.5.68		
	OCe11102	v8.3.5.48.2p		
QLogic	QLE8142	v8.05.00.03.06.0-k		
	QLE8152	v8.03.07.13.11.1-k		
	QLE8240, QLE8242	v8.03.07.07-k		
	QLE8360, QLE8362	v8.05.00.03.11.1-k		
FCOE Switches				
Manufacturer	Models	Firmware Versions	Notes	
Any	Generic DCB IP Switch	Any DCB 10GigE FW		
Brocade	DCX (FCoE)	v7.2.0a - v7.2.1b, v7.3.0 - v7.3.0a, v7.3.1 - v7.3.1a	VSP G1000 & VSP only	
Cisco	9250i (FCoE)	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1)	Cisco OS v6.2(15) is no longer supported.	
	9513 (FCoE)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1)	Cisco OS v6.2(15) is no longer supported.	
	9706 (FCoE)	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(21)	Cisco OS v6.2(15) is no longer supported.	
	9710 (FCoE)	v6.2(7) - v6.2(13b), v6.2(17) - v6.2(21)	Cisco OS v6.2(15) is no longer supported.	
	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T-2232TM-E	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(6)N1(1)		VSP G1000 & VSP only
	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(5), v7.0(0)N1(1) - v7.0(6)N1(1)		
UCS 6120XP, 6140XP, 6248up, 6296up	2.0(5a) - v2.0(5f), 2.1(1a) - v2.1(1f), v2.1(2a)			