



Solaris Support Matrix

Hitachi VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM

Note: Configurations added since the last matrix will be shown in red text.

Introduction

Use this interoperability matrix to check whether a proposed customer configuration is supported. Each tab contains a set of components that together comprise an Hitachi Vantara-supported solution. This includes operating system (OS) and maintenance release, host bus adapter (HBA), HBA driver, and storage area network (SAN) switches, both Fibre channel (FC) and Fibre channel over Ethernet (FCoE).

Note: The arrays supported now include the VSP F700, F900, G700, G900, F350, F370, G350, and G370.

Note on the 16 & 32 Gb Interfaces:

- The 32Gb interface is only available on the GX00 and FX00 arrays. It is supported with both 16 & 32Gb SFPs and operates at a maximum of 32Gbps.
- The VSP and HUS VM do not have 16Gb FC interfaces.
- With SVOS 7, for Direct connection to 16Gb or 32Gb FC you must set the storage port to Fabric = OFF and Connection Type P-to-P (Point to Point)

Note: The Hitachi FIVE FC HBA also has an alternate option of Fabric Emulation. When it is configured in this mode it should be treated as switch attached and the storage port should be set to Fabric = On and Connection Type = P-to-P

If a combination does not appear on the OS support matrix, the customer's Hitachi Vantara Sales Engineer (SE) or other Hitachi field service employee must submit an Interoperability Support Request in order to gain support for the new configuration.

Legal Disclaimer

This information is subject to change without notice. The information contained in this document is provided by Hitachi Vantara for general information purposes only and is based on information as of the date of distribution (indicated by the date above). Hitachi Vantara makes no express or implied warranties of any kind whatsoever regarding the contents of this Document or the performance of the products referred to in these documents and Hitachi Vantara expressly disclaims all warranties including, without limitation, the implied warranties of satisfactory quality, merchantability or fitness for a particular purpose, the statutory warranty against infringement, and any warranty of title. Hitachi Vantara will have no liability whatsoever for any direct loss or damage (but excluding any liability for death, personal injury or fraudulent misrepresentation) or for any indirect, special, incidental or consequential damages, including but not limited to loss of data or records, lost profits or other economic loss, arising out of or in connection with the use of this information even if such loss was foreseeable or Hitachi Vantara had been advised of the possibility of such loss.

VSP G1x00, F1500, Gxx0, Fxx0, VSP support for Oracle Solaris 11.4 (SPARC)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe16000, LPe16002, LPe16000B, LPe16002B	Bundled	
	LPe32000, LPe32002, LPe32002-M2-O, LPe32004	Bundled	
Oracle	7101674, 7101682	Bundled	
	7101684, 7101690	Bundled	
	7335908, 7115461	Bundled	
	7335902, 7115462	Bundled	
QLogic	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	Bundled	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2742-ORL, QLE2764	Bundled	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v8.2.1a	
	G610	v8.2.1a	
	G620, X6	v8.2.1a	
	G630	v8.2.1a	
Cisco	9132T	v8.3(1) - v8.3(2)	
	9148S, 9706	v8.3(1) - v8.3(2)	
	9250i	v8.3(1) - v8.3(2)	
	9396S	v8.3(1) - v8.3(2)	
	9710	v8.3(1) - v8.3(2)	
	9718	v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.3(1) - v8.3(2)	
	9718 (32Gb)	v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6740	v7.1.0	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
FCOE Storage Interface			
Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Oracle	7101674, 7101682	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
	7101684, 7101690	Bundled	
FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6740	v7.1.0	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	
10 Gbps iSCSI Storage Interface			
iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Oracle	7101674, 7101682	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
	7101684, 7101690	Bundled	
iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only

VSP G1x00, F1500, Gxx0, Fxx0, VSP support for Oracle Solaris 11.4 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe32000, LPe32002, LPe32002-M2-O, LPe32004	Bundled	
	OCe14102	Bundled	
Oracle	7335908, 7115461	Bundled	
	7335902, 7115462	Bundled	
QLogic	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	Bundled	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2742-ORL, QLE2764	Bundled	

FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	6505, 6510, 6520, 7840, DCX 8510	v8.1.2d, v8.1.2f - v8.1.2g, v8.2.0a - v8.2.0b	Brocade FOS v8.1.2e is not supported.
	G610	v8.2.1a	
	G620, X6	v8.2.1a	
	G630	v8.2.1a	
Cisco	9132T	v8.3(1) - v8.3(2)	
	9148S, 9706	v8.3(1) - v8.3(2)	
	9250i	v8.3(1) - v8.3(2)	
	9396S	v8.3(1) - v8.3(2)	
	9710	v8.3(1) - v8.3(2)	
	9718	v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.3(1) - v8.3(2)	
	9718 (32Gb)	v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6730	v4.1.3d	
	VDX 6740	v7.1.0	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	

FCOE Storage Interface			
Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe14102	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only

FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6740	v7.1.0	
Cisco	Nexus 5672up, 5672up-2248pq	v7.3(0)N1(1) - v7.3(1)N1(1)	

10 Gbps iSCSI Storage Interface			
iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Oracle	7101674, 7101682	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only
	7101684, 7101690	Bundled	

iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for Oracle Solaris 11.3 (SPARC)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe12000, LPe12002	Bundled	
	LPe16000, LPe16002, LPe16000B, LPe16002B	Bundled	
	LPe32000, LPe32002, LPe32002-M2-O, LPe32004	Bundled	
	OCe11102	Bundled	
Oracle	7101674, 7101682	Bundled	
	7101684, 7101690	Bundled	
	7335908, 7115461	Bundled	
	7335902, 7115462	Bundled	
QLogic	QLE2560, QLE2562	Bundled	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	Bundled	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2742-ORL, QLE2764	Bundled	
	QLE8360, QLE8362	Bundled	
Sun	SG-XPCIE1FC-EM8-Z	Bundled	
	SG-XPCIE2FC-EM8-Z		
	SG-XPCIE1FC-QF8-Z	Bundled	
	SG-XPCIE2FC-QF8-Z		
	SG-XPCIEFCGBE-Q8-N	Bundled	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5300, 7800, DCX, DCX-4s	v7.4.2d	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2g, v8.2.0a - v8.2.0b	Brocade FOS v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2g, v8.2.0a - v8.2.0b	Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2g, v8.2.0a - v8.2.0b	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
Cisco	9148, 9222i, 9506 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6730 (8G)	v4.1.2	
Cisco	9706 (FCoE), 9710 (FCoE), 9718 (FCoE)	v7.3(0)DY(1)	
	Nexus 5672up, 5672up-2248pq	v7.1(0)N1(1a) - v7.1(1)N1(1)	

FCOE Storage Interface			
Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCE11102	Bundled	VSP G1000, G800, G600, G400, G200 only
QLogic	QLE8360, QLE8362	Bundled	VSP G1000, G800, G600, G400, G200 only
FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6730	v4.1.2	VSP G1000 & VSP only
Cisco	Nexus 5672up, 5672up-2248pq	v7.1(0)N1(1a) - v7.1(1)N1(1)	VSP G1000 & VSP only

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for Oracle Solaris 11.3 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI, LPe1205-HI	Bundled	
	LPe16000, LPe16002, LPe16000B, LPe16002B	Bundled	
	LPe32000, LPe32002, LPe32002-M2-O, LPe32004	Bundled	
	OCe11102	Bundled	
Oracle	7101674, 7101682	Bundled	
	7101684, 7101690	Bundled	
	7335908, 7115461	Bundled	
	7335902, 7115462	Bundled	
Qlogic	QLE2560, QLE2562	Bundled	
	QLE2690, QLE2692, QLE2740, QLE2742, QLE2742-ORL, QLE2764	Bundled	
Sun	SG-XPCIE1FC-EM8-Z	Bundled	
	SG-XPCIE2FC-EM8-Z		
	SG-XPCIE1FC-QF8-Z	Bundled	
	SG-XPCIE2FC-QF8-Z		
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5300, 7800, DCX, DCX-4s	v7.4.2d	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2g, v8.2.0a - v8.2.0b	Brocade FOS v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2g, v8.2.0a - v8.2.0b	Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
	G620, X6	v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2g, v8.2.0a - v8.2.0b	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported.
Cisco	9148, 9222i, 9506 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9132T	v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	Cisco OS v6.2(15) is no longer supported.
	9718	v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.
	9706 (32Gb), 9710 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2)	
	9718 (32Gb)	v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(2)	Cisco OS v8.3(1) is no longer supported on the 9718.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6740	v6.0.1a	
Cisco	Nexus 5672up, 5672up-2248pq	v7.1(0)N1(1a) - v7.1(1)N1(1)	

FCOE Storage Interface			
Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCE11102	Bundled	VSP G1000, G800, G600, G400, G200 only
QLogic	QLE8360, QLE8362	Bundled	VSP G1000, G800, G600, G400, G200 only

FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6740	v6.0.1a	VSP G1000 & VSP only
Cisco	Nexus 5672up, 5672up-2248pq	v7.1(0)N1(1a) - v7.1(1)N1(1)	VSP G1000 & VSP only

10 Gbps iSCSI Storage Interface			
iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Oracle	7101684	Bundled	VSP G1x00, F1500, Gxx0, Fxx0 only

iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	VSP G1x00, F1500, Gxx0, Fxx0 only
Brocade	VDX 6730	v4.1.3a	
	VDX 6740	v6.0.1a	
Cisco	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v7.3(0)N1(1) - v7.3(1)N1(1)	

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for Oracle Solaris 11.2 (SPARC)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe16000, LPe16002, LPe16000B, LPe16002B	Bundled	
Oracle	7101674, 7101682	Bundled	
	7101684, 7101690	Bundled	
QLogic	QLE2560, QLE2562	Bundled	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	Bundled	
Sun	SG-XPCIE1FC-EM8-Z	Bundled	
	SG-XPCIE2FC-EM8-Z		
	SG-XPCIE1FC-QF8-Z	Bundled	
	SG-XPCIE2FC-QF8-Z		
	SG-XPCIEFCGBE-E8-N	Bundled	
	SG-XPCIEFCGBE-Q8-N	Bundled	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5300, 7800, DCX, DCX-4s	v7.4.2d	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d	
	G610	v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2g	Brocade FOS v8.1.0, v8.1.2c, and v8.1.2e are not supported.
	G620, X6	v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f - v8.1.2g	Brocade FOS v8.0.0, v8.1.0, v8.1.2c, and v8.1.2e are not supported.
Cisco	9148, 9222i, 9506 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6730 (8G)	v4.0.1	
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1), v7.3(0)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(5), v7.0(0)N1(1) - v7.0(6)N1(1)	Cisco Nexus 6001/6004 series requires v6.0(2)N1(2) and above. Nexus 6001T requires v6.0(2)N2(1) and above.

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for Oracle Solaris 11.2 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI, LPe1205-HI	Bundled	
	LPe16000, LPe16002, LPe16000B, LPe16002B	Bundled	
	Emulex LPm16002B-HI	Bundled	
	OCe10102	Bundled	
Oracle	7101674, 7101682	Bundled	
	7101684, 7101690	Bundled	
Qlogic	QLE2560, QLE2562	Bundled	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	Bundled	
Sun	SG-XPCIE1FC-EM8-Z	Bundled	
	SG-XPCIE2FC-EM8-Z		
	SG-XPCIE1FC-QF8-Z	Bundled	
	SG-XPCIE2FC-QF8-Z		
	SG-XPCIEFCGBE-E8-N	Bundled	
	SG-XPCIEFCGBE-Q8-N	Bundled	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5300, 7800, DCX, DCX-4s	v7.4.2d	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d	
Cisco	9148, 9222i, 9506 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1)), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6730 (8G)	v4.0.1	
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(5), v7.0(0)N1(1) - v7.0(6)N1(1)	Cisco Nexus 6001/6004 series requires v6.0(2)N1(2) and above. Nexus 6001T requires v6.0(2)N2(1) and above.
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(3a) - v2.2(3d)	

FCOE Storage Interface

Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
QLogic	QLE8360, QLE8362	Bundled	

FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T-2232TM-E	v7.0(0)N1(1), v7.0(1)N1(1) - v7.0(5)N1(1)	VSP G1000 & VSP only
	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1), v7.0(1)N1(1) - v7.0(5)N1(1)	VSP G1000 & VSP only

10 Gbps iSCSI Storage Interface

iSCSI Adapters			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCE11102	Bundled	
Oracle	7101684	v2.90.15.0	VSP G1x00, F1500, Gxx0, Fxx0 only

iSCSI Switches			
Manufacturer	Models	Firmware Versions	Notes
Any	Generic 10GigE Switch	Any 10GigE FW	
Brocade	VDX 6730	v4.1.2, v4.1.3a	
Cisco	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1) - v7.0(6)N1(1)	VSP G1x00, F1500, Gxx0, Fxx0 only

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for Oracle Solaris 11.1 (SPARC)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe12000, LPe12002, LPe1205, LPe1205-HI	Bundled	
	LPe16000, LPe16002, LPe16000B, LPe16002B	Bundled	
	OCe11102	Bundled	
Oracle	7101674, 7101682	Bundled	
Qlogic	QLE2560, QLE2562	Bundled	
	QLE2660, QLE2662, QLE2670, QLE2672, QME2662	Bundled	
Sun	SG-XPCIE1FC-EM8-Z	Bundled	
	SG-XPCIE2FC-EM8-Z		
	SG-XPCIE1FC-QF8-Z	Bundled	
	SG-XPCIE2FC-QF8-Z		
	SG-XPCIEFCGBE-E8-N	Bundled	
	SG-XPCIEFCGBE-Q8-N	Bundled	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5300, 7800, DCX, DCX-4s	v7.4.2d	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d	
Cisco	9148, 9222i, 9506 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1)), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6730 (8G)	v4.0.1	
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1), v7.3(0)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(5), v7.0(0)N1(1) - v7.0(6)N1(1)	Cisco Nexus 6001/6004 series requires v6.0(2)N1(2) and above. Nexus 6001T requires v6.0(2)N2(1) and above.

FCOE Storage Interface

Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	OCe11102	Bundled	

FCOE Switches			
Manufacturer	Models	Firmware Versions	Notes
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T-2232TM-E	v7.0(0)N1(1), v7.0(1)N1(1) - v7.0(5)N1(1)	VSP G1000 & VSP only
	Nexus 6001P, 6001p-2248pq, 6001T, 6004	v7.0(0)N1(1), v7.0(1)N1(1) - v7.0(5)N1(1)	VSP G1000 & VSP only

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for Oracle Solaris 11.1 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI, LPe1205-HI	Bundled	
	Emulex LPm16002B-HI	v2.90.15.0	
HPE	456972-B21	Bundled	
	LPe1205		
Qlogic	QLE2560, QLE2562	Bundled	
Sun	SG-XPCIE1FC-EM8-Z	Bundled	
	SG-XPCIE2FC-EM8-Z		
	SG-XPCIE1FC-QF8-Z	Bundled	
	SG-XPCIE2FC-QF8-Z		
	SG-XPCIEFCGBE-Q8-N	Bundled	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5300, 7800, DCX, DCX-4s	v7.4.2d	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d	
Cisco	9148, 9222i, 9506 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6730 (8G)	v4.0.1	
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(5), v7.0(0)N1(1) - v7.0(6)N1(1)	Cisco Nexus 6001/6004 series requires v6.0(2)N1(2) and above. Nexus 6001T requires v6.0(2)N2(1) and above.
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(3a) - v2.2(3d)	

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for Oracle Solaris 11 (SPARC)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe12000, LPe12002	Bundled	
Qlogic	QLE2560, QLE2562	Bundled	
	QLE8142	Bundled	
Sun	SG-XPCIE1FC-EM8-Z	Bundled	
	SG-XPCIE2FC-EM8-Z		
	SG-XPCIE1FC-QF8-Z	Bundled	
	SG-XPCIE2FC-QF8-Z		
	SG-XPCIEFCGBE-E8-N	Bundled	
	SG-XPCIEFCGBE-Q8-N	Bundled	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5300, 7800, DCX, DCX-4s	v7.4.2d	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d	
Cisco	9148, 9222i, 9506 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for Oracle Solaris 11 (X64)

FC Storage Interface			
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)			
Manufacturer	Models	Driver Versions	Notes
Emulex	LPe12000, LPe12002, LPe1205, LPe1205A-HI, LPe1205-HI	Bundled	
HPE	456972-B21 LPe1205	Bundled	
Qlogic	QLE2560, QLE2562	Bundled	
Sun	SG-XPCIE1FC-EM8-Z	Bundled	
	SG-XPCIE2FC-EM8-Z		
	SG-XPCIE1FC-QF8-Z SG-XPCIE2FC-QF8-Z	Bundled	
FC Switches			
Manufacturer	Models	Firmware Versions	Notes
Brocade	300, 5300, 7800, DCX, DCX-4s	v7.4.2d	
	6505, 6510, 6520, 7840, DCX 8510	v7.4.2d	
Cisco	9148, 9222i, 9506 (8Gb), 9513, 9513 (8Gb)	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1)	Cisco OS v6.2(15) is no longer supported.
	9148S, 9706	v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9250i	v6.2(5) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9396S	v6.2(13) - v6.2(13b), v6.2(17) - v6.2(27), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.
	9710	v6.2(1) - v6.2(13b), v6.2(17) - v6.2(27), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b)	Cisco OS v6.2(15) is no longer supported.

FCOE Switches (FCF mode)			
Manufacturer	Models	Firmware Versions	Notes
Brocade	VDX 6730 (8G)	v4.0.1	
Cisco	Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TME, 5596up	v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(8b), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	
	Nexus 5672up, 5672up-2248pq	v7.0(0)N1(1) - v7.0(6)N1(1), v7.1(0)N1(1a) - v7.1(1)N1(1)	
	Nexus 6001p-2248pq, 6001T, 6004	v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(5), v7.0(0)N1(1) - v7.0(6)N1(1)	Cisco Nexus 6001/6004 series requires v6.0(2)N1(2) and above. Nexus 6001T requires v6.0(2)N2(1) and above.
	UCS 6120XP, 6140XP, 6248up, 6296up	v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(3a) - v2.2(3d)	