



Windows Support Matrix

Hitachi VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM

Note: Configurations added since the last matrix will be shown in red text.

Introduction

Use this interoperability matrix to check whether a proposed customer configuration is supported. Each tab contains a set of components that together comprise an Hitachi Vantara-supported solution. This includes operating system (OS) and maintenance release, host bus adapter (HBA), HBA driver, and storage area network (SAN) switches, both Fibre channel (FC) and Fibre channel over Ethernet (FCoE).

Note: The arrays supported now include the VSP F700, F900, G700, G900, F350, F370, G350, and G370.

Note on the 16 & 32 Gb Interfaces:

- The 32Gb interface is only available on the GX00 and FX00 arrays. It is supported with both 16 & 32Gb SFPs and operates at a maximum of 32Gbps.
- The VSP and HUS VM do not have 16Gb FC interfaces.
- With SVOS 7, for Direct connection to 16Gb or 32Gb FC you must set the storage port to Fabric = OFF and Connection Type P-to-P (Point to Point)

Note: The Hitachi FIVE FC HBA also has an alternate option of Fabric Emulation. When it is configured in this mode it should be treated as switch attached and the storage port should be set to Fabric = On and Connection Type = P-to-P

If a combination does not appear on the OS support matrix, the customer's Hitachi Vantara Sales Engineer (SE) or other Hitachi field service employee must submit an Interoperability Support Request in order to gain support for the new configuration.

Legal Disclaimer

This information is subject to change without notice. The information contained in this document is provided by Hitachi Vantara for general information purposes only and is based on information as of the date of distribution (indicated by the date above). Hitachi Vantara makes no express or implied warranties of any kind whatsoever regarding the contents of this Document or the performance of the products referred to in these documents and Hitachi Vantara expressly disclaims all warranties including, without limitation, the implied warranties of satisfactory quality, merchantability or fitness for a particular purpose, the statutory warranty against infringement, and any warranty of title. Hitachi Vantara will have no liability whatsoever for any direct loss or damage (but excluding any liability for death, personal injury or fraudulent misrepresentation) or for any indirect, special, incidental or consequential damages, including but not limited to loss of data or records, lost profits or other economic loss, arising out of or in connection with the use of this information even if such loss was foreseeable or Hitachi Vantara had been advised of the possibility of such loss.

VSP G1x00, F1500, Gxx0, Fxx0, VSP support for Microsoft Windows Server 2019

| FC Storage Interface | | | |
|-------------------------------------------------------------|--------------------------------------------------|---------------------------------------------|---------------------------------------------------|
| Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA) | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Emulex | LPe16000, LPe16002, LPe16002B | v11.4.225.8009 | |
| | LPe31000, LPe31002, LPe31004, LPe32000, LPe32002 | v11.4.225.8009 | |
| | OCe14102 | v11.0.247.8000 | |
| | | | |
| HPE | 3530c | v11.4.225.8009 | |
| | SN1100E | v11.4.225.8009 | |
| | SN1200E | v11.4.225.8009 | |
| | SN1600E | v11.4.225.8009 | |
| | SN1000Q | v9.1.15.1 | |
| | SN1100Q | v9.1.15.1 | |
| | SN1600Q | v9.1.15.1 | |
| IBM | 00Y3337, 00Y3341 | v9.1.15.1 | |
| Qlogic | QLE2660, QLE2662, QLE2670, QLE2672, QME2662 | v9.1.15.1 | |
| | QLE2690, QLE2692, QLE2740, QLE2742, QLE2764 | v9.1.15.1 | |
| | QLE8360, QLE8362 | v9.1.11.3 | |
| FC Switches | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | 6505, 6510, 6520, 7840, DCX 8510 | v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1b | Brocade FOS v8.2.0, and v8.2.1 are not supported. |
| | G610 | v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1b | Brocade FOS v8.2.0, and v8.2.1 are not supported. |
| | G620, X6 | v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1b | Brocade FOS v8.2.0, and v8.2.1 are not supported. |
| | G630 | v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1b | Brocade FOS v8.2.0, and v8.2.1 are not supported. |
| Cisco | 9132T | v8.3(1) - v8.3(2) | |
| | 9148S, 9706 | v8.3(1) - v8.3(2) | |
| | 9250i | v8.3(1) - v8.3(2) | |
| | 9396S | v8.3(1) - v8.3(2) | |
| | 9710 | v8.3(1) - v8.3(2) | |
| | 9718 | v8.3(1) - v8.3(2) | |
| | 9706 (32Gb), 9710 (32Gb), 9718 (32Gb) | v8.3(1) - v8.3(2) | |
| FCOE Switches (FCF mode) | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | VDX 6740 | v6.0.1a | |
| Cisco | Nexus 5672up, 5672up-2248pq | v7.3(0)N1(1) - v7.3(1)N1(1) | |

| FCOE Storage Interface | | | |
|-----------------------------------------|-----------------------------|-----------------------------|----------------------|
| Converged Network Adapters (CNA) | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Emulex | OCE14102 | v11.0.247.8000 | |
| QLogic | QLE8360, QLE8362 | v9.1.11.3 | |
| FCOE Switches | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Any | Generic DCB IP Switch | Any DCB 10GigE FW | |
| Brocade | VDX 6740 | v6.0.1a | VSP G1000 & VSP only |
| Cisco | Nexus 5672up, 5672up-2248pq | v7.3(0)N1(1) - v7.3(1)N1(1) | |

| 10 Gbps iSCSI Storage Interface | | | |
|----------------------------------------|-----------------------|--------------------------|-----------------------------------|
| iSCSI Adapters | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Any | 10 GbE NIC | Bundled | |
| Emulex | OCE14102 | v11.4.1174.0 | VSP G1x00, F1500, Gxx0, Fxx0 only |
| QLogic | QLE8360, QLE8362 | v2.1.5.0 | |
| iSCSI Switches | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Any | Generic 10GigE Switch | Any 10GigE FW | VSP G1x00, F1500, Gxx0, Fxx0 only |

VSP G1x00, F1500, Gxx0, Fxx0, VSP support for Microsoft Windows Server 2016

| FC Storage Interface | | | |
|-------------------------------------------------------------|------------------------------------------------------------|------------------------------------------------------------------------------|--------------------------------------------------------------------------|
| Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA) | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Cisco | UCS 1225, 1225T, 1227, 1240, 1280, 1285 | v3.0.0.7 v3.0.0.8 | Must connect to a Cisco UCS or UCS Mini top of rack interconnect switch. |
| | UCS 1340, 1380 | v3.0.0.7 v3.0.0.8 | |
| Emulex | LPe12000, LPe12002, LPe1205 | v11.0.247.8000 v11.1.145.16 v11.2.139.0 | |
| | LPe16000, LPe16002, LPe16002B | v11.0.247.8000 v11.1.145.16 v11.2.139.0 v11.4.204.8 v12.0.193.13 | |
| | LPe31000, LPe31002, LPe31004, LPe32000, LPe32002 | v11.1.145.16 v11.2.139.0 v11.4.204.8 v12.0.193.13 | |
| | OCe11102 | v11.0.247.8000 v11.2.1135.0 | |
| | OCm14102 | v11.2.1135.0 | |
| HPE | 3530c | v11.1.145.16 v11.2.139.0 | |
| | 3820C | v7.14.15.0 | |
| | 3830C | v9.2.2.2.0 | |
| | QMH2682 | v9.2.4.2.1 | |
| | 456972-B21 | v11.1.145.16 | |
| | LPe1205 | | |
| | 534M, 534FLB | v7.14.15.0 | |
| | 536FLB | v7.14.15.0 | |
| | 554M, 554FLB | v11.1.145.16 | |
| | 630M, 630FLB | v7.14.15.0 | |
| | 650FLB, 650M | v11.1.145.16 | |
| | 659818-B21 | v11.1.145.16 | |
| | LPe1205A | | |
| | 81E, 82E, AJ762A, AJ762B, AJ763A, AJ763B, AH402A, AH403A | v11.0.247.8000 | |
| | 81Q, 82Q, AK344A, AJ764A | v9.1.15.1 | |
| | SN1000Q | v9.1.15.1 v9.2.3.20 | |
| | SN1100Q | v9.2.3.20 | |
| | SN1600Q | v9.2.3.20 | |
| | SN1100E | v11.0.247.8000 v11.1.145.16 v11.2.139.0 v11.4.204.8 v12.0.193.13 | |
| | SN1200E | v11.1.145.16 v11.2.139.0 v11.4.204.8 v12.0.193.13 | |
| SN1600E | v11.1.145.16 v11.2.139.0 v11.4.204.8 v12.0.193.13 | | |
| IBM | 42D0485, 42D0494 | v11.0.247.8000 | |
| | 42D0501, 42D0510 | v9.1.15.1 | |
| Qlogic | QLE2560, QLE2562 | v9.1.15.1 v9.2.3.20 | |
| | QLE2660, QLE2662, QLE2670, QLE2672, QME2662 | v9.1.15.1 v9.2.3.20 | |

| | | | |
|---------------------------------|--------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|
| | QLE2690, QLE2692, QLE2740, QLE2742, QLE2764 | v9.2.3.20 | |
| | QLE8360, QLE8362 | v9.1.11.3 v9.1.13.10 | |
| FC Switches | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | 300, 5300, 7800, DCX, DCX-4s | v7.4.2d | |
| | 6505, 6510, 6520, 7840, DCX 8510 | v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.1a - v8.2.1b | Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, and v8.2.1 are not supported. |
| | G610 | v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1b | Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported. |
| | G620, X6 | v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1b | Brocade FOS v8.0.0, v8.1.0, v8.1.2c, v8.1.2e, v8.2.0, and v8.2.1 are not supported. |
| | G630 | v8.2.0a - v8.2.0b, v8.2.1a - v8.2.1b | Brocade FOS v8.2.0, and v8.2.1 are not supported. |
| Cisco | 9148, 9222i, 9506 (8Gb), 9509 (8Gb), 9513, 9513 (8Gb) | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9132T | v8.2(1) - v8.2(2), v8.3(1) - v8.3(2) | |
| | 9148S, 9706 | v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(25), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9148T, 9396T | v8.3(1) - v8.3(2) | |
| | 9250i | v6.2(5) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9396S | v6.2(13) - v6.2(13b), v6.2(17) - v6.2(25), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9710 | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9718 | v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2) | |
| | 9706 (32Gb), 9710 (32Gb), 9718 (32Gb) | v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2), v8.3(1) - v8.3(2) | |
| FCOE Switches (FCF mode) | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | VDX 6730 | v4.1.3a | |
| | VDX 6740 | v6.0.1a | |
| Cisco | Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T-2232TM-E | v7.3(0)N1(1) - v7.3(1)N1(1) | |
| | Nexus 5672up, 5672up-2248pq | v7.3(0)N1(1) - v7.3(1)N1(1) | |
| | Nexus 6001P, 6001p-2248pq, 6001T, 6004 | v7.3(0)N1(1) - v7.3(1)N1(1) | |
| | UCS 6120XP, 6140XP, 6248up, 6296up | v3.1.2(b) - v3.1.2(e), v3.1.3(a) | |
| | UCS 6324 | v3.1.2(b) - v3.1.2(e), v3.1.3(a) | Cisco UCS Mini only |

| FCOE Storage Interface | | | |
|-----------------------------------------|---------------------------------------|------------------------------|----------------------|
| Converged Network Adapters (CNA) | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Emulex | OCe11102 | v11.0.247.8000 | |
| QLogic | QLE8360, QLE8362 | v9.1.11.3 | |
| FCOE Switches | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Any | Generic DCB IP Switch | Any DCB 10GigE FW | VSP G1000 & VSP only |
| Brocade | VDX 6740 | v6.0.1a | |
| Cisco | 9706 (FCoE), 9710 (FCoE), 9718 (FCoE) | v6.2(25), v8.1(1) - v8.1(1b) | |
| | Nexus 5672up, 5672up-2248pq | v7.3(0)N1(1) - v7.3(1)N1(1) | |

| 10 Gbps iSCSI Storage Interface | | | |
|----------------------------------------|--------------------------------------------------------------------------------------|----------------------------------------------------------|-----------------------------------|
| iSCSI Adapters | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Any | 10 GbE NIC | Bundled | VSP G1x00, F1500, Gxx0, Fxx0 only |
| Emulex | OCe14102 | v11.0.273.8008 | |
| Intel | 82599ES | v2.0.2.15 | |
| QLogic | QLE8440, QLE8442 | v7.14.1.1 | |
| iSCSI Switches | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Any | Generic 10GigE Switch | Any 10GigE FW | VSP G1x00, F1500, Gxx0, Fxx0 only |
| Cisco | Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T-2232TM-E | v5.2(1)N1(1) - v5.2(1)N1(9), v7.0(0)N1(1) - v7.0(8)N1(1) | |

VSP G1x00, F1500, Gxx0, Fxx0, VSP support for Microsoft Windows Server 2012 R2

| FC Storage Interface | | | | |
|-------------------------------------------------------------|--------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------|--|
| Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA) | | | | |
| Manufacturer | Models | Driver Versions | Notes | |
| Cisco | UCS 1225, 1225T, 1227, 1240, 1280, 1285 | v2.3.0.20 v2.4.0.8 v2.4.0.9 v2.4.0.11 v2.4.0.19 v2.4.0.20 | Must connect to a Cisco UCS or UCS Mini top of rack interconnect switch. | |
| | UCS 1340, 1380 | v2.4.0.8 v2.4.0.9 v2.4.0.11 v2.4.0.19 v2.4.0.20 | Must connect to a Cisco UCS top of rack interconnect switch. | |
| | UCS M81KR | v2.3.0.12 v2.4.0.9 v2.4.0.11 v2.4.0.19 | Must connect to a Cisco UCS top of rack interconnect switch. | |
| Emulex | LPe12000, LPe12002, LPe1205, LPe1205-HI | v2.74.214.004 v2.76.002.001 v2.76.003.001 v10.2.261.4 v10.2.370.8 v10.4.246.0 v10.6.114.0 v11.0.247.0 v11.1.145.16 v11.2.139.0 | | |
| | LPe16000, LPe16002, LPe16002B | v2.74.214.004 v2.76.002.001 v2.76.003.001 v10.1.1.26 v10.2.261.4 v10.2.370.8 v10.6.114.0 v11.0.247.0 v11.1.145.16 v11.2.139.0 v11.4.204.8 | | |
| | LPm16002B-HI | v2.76.002.001 | | |
| | LPe31000, LPe31002, LPe31004, LPe32000, LPe32002 | v11.0.235.9 v11.0.247.0 v11.2.139.0 v11.2.156.18 v11.4.204.8 | | |
| | OCe10102 | v2.76.002.001 v2.76.003.001 v10.4.246.0 | | |
| | OCe11102 | v2.76.002.001 v10.2.370.8 v10.6.114.0 | | |
| | Oce14102 | v10.4.246.0 v11.2.1135.0 | | |
| | OCm11104-F2-HI | v10.2.261.4 | | |
| | OCm14102 | v10.4.246.0 v11.2.1135.0 | | |
| | HPE | 451871-B21 | v9.1.11.28 | |
| | | QMH2562 | | |
| 456972-B21 | | v10.2.261.4 | | |
| LPe1205 | | v11.1.145.16 | | |
| 534M, 534FLB | | v7.14.15.0 | | |
| 536FLB | v7.14.15.0 | | | |

| | | | |
|-----|-------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------|--|
| | 554M, 554FLB | v2.74.014.001 v2.76.003.001 v10.2.261.4 v10.2.370.8 v10.4.246.0 v11.1.145.16 | |
| | 630M, 630FLB | v7.14.15.0 | |
| | 650FLB, 650M | v10.2.261.4 v10.2.370.8 v10.4.246.0 v11.1.145.16 | |
| | 651281-B21 QMH2572 | v9.1.11.28 | |
| | 659818-B21 LPe1205A | v2.76.003.001 v11.1.145.16 | |
| | 710608-B21 QMH2672 | v9.1.12.22 | |
| | 718203-B21 LPe1605 | v10.4.246.0 | |
| | 81E, 82E, AJ762A, AJ762B, AJ763A, AJ763B, AH402A, AH403A | v2.74.214.004 v2.76.002.001 v2.76.003.001 v10.2.261.4 v10.2.370.8 v10.4.246.0 v10.6.114.0 v11.0.247.0 v11.1.145.16 | |
| | 81Q, 82Q, AK344A, AJ764A | v9.1.11.24 v9.1.12.21 v9.1.12.22 | |
| | CN1200E | v10.4.246.0 | |
| | NC551i, NC551m | v2.74.014.001 | |
| | NC553i, NC553m, CN1100E | v2.74.014.001 v2.76.003.001 v10.4.246.0 v11.1.145.16 | |
| | SN1000E | v2.74.214.004 v2.76.002.001 | |
| | SN1000Q | v9.1.11.24 v9.1.12.21 v9.1.12.22 | |
| | SN1100E | v2.74.214.004 v2.76.002.001 v2.76.003.001 v10.2.261.4 v10.2.370.8 | |
| IBM | 42D0485, 42D0494 | v2.74.214.004 v2.76.002.001 v2.76.003.001 v10.2.261.4 v10.2.370.8 v10.4.246.0 v10.6.114.0 v11.0.247.0 v11.1.145.16 | |
| | 42D0501, 42D0510 | v9.1.11.24 v9.1.12.21 v9.1.12.22 | |
| | 69Y1942 | v9.1.11.28 v9.1.11.3 | |

| | | | |
|--------|---------------------------------------------|--------------------------------------------------------------------------------------------------------------------------|--|
| Qlogic | QLE2560, QLE2562 | v9.1.11.24 v9.1.11.28 v9.1.11.3 v9.1.12.21 v9.1.12.22 v9.1.13.20 v9.1.15.21 v9.2.3.20 | |
| | QLE2660, QLE2662, QLE2670, QLE2672, QME2662 | v9.1.10.26 v9.1.11.24 v9.1.11.28 v9.1.11.3 v9.1.12.21 v9.1.12.22 v9.1.15.21 v9.1.17.21 v9.2.3.20 | |
| | QLE2690, QLE2692, QLE2740, QLE2742, QLE2764 | v9.1.11.3 v9.1.15.21 v9.1.17.21 v9.2.3.20 | |
| | QLE8142 | v9.1.11.12 | |
| | QLE8260, QLE8262 | v9.1.12.10 | |
| | QLE8360, QLE8362 | v9.1.11.12 v9.1.11.16 v9.1.11.3 v9.1.12.10 v9.1.13.10 v9.2.3.20 | |
| | QME2572 | v9.1.11.24 | |

| FC Switches | | | |
|--------------------------|-------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------|
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | 300, 5300, 7800, DCX, DCX-4s | v7.4.2d | |
| | 6505, 6510, 6520, 7840, DCX 8510 | v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b | Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported. |
| | G610 | v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b | Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported. |
| | G620, X6 | v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b | Brocade FOS v8.0.0, v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported. |
| Cisco | 9148, 9222i, 9506 (8Gb), 9509 (8Gb), 9513, 9513 (8Gb) | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9132T | v8.2(1) - v8.2(2) | |
| | 9148S, 9706 | v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(25), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9250i | v6.2(5) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9396S | v6.2(13) - v6.2(13b), v6.2(17) - v6.2(25), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9710 | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9718 | v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | |
| | 9706 (32Gb), 9710 (32Gb), 9718 (32Gb) | v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | |
| FCOE Switches (FCF mode) | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | VDX 6730 (8G) | v4.0.1 | |
| Cisco | 9710 (FCoE), 9718 (FCoE) | v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) | |
| | Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up | v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1), v7.2(0)N1(1) - v7.2(1)N1(1), v7.3(0)N1(1) - v7.3(1)N1(1), v7.1(4)N1(1) | |
| | Nexus 5672up, 5672up-2248pq | v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1), v7.2(0)N1(1) - v7.2(1)N1(1), v7.3(0)N1(1) - v7.3(1)N1(1) | |
| | Nexus 7710 (FCoE) | v7.3(0)D1(1) - v7.3(1)D1(1) | |
| | UCS 6120XP, 6140XP, 6248up, 6296up | v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(3a) - v2.2(4c), v2.2(5b) - v2.2(5d), v2.2(6c) - v2.2(8f), v3.1(1e) - v3.1(1l), v3.1.2(b) - v3.1.2(e), v3.1.3(a) - v3.1.3(d) | |
| | UCS 6324 | v3.0(2c) - v3.0(2d), v3.1(1e) - v3.1(1l), v3.1.2(b) - v3.1.2(e), v3.1.3(a) - v3.1.3(d) | Cisco UCS Mini only |

| FCOE Storage Interface | | | |
|-----------------------------------------|--------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------|
| Converged Network Adapters (CNA) | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Brocade | 1860 | v3.2.3.1 v3.2.4.0 | |
| Cisco | UCS 1225, 1225T, 1227, 1240, 1280, 1285 | v2.3.0.20 v2.4.0.8 v2.4.0.9 v2.4.0.13 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | UCS 1340, 1380 | v2.4.0.8 v2.4.0.9 v2.4.0.11 v2.4.0.13 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | UCS M81KR | v2.4.0.9 v2.4.0.11 | Must connect to a Cisco UCS top of rack interconnect switch. |
| Emulex | Oce10102 | v2.76.002.001 v10.4.246.0 | |
| | Oce11102 | v10.0.720.0 v10.2.370.8 v10.6.114.0 | |
| | Oce14102 | v11.1.145.16 | |
| Qlogic | QLE8260, QLE8262 | v9.1.12.10 | |
| | QLE8360, QLE8362 | v9.1.11.3 v9.1.11.16 v9.1.12.10 v9.1.13.10 | |
| FCOE Switches | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Any | Generic DCB IP Switch | Any DCB 10GigE FW | VSP G1000 & VSP only |
| Brocade | DCX (FCoE) | v7.2.0a - v7.2.1b, v7.3.0 - v7.3.2 | VSP G1000 & VSP only |
| Cisco | 9132T | v8.2(1) - v8.2(2) | |
| | 9250i (FCoE) | v6.2(5) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9513 (FCoE) | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9706 (FCoE) | v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9710 (FCoE) | v6.2(7) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9718 (FCoE) | v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1a), v8.2(1) - v8.2(2) | VSP G1000 & VSP only |
| | Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T-2232TM-E | v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(7)N1(1), v7.1(0)N1(1a) - v7.2(1)N1(1) | VSP G1000 & VSP only |
| | Nexus 5672up, 5672up-2248pq | v7.1(0)N1(1a) - v7.2(1)N1(1), v7.3(0)N1(1) - v7.3(1)N1(1) | VSP G1000 & VSP only |
| | Nexus 7710 (FCoE) | v7.3(0)D1(1) - v7.3(1)D1(1) | VSP G1000 & VSP only |
| | UCS 6120XP, 6140XP, 6248up, 6296up | v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(3a) - v2.2(4c), v2.2(5b) - v2.2(5d), v2.2(6c) - v2.2(6g), v2.2(7b), v2.2(8a), v3.1(1e) | VSP G1000 & VSP only |
| Nexus 6001P, 6001p-2248pq, 6001T, 6004 | v6.0(2)N1(2), v6.0(2)N1(2a), v7.0(0)N1(1) - v7.0(7)N1(1) | VSP G1000 & VSP only | |

10 Gbps iSCSI Storage Interface

| iSCSI Adapters | | | |
|----------------|--------------------------------------------------------------------------------------|----------------------------------------------------------|-----------------------------------|
| Manufacturer | Models | Driver Versions | Notes |
| Any | 10 GbE NIC | Bundled | VSP G1x00, F1500, Gxx0, Fxx0 only |
| Emulex | OCe10102 | v10.4.245.0 v10.4.255.23 | |
| | OCe11102 | v10.2.478.1 | |
| | OCe14102 | v10.4.255.23 | |
| HPE | 530SFP+ | v7.10.30.0 v7.10.39.0 | |
| | 534FLB | v7.13.104.0 | |
| | 534FLR-SFP+ | v7.13.104.0 | |
| | 554FLR-SFP | v10.2.421.0 | |
| | CN1100R | v7.13.104.0 | |
| | CN1200E | v11.1.145.30 | |
| Intel | 82599ES | v2.0.2.15 | |
| QLogic | QLE8360, QLE8362 | v2.1.6.10 | |
| | QLE8440, QLE8442 | v7.12.0.0 v7.12.3.0 | |
| iSCSI Switches | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Any | Generic 10GigE Switch | Any 10GigE FW | VSP G1x00, F1500, Gxx0, Fxx0 only |
| Brocade | VDX 6730 | v4.1.2, v4.1.3a | |
| Cisco | Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T-2232TM-E | v5.2(1)N1(1) - v5.2(1)N1(9), v7.0(0)N1(1) - v7.0(8)N1(1) | |
| | Nexus 6001P, 6001p-2248pq, 6001T, 6004 | v7.0(0)N1(1) - v7.0(8)N1(1) | |

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for Microsoft Windows Server 2012

| FC Storage Interface | | | |
|-------------------------------------------------------------|-----------------------------------------|----------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------|
| Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA) | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Cisco | UCS 1225, 1225T, 1227, 1240, 1280, 1285 | v2.2.0.9 v2.2.0.17 v2.3.0.12 v2.4.0.8 | Must connect to a Cisco UCS or UCS Mini top of rack interconnect switch. |
| | UCS M81KR | v2.2.0.9 v2.2.0.17 v2.3.0.12 v2.4.0.8 | Must connect to a Cisco UCS top of rack interconnect switch. |
| Emulex | LPe12000, LPe12002, LPe1205, LPe1205-HI | v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.002.001 v10.2.261.4 v10.2.370.8 v10.4.246.0 | |
| | LPe16000, LPe16002, LPe16002B | v2.72.012.001 v2.74.014.001 v2.76.002.001 v2.76.003.001 v10.2.261.4 | |
| | Oce14102 | v10.4.246.0 | |
| | OCm11104-F2 | v2.72.012.001 v10.2.261.4 | |
| | OCm14102 | v10.4.246.0 | |
| HPE | 451871-B21 QMH2562 | v9.1.10.26 v9.1.10.27 v9.1.11.20 v9.1.11.23 v9.1.11.28 v9.1.12.22 | |
| | 456972-B21 LPe1205 | v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.002.001 v11.1.145.16 | |
| | 554M, 554FLB | v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.003.001 v10.2.261.4 v10.4.246.0 v11.1.145.16 | |
| | 650FLB, 650M | v10.2.261.4 v10.2.370.8 v10.4.246.0 v11.1.145.16 | |
| | 651281-B21 QMH2572 | v9.1.10.26 v9.1.10.27 v9.1.11.20 v9.1.11.23 v9.1.11.24 v9.1.11.28 v9.1.12.22 v9.1.15.21 | |
| | 659818-B21 LPe1205A | v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.002.001 v11.1.145.16 | |
| | | | |

| | | | |
|--------|-------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------|--|
| | 710608-B21 QMH2672 | v9.1.11.28 v9.1.12.22 | |
| | 81E, 82E, AJ762A, AJ762B, AJ763A, AJ763B, AH402A, AH403A | v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.002.001 v10.2.261.4 | |
| | 81Q, 82Q, AK344A, AJ764A | v9.1.10.25 v9.1.10.26 v9.1.10.27 v9.1.11.20 v9.1.11.23 v9.1.11.24 v9.1.11.28 v9.1.12.22 | |
| | NC551i, NC551m | v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.003.001 | |
| | NC553i, NC553m, CN1100E | v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.003.001 v10.2.261.4 v10.4.246.0 v11.1.145.16 | |
| | SN1000E | v2.72.012.001 v2.74.014.001 v2.76.002.001 | |
| | SN1000Q | v9.1.10.26 v9.1.11.24 v9.1.12.22 | |
| IBM | 42D0485, 42D0494 | v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.002.001 v10.2.261.4 | |
| | 42D0501, 42D0510 | v9.1.10.25 v9.1.10.26 v9.1.10.27 v9.1.11.20 v9.1.11.23 v9.1.12.22 | |
| | 46M6140 | v2.74.014.001 | |
| Qlogic | QLE2560, QLE2562 | v9.1.10.25 v9.1.10.26 v9.1.10.27 v9.1.11.20 v9.1.11.23 v9.1.11.24 v9.1.11.28 v9.1.12.22 | |
| | QLE2660, QLE2662, QLE2670, QLE2672, QME2662 | v9.1.10.26 v9.1.11.24 | |
| | QLE8142 | v9.1.10.15 v9.1.11.24 | |
| | QLE8360, QLE8362 | v9.1.10.18 | |
| | QME2572 | v9.1.11.24 | |

| FC Switches | | | |
|---------------------------------|-------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------|
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | 300, 5300, 7800, DCX, DCX-4s | v7.4.2d | |
| | 6505, 6510, 6520, 7840, DCX 8510 | v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b | Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported. |
| | G610 | v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b | Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported. |
| | G620, X6 | v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b | Brocade FOS v8.0.0, v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported. |
| Cisco | 9148, 9222i, 9506 (8Gb), 9509 (8Gb), 9513, 9513 (8Gb) | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9148S, 9706 | v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(25), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9250i | v6.2(5) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9396S | v6.2(13) - v6.2(13b), v6.2(17) - v6.2(25), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9710 | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9718 | v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | |
| | 9706 (32Gb), 9710 (32Gb), 9718 (32Gb) | v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | |
| FCOE Switches (FCF mode) | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | VDX 6730 (8G) | v4.0.1 | |
| Cisco | Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up | v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(9), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(7)N1(1), v7.1(0)N1(1a) - v7.2(1)N1(1) | |
| | Nexus 5672up, 5672up-2248pq | v7.0(0)N1(1) - v7.0(7)N1(1), v7.1(0)N1(1a) - v7.2(1)N1(1) | |
| | UCS 6120XP, 6140XP, 6248up, 6296up | v2.0(4a) - v2.0(4d), v2.0(5a) - v2.0(5f), v2.1(1a) - v2.1(1c), v2.1(2a) - v2.1(2d), v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(3a) - v2.2(4c) | |
| | UCS 6324 | v3.0(2c) - v3.0(2d) | Cisco UCS Mini only |

| FCOE Storage Interface | | | |
|----------------------------------|-----------------------------------------|------------------------------------|--------------------------------------------------------------|
| Converged Network Adapters (CNA) | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Cisco | UCS 1225, 1225T, 1227, 1240, 1280, 1285 | v2.2.0.17 v2.3.0.12 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | UCS M81KR | v2.2.0.17 v2.3.0.12 v2.4.0.8 | Must connect to a Cisco UCS top of rack interconnect switch. |
| Emulex | LPe16000, LPe16002, LPe16002B | v2.72.012.001 | |
| | OCe11102 | v10.0.720.0 | |
| | OCm11104-F2 | v2.72.012.001 | |
| HPE | NC553i, NC553m, CN1100E | v2.76.003.001 | |
| QLogic | QLE2670, QLE2672 | v9.1.10.26 | |
| | QLE8142 | v9.1.10.15 v9.1.11.24 | |
| | QLE8360, QLE8362 | v9.1.10.18 | |

| FCOE Switches | | | |
|----------------------|-------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------|-------------------------------------------|
| Manufacturer | Models | Firmware Versions | Notes |
| Any | Generic DCB IP Switch | Any DCB 10GigE FW | VSP G1000 & VSP only |
| Brocade | DCX (FCoE) | v7.2.0a - v7.2.1b, v7.3.0 - v7.3.2 | |
| Cisco | 9250i (FCoE) | v6.2(5) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9513 (FCoE) | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9706 (FCoE) | v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9710 (FCoE) | v6.2(7) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up | v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.2(1)N1(1) | |
| | UCS 6120XP, 6140XP, 6248up, 6296up | 2.0(5a) - v2.0(5f), 2.1(1a) - v2.1(1f), v2.1(2a) - v2.1(2d), v2.1(3a) - v2.1(3g), v2.2(3a) - v2.2(4c) | VSP G1000 & VSP only |

10 Gbps iSCSI Storage Interface

| iSCSI Adapters | | | |
|-----------------------|-----------------------|--------------------------|-----------------------------------|
| Manufacturer | Models | Driver Versions | Notes |
| Any | 10 GbE NIC | Bundled | VSP G1x00, F1500, Gxx0, Fxx0 only |
| iSCSI Switches | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Any | Generic 10GigE Switch | Any 10GigE FW | VSP G1x00, F1500, Gxx0, Fxx0 only |

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for Microsoft Windows Server 2008 R2 SP1 (X64)

| FC Storage Interface | | | |
|-------------------------------------------------------------|-----------------------------------------|------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA) | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Cisco | UCS 1225, 1225T, 1227, 1240, 1280, 1285 | v2.1.0.17 v2.1.0.18 v2.1.0.20 v2.1.0.25 v2.1.0.27 v2.1.0.31 v2.1.0.34 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | UCS 1340, 1380 | v2.1.0.27 v2.1.0.31 v2.1.0.34 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | UCS M71KR-Q, M72KR-Q | v9.1.8.27 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | UCS M81KR | v2.0.1.6 v2.1.0.11 v2.1.0.17 v2.1.0.18 v2.1.0.20 v2.1.0.25 v2.1.0.27 v2.1.0.31 v2.1.0.34 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | UCS P81E | v2.0.1.3 v2.1.0.11 v2.1.0.17 v2.1.0.20 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | Emulex | LPe12000, LPe12002, LPe1205, LPe1205-HI | v2.70.018 v2.70.019 v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.003.001 v10.2.261.4 v10.2.370.8 v10.4.246.0 v10.6.114.0 v11.1.145.16 |

| | | | |
|-----|-------------------------------|----------------------------------------------------------------------------------------------------------------------------------------|--|
| | LPe16000, LPe16002, LPe16002B | v2.70.018 v2.70.019 v2.72.012.001 v2.74.009.001 v2.74.014.001 v10.2.261.4 v10.2.370.8 v10.4.246.0 v11.1.145.16 | |
| | OCe10102 | v2.76.003.001 v10.0.720.0 | |
| | OCe11102 | v2.70.018 v2.76.003.001 v10.0.720.0 v10.2.370.8 | |
| | Oce14102 | v10.4.246.0 | |
| | OCm11104-F2 | v2.72.012.001 | |
| | OCm14102 | v10.4.246.0 | |
| HPE | 451871-B21 QMH2562 | v9.1.10.26 v9.1.11.20 v9.1.17.25 | |
| | 456972-B21 LPe1205 | v2.70.018 v2.70.019 v2.74.009.001 v2.74.014.001 v10.2.261.4 v10.4.246.0 v11.1.145.16 | |
| | 554M, 554FLB | v2.70.018 v2.70.019 v2.74.009.001 v2.74.014.001 v2.76.003.001 v10.2.261.4 v10.2.370.8 v10.4.246.0 v11.1.145.16 | |
| | 650FLB, 650M | v10.2.261.4 v10.2.370.8 v10.4.246.0 v11.1.145.16 | |
| | 651281-B21 QMH2572 | v9.1.10.26 v9.1.10.27 v9.1.11.20 v9.1.11.28 v9.1.17.25 | |

| | | |
|-------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------|--|
| 659818-B21 LPe1205A | v2.70.019 v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.002.001 v10.2.261.4 v10.4.246.0 v11.1.145.16 | |
| 710608-B21 QMH2672 | v9.1.11.28 v9.1.12.22 | |
| 81E, 82E, AJ762A, AJ762B, AJ763A, AJ763B, AH402A, AH403A | v2.70.018 v2.70.019 v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.003.001 v10.2.261.4 v10.2.370.8 v10.4.246.0 | |
| 81Q, 82Q, AK344A, AJ764A | v9.1.10.26 v9.1.10.28 v9.1.11.20 v9.1.11.24 v9.1.12.21 v9.1.12.22 | |
| CN1200E | v10.4.246.0 | |
| NC551i, NC551m | v2.70.018 v2.70.019 v2.74.009.001 v2.74.014.001 | |
| NC553i, NC553m, CN1100E | v2.70.018 v2.70.019 v2.74.009.001 v2.74.014.001 v2.76.003.001 v10.2.261.4 v11.1.145.16 | |
| SN1000E | v2.70.018 v2.70.019 v2.72.012.001 v2.74.009.001 v2.74.014.001 | |

| | | | |
|--------|------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------|--|
| | SN1000Q | v9.1.10.26 v9.1.11.20 v9.1.12.21 v9.1.17.25 | |
| | SN1100E | v10.4.246.0 | |
| IBM | 42D0485, 42D0494 | v2.70.018 v2.70.019 v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.003.001 v10.2.261.4 v10.2.370.8 | |
| | 42D0501, 42D0510 | v9.1.10.26 v9.1.10.27 v9.1.10.28 v9.1.11.20 v9.1.11.24 v9.1.12.21 v9.1.12.22 | |
| | 44X1940, 44X1942, 44X1945, 44X1947 | v9.1.10.26 v9.1.11.24 v9.1.12.21 | |
| | 46M6065 | v9.1.10.26 v9.1.11.20 | |
| | 46M6140 | v2.70.018 v2.74.014.001 | |
| QLogic | QLE2560, QLE2562 | v9.1.10.26 v9.1.10.28 v9.1.11.20 v9.1.11.24 v9.1.11.28 v9.1.12.21 v9.1.12.22 v9.1.13.20 v9.1.15.21 v9.1.17.21 v9.1.17.25 | |
| | QLE2660, QLE2662, QLE2670, QLE2672 | v9.1.10.26 v9.1.11.20 v9.1.11.28 v9.1.12.21 v9.1.13.20 v9.1.17.21 | |
| | QLE8152 | v9.1.10.18 | |
| | QLE8260, QLE8262 | v9.1.12.10 | |
| | QLE8360, QLE8362 | v9.1.12.10 | |
| | QME2572 | v9.1.11.28 | |

| FC Switches | | | |
|------------------------------------|---------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------|
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | 300, 5300, 7800, DCX, DCX-4s | v7.4.2d | |
| | 6505, 6510, 6520, 7840, DCX 8510 | v7.4.2d, v8.0.1 - v8.0.2f, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b | Brocade FOS v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported. |
| | G620, X6 | v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.1.2d, v8.1.2f, v8.2.0a - v8.2.0b | Brocade FOS v8.0.0, v8.1.0, v8.1.2c, v8.1.2e, and v8.2.0 are not supported. |
| Cisco | 9148, 9222i, 9506 (8Gb), 9509 (8Gb), 9513, 9513 (8Gb) | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9148S, 9706 | v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(25), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9250i | v6.2(5) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9396S | v6.2(13) - v6.2(13b), v6.2(17) - v6.2(25), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9710 | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9718 | v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | |
| FCOE Switches (FCF mode) | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | VDX 6730 (8G) | v4.0.1 | |
| Cisco | 9250i (FCoE) | v6.2(5) - v6.2(13b), v6.2(17) - v6.2(19), v7.3(0)D1(1) - v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9513 (FCoE) | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(19), v7.3(0)D1(1) - v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9706 (FCoE) | v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(19), v7.3(0)D1(1) - v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9710 (FCoE) | v6.2(7) - v6.2(13b), v6.2(17) - v6.2(19), v7.3(0)D1(1) - v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9718 (FCoE) | v7.3(0)D1(1) - v7.3(1)D1(1) | VSP G1000 & VSP only |
| | Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596T-2232TM-E, 5596up | v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(9), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1), v7.2(0)N1(1) - v7.2(1)N1(1), v7.3(0)N1(1) - v7.3(1)N1(1) | |
| | Nexus 5672up, 5672up-2248pq | v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1), v7.2(0)N1(1) - v7.2(1)N1(1), v7.3(0)N1(1) - v7.3(1)N1(1) | |
| | Nexus 6001p-2248pq, 6001T, 6004 | v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(8)N1(1) | Cisco Nexus 6001/6004 series requires v6.0(2)N1(2) and above. Nexus 6001T requires v6.0(2)N2(1) and above. |
| | Nexus 7710 (FCoE) | v7.3(0)D1(1) - v7.3(1)D1(1) | |
| UCS 6120XP, 6140XP, 6248up, 6296up | v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(3a) - v2.2(4c), v2.2(5b) - v2.2(5d), v2.2(6c) - v2.2(8f) | | |

| FCOE Storage Interface | | | |
|-----------------------------------------|-----------------------------------------|----------------------------------------------------------|--------------------------------------------------------------|
| Converged Network Adapters (CNA) | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Cisco | UCS 1225, 1225T, 1227, 1240, 1280, 1285 | v2.1.0.20 v2.1.0.25 v2.1.0.27 v2.4.0.13 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | UCS 1340, 1380 | v2.1.0.27 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | UCS M81KR | v2.1.0.20 v2.1.0.25 v2.1.0.27 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | UCS P81E | v2.1.0.17 v2.1.0.20 | Must connect to a Cisco UCS top of rack interconnect switch. |
| Emulex | LPe16000, LPe16002, LPe16002B | v2.72.012.001 | |
| | OCe10102 | v2.76.003.001 v10.0.720.0 | |
| | OCe11102 | v2.70.018 v2.76.003.001 v10.0.720.0 v10.2.370.8 | |
| QLogic | QLE2670, QLE2672 | v9.1.10.26 | |
| | QLE8142 | v9.1.9.15 | |
| | QLE8152 | v9.1.9.55 v9.1.10.18 | |
| | QLE8240, QLE8242 | v9.1.9.36 | |
| | QLE8260, QLE8262 | v9.1.12.10 | |
| | QLE8360, QLE8362 | v9.1.10.18 v9.1.11.16 v9.1.12.10 | |
| | | | |

| FCOE Switches | | | |
|------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------|
| Manufacturer | Models | Firmware Versions | Notes |
| Any | Generic DCB IP Switch | Any DCB 10GigE FW | VSP G1000 & VSP only |
| Brocade | DCX (FCoE) | v7.2.0a - v7.2.1b, v7.3.0 - v7.3.2 | |
| Cisco | 9250i (FCoE) | v6.2(5) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9513 (FCoE) | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9706 (FCoE) | v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) - v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9710 (FCoE) | v6.2(7) - v6.2(13b), v6.2(17) - v6.2(21), v7.3(0)D1(1) v7.3(1)D1(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9718 (FCoE) | v7.3(0)D1(1) - v7.3(1)D1(1) | VSP G1000 & VSP only |
| | Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T-2232TM-E | v5.1(3)N1(1) - v5.1(3)N2(1c), v5.2(1)N1(1) - v5.2(1)N1(9), v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(6), v7.0(0)N1(1) - v7.0(8)N1(1), v7.1(0)N1(1a) - v7.1(4)N1(1), v7.2(0)N1(1) - v7.2(1)N1(1), v7.3(0)N1(1) | |
| | Nexus 5672up, 5672up-2248pq | v7.1(0)N1(1a) - v7.1(4)N1(1), v7.2(0)N1(1) - v7.2(1)N1(1), v7.3(0)N1(1) | |
| | Nexus 6001P, 6001p-2248pq, 6001T, 6004 | v6.0(2)N1(2), v6.0(2)N1(2a), v6.0(2)N2(1) - v6.0(2)N2(4), v7.0(0)N1(1) - v7.0(7)N1(1) | |
| Nexus 7710 (FCoE) | v7.3(0)D1(1) - v7.3(1)D1(1) | | |
| UCS 6120XP, 6140XP, 6248up, 6296up | 2.0(5a) - v2.0(5f), 2.1(1a) - v2.1(1f), v2.1(2a) - v2.1(2d), v2.1(3a) - v2.1(3g), v2.2(1b) - v2.2(1d), v2.2(2c), v2.2(3a) - v2.2(4c), v2.2(5b) - v2.2(5d), v2.2(6c) - v2.2(6g) | | |

10 Gbps iSCSI Storage Interface

| iSCSI Adapters | | | |
|----------------|------------------|--------------------------|-----------------------------------|
| Manufacturer | Models | Driver Versions | Notes |
| Any | 10 GbE NIC | Bundled | VSP G1x00, F1500, Gxx0, Fxx0 only |
| HPE | 554FLR-SFP | v10.2.421.0 | |
| | 530SFP+ | v7.10.30.0 | |
| QLogic | QLE8240, QLE8242 | v2.1.6.10 v5.3.29.801 | |
| | QLE8440, QLE8442 | v2.1.6.10 | |

| iSCSI Switches | | | |
|----------------|--------------------------------------------------------------------------------------------|-----------------------------|-----------------------------------|
| Manufacturer | Models | Firmware Versions | Notes |
| Any | Generic 10GigE Switch | Any 10GigE FW | VSP G1x00, F1500, Gxx0, Fxx0 only |
| Brocade | VDX 6730 | v4.1.2, v4.1.3a | |
| Cisco | Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T-2232TM-E | v7.0(0)N1(1) - v7.0(8)N1(1) | |
| | Nexus 6001P, 6001p-2248pq, 6001T, 6004 | v7.0(0)N1(1) - v7.0(8)N1(1) | |

VSP G1x00, F1500, Gxx0, Fxx0, VSP, HUS VM support for Microsoft Windows Server 2008 SP2 (X64)

| FC Storage Interface | | | |
|--------------------------------------------------------------------|----------------------------------------------------------|-----------------------------------------------------------------------------------------|--------------------------------------------------------------|
| Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA) | | | |
| Manufacturer | Models | Driver Versions | Notes |
| Cisco | UCS 1240, 1280 | v2.1.0.20 | Must connect to a Cisco UCS top of rack interconnect switch. |
| | UCS M81KR | v2.1.0.11 v2.1.0.17 | Must connect to a Cisco UCS top of rack interconnect switch. |
| Emulex | LPe12000, LPe12002, LPe1205, LPe1205A-HI, LPe1205-HI | v2.70.018 v2.70.019 v2.72.012.001 v2.74.009.001 v2.74.014.001 | |
| | LPe16000, LPe16002, LPe16002B | v2.70.018 v2.70.019 v2.74.009.001 v10.2.261.4 | |
| | OCe11102 | v2.70.018 | |
| | Oce14102 | v10.4.246.0 | |
| | OCm11104-F2 | v2.72.012.001 | |
| | OCm14102 | v10.4.246.0 | |
| HPE | 451871-B21 QMH2562 | v9.1.10.26 v9.1.10.27 v9.1.11.20 v9.1.11.28 | |
| | 456972-B21 LPe1205 | v2.70.018 v2.70.019 v2.74.009.001 v2.74.014.001 v11.1.145.16 | |
| | 554M, 554FLB | v2.70.018 v2.70.019 v2.74.009.001 v2.74.014.001 v10.2.261.4 v11.1.145.16 | |
| | 650FLB, 650M | v10.4.246.0 v11.1.145.16 | |
| | 651281-B21 QMH2572 | v9.1.10.26 v9.1.10.27 v9.1.11.20 | |
| | 659818-B21 LPe1205A | v2.72.012.001 v2.74.009.001 v2.74.014.001 v2.76.002.001 v11.1.145.16 | |
| | 81E, 82E, AJ762A, AJ762B, AJ763A, AJ763B, AH402A, AH403A | v2.70.018 v2.70.019 v2.72.012.001 v2.74.009.001 v2.74.014.001 | |
| | 81Q, 82Q, AK344A, AJ764A | v9.1.10.26 v9.1.10.27 v9.1.11.20 v9.1.12.22 | |
| | NC551i, NC551m | v2.70.018 v2.70.019 v2.74.009.001 v2.74.014.001 | |
| | NC553i, NC553m, CN1100E | v2.70.018 v2.70.019 v2.74.009.001 v2.74.014.001 | |

| | | | |
|--------|------------------------------------|---------------------------------------------------------------------------|--|
| | SN1000E | v2.70.018 v2.70.019 v2.74.009.001 | |
| IBM | 42D0485, 42D0494 | v2.70.018 v2.70.019 v2.72.012.001 v2.74.009.001 v2.74.014.001 | |
| | 42D0501, 42D0510 | v9.1.10.26 v9.1.10.27 v9.1.11.20 v9.1.12.22 | |
| | 44X1940, 44X1942, 44X1945, 44X1947 | v9.1.10.26 | |
| QLogic | QLE2560, QLE2562 | v9.1.10.26 v9.1.10.27 v9.1.11.20 v9.1.12.22 v9.1.13.20 | |

| FC Switches | | | |
|--------------|-------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------|-------------------------------------------|
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | 300, 5300, 7800, DCX, DCX-4s | v7.4.2d | |
| | 6505, 6510, 6520, 7840, DCX 8510 | v7.4.2d | |
| Cisco | 9148, 9222i, 9506 (8Gb), 9509 (8Gb), 9513, 9513 (8Gb) | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1) - v7.3(1)DY(1) | Cisco OS v6.2(15) is no longer supported. |
| | 9148S, 9706 | v6.2(9a) - v6.2(13b), v6.2(17) - v6.2(25), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9250i | v6.2(5) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9396S | v6.2(13) - v6.2(13b), v6.2(17) - v6.2(25), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9710 | v6.2(1) - v6.2(13b), v6.2(17) - v6.2(25), v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | Cisco OS v6.2(15) is no longer supported. |
| | 9718 | v7.3(0)D1(1) - v7.3(1)D1(1), v7.3(0)DY(1), v8.1(1) - v8.1(1b), v8.2(1) - v8.2(2) | |

| FCOE Switches (FCF mode) | | | |
|--------------------------|--------------------------------------------------------------------------------------|-----------------------------------------------------------|-------|
| Manufacturer | Models | Firmware Versions | Notes |
| Brocade | VDX 6730 (8G) | v4.0.1 | |
| Cisco | 9250i (FCoE), 9513 (FCoE) | v7.3(0)D1(1) - v7.3(1)D1(1) | |
| | Nexus 5010-2232pp, 5020, 5548p, 5548up, 5548up-2232pp, 5596up, 5596T, 5596T-2232TM-E | v5.1(3)N1(1) - v5.1(3)N2(1c), v7.3(0)N1(1) | |
| | Nexus 5672up, 5672up-2248pq | v7.0(0)N1(1) - v7.0(7)N1(1), v7.1(0)N1(1a) - v7.2(1)N1(1) | |
| | UCS 6120XP, 6140XP, 6248up, 6296up | v2.0(1q), v2.0(1t), v2.0(3a), v2.1(1a) | |

| FCOE Storage Interface | | | |
|----------------------------------|-----------------------|------------------------------------|----------------------|
| Converged Network Adapters (CNA) | | | |
| Manufacturer | Models | Driver Versions | Notes |
| QLogic | QLE8142 | v9.1.9.15 | |
| FCOE Switches | | | |
| Manufacturer | Models | Firmware Versions | Notes |
| Any | Generic DCB IP Switch | Any DCB 10GigE FW | VSP G1000 & VSP only |
| Brocade | DCX (FCoE) | v7.2.0a - v7.2.1b, v7.3.0 - v7.3.2 | |