



Hitachi NAS Platform (HNAS) Support Matrix

Hitachi Virtual Storage Platform 5x00, G1500, F1500, G1000, Gxx0, Fxx0

Note: Configurations added since the last matrix will be shown in red text.

Introduction

Use this

interoperability matrix to check whether a proposed customer configuration is supported. Each tab contains a set of components that together comprise an HDS-supported solution. This includes HNAS platform model, and NASOS version and storage area network (SAN) switches, both Fibre channel (FC) and Fibre channel over Ethernet (FCoE).

In the sample datapath below, a customer configuration is supported if that particular HNAS platform and NASOS version, switch and switch firmware combinations both appear on the support matrix.

For example: HNAS 4040 loaded with NASOS 11.2.3319.16 connected to a Brocade DCX 6510 switch with FOS v7.2.1 installed.

If a combination does not appear on the OS support matrix, the customer's Hitachi Data Systems Sales Engineer (SE) or other HDS field service employee must submit an Interoperability Support Request in order to gain support for the new configuration.

Note that in some cases a component (HNAS OS, switch or switch firmware version) may no longer be supported (end of service life, EOSL) in which case the customer should choose components that are already supported from the matrix. Click on a tab to view associated components.

Gxx0 refers to : G900,G800,G700, G600, G400,G370,G350 and G200

Fxx0 refers to : F900,F800, F700,F600, F400,F370,F350

G1x00 refers to : G1500 and G1000

5x00 refers to: 5500, 5500H, 5100, 5100H

Legal Disclaimer

This information is subject to change without notice. The information contained in this document is provided by HDS for general information purposes only and is based on information as of the date of distribution (indicated by the date above). HDS makes no express or implied warranties of any kind whatsoever regarding the contents of this Document or the performance of the products referred to in these documents and HDS expressly disclaims all warranties including, without limitation, the implied warranties of satisfactory quality, merchantability or fitness for a particular purpose, the statutory warranty against infringement, and any warranty of title. HDS will have no liability whatsoever for any direct loss or damage (but excluding any liability for death, personal injury or fraudulent misrepresentation) or for any indirect, special, incidental or consequential damages, including but not limited to loss of data or records, lost profits or other economic loss, arising out of or in connection with the use of this information even if such loss was foreseeable or HDS had been advised of the possibility of such loss.

Storage (Hitachi Virtual Storage Platform 5x00 G1x00, F1500, Gxx0, Fxx0) Switch Firmware interoperability

VSP G1x00, F1500, G800, G600, G400, G200							
HNAS Model					NASOS		
4100	4080	4060	4040	30x0*	Versions	Notes	
Y	Y	Y	Y	Y	NASOS 12.7.4221.01		
Y	Y	Y	Y	Y	NASOS 12.7.4221.09		
Y	Y	Y	Y	Y	NASOS 12.7.4221.12		
Y	Y	Y	Y	Y	NASOS 13.0.4323.02		
Y	Y	Y	Y	Y	NASOS 13.0.4323.02a		
Y	Y	Y	Y	Y	NASOS 13.0.4323.05		
Y	Y	Y	Y	Y	NASOS 13.0.4323.08		
Y	Y	Y	Y	Y	NASOS 13.1.4428.02		
Y	Y	Y	Y	Y	NASOS 13.2.4527.01		
Y	Y	Y	Y	N	NASOS 13.3.4633.02		
VSP 5x00, G/F900, G/F700, G/F370, G/F350							
4100	4080	4060	4040	30x0*	Versions	Notes	
Y	Y	Y	N	N	NASOS 13.3.4633.02	VSP 5x00 not supported for this NAOS version	
Y	Y	Y	N	N	NASOS 13.5.5336.00		
Host Bus Adapters (FC-HBA)/Converged Network Adapters (CNA)							
Manufacturer		Models		Driver Versions	Notes		
Hitachi		Integrated FC		Bundled			
FC Switches							
Manufacturer		Models		Firmware Versions	Notes		
Brocade		300, 5100, 5300, 7800, DCX, DCX-4s		v6.4.0 - v6.4.3h, v7.0.0 - v7.0.2e, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a			
		6505, 6510, 6520, 8510		v7.0.0 - v7.0.2e, v7.1.0a - v7.1.2b, v7.2.0a - v7.2.1g, v7.3.0 - v7.3.2b, v7.4.0 - v7.4.2a, v8.0.1 - v8.0.2e, v8.1.0a - 8.1.2b			
		G620, X6		v8.0.1 - v8.0.2e, v8.1.0a - v8.1.2b, v8.2.0a - v8.2.0b	Brocade FOS v8.0.0 is not supported.		
Cisco		9222i, 9506 (4Gb), 9506 (8Gb), 9509 (4Gb), 9509 (8Gb), 9513, 9513 (8Gb), 9148		v5.2(1) - v5.2(8h), v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23)	Cisco OS v5.2(8) is not supported		
		9250i		v6.2(5) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1) - v7.3(1)D1(1)			
		9396S		v6.2(13) - v6.2(13b), v6.2(17) - v6.2(23)			
		9710		v6.2(1) - v6.2(13b), v6.2(17) - v6.2(23), v7.3(0)D1(1)			
		9718		v7.3(0)D1(1) - v7.3(1)D1(1), 8.3(2)			
FCOE Switches (FCF mode)							
Manufacturer		Models		Firmware Versions	Notes		
Brocade		VDX 6730 (8G)		v4.0.1			
		VDX 6740 (8G),		v5.0.1a, v6.0.1a			
ISVs							
For complete list of ISV certified product, refer to Alliance-Central pages in sharepoint							

Legacy versions below Recommended GA firmwares

HNAS Model					NASOS	
4100	4080	4060	4040	30x0*	Versions	Notes
N	N	N	N	Y	NASOS 10.2.3072.02	
N	N	N	N	Y	NASOS 10.2.3072.06	
N	N	N	N	Y	NASOS 10.2.3073.04	
N	N	N	N	Y	NASOS 10.2.3073.05	
N	N	N	N	Y	NASOS 10.2.3074.03	
N	N	N	N	Y	NASOS 11.0.3124.01	
N	N	N	N	Y	NASOS 11.1.3225.02	
N	N	N	N	Y	NASOS 11.1.3225.81	
Y	Y	Y	N	N	NASOS 11.1.3250.10	
Y	Y	Y	Y	Y	NASOS 11.2.3319.14	
Y	Y	Y	Y	Y	NASOS 11.2.3319.15	
Y	Y	Y	Y	Y	NASOS 11.2.3319.16	
Y	Y	Y	Y	Y	NASOS 11.2.3319.19	
Y	Y	Y	Y	Y	NASOS 11.2.3319.20	
Y	Y	Y	Y	Y	NASOS 11.3.3434.03	
Y	Y	Y	Y	Y	NASOS 11.3.3450.10	
Y	Y	Y	Y	Y	NASOS 11.3.3450.14	
Y	Y	Y	Y	Y	NASOS 11.3.3450.15	
Y	Y	Y	Y	Y	NASOS 11.3.3450.16	
Y	Y	Y	Y	Y	NASOS 11.3.3450.21	
Y	Y	Y	Y	Y	NASOS 12.0.3528.04	
Y	Y	Y	Y	Y	NASOS 12.1.3613.06	
Y	Y	Y	Y	Y	NASOS 12.1.3613.10	
Y	Y	Y	Y	Y	NASOS 12.1.3613.16	
Y	Y	Y	Y	Y	NASOS 12.2.3719.07	
Y	Y	Y	Y	Y	NASOS 12.2.3753.08	
Y	Y	Y	Y	Y	NASOS 12.3.3826.03	
Y	Y	Y	Y	Y	NASOS 12.3.3826.03a	
Y	Y	Y	Y	Y	NASOS 12.3.3826.03c	
Y	Y	Y	Y	Y	NASOS 12.3.3826.07	
Y	Y	Y	Y	Y	NASOS 12.3.3826.11	
Y	Y	Y	Y	Y	NASOS 12.3.3826.12	
Y	Y	Y	Y	Y	NASOS 12.3.3826.14	
Y	Y	Y	N	N	NASOS 12.4.3924.11	
Y	Y	Y	Y	Y	NASOS 12.4.3924.14	
Y	Y	Y	Y	Y	NASOS 12.4.3924.15	
Y	Y	Y	Y	Y	NASOS 12.4.3924.19	
Y	Y	Y	Y	Y	NASOS 12.5.4038.03	
Y	Y	Y	Y	Y	NASOS 12.5.4038.06	
Y	Y	Y	Y	Y	NASOS 12.5.4038.09	